IEEE P1003.2 Draft 11.2 – September 1991

Copyright © 1991 by the
Institute of Electrical and Electronics Engineers, Inc.
345 East 47th Street
New York, NY 10017, USA
All rights reserved as an unpublished work.

This is an unapproved and unpublished IEEE Standards Draft, subject to change. The publication, distribution, or copying of this draft, as well as all derivative works based on this draft, is expressly prohibited except as set forth below.

Permission is hereby granted for IEEE Standards Committee participants to reproduce this document for purposes of IEEE standardization activities only, and subject to the restrictions contained herein.

Permission is hereby also granted for member bodies and technical committees of ISO and IEC to reproduce this document for purposes of developing a national position, subject to the restrictions contained herein.

Permission is hereby also granted to the preceding entities to make limited copies of this document in an electronic form only for the stated activities.

The following restrictions apply to reproducing or transmitting the document in any form: 1) all copies or portions thereof must identify the document's IEEE project number and draft number, and must be accompanied by this entire notice in a prominent location; 2) no portion of this document may be redistributed in any modified or abridged form without the prior approval of the IEEE Standards Department.

Other entities seeking permission to reproduce this document, or any portion thereof, for standardization or other activities, must contact the IEEE Standards Department for the appropriate license.

Use of information contained in this unapproved draft is at your own risk.

IEEE Standards Department
Copyright and Permissions
445 Hoes Lane, P.O. Box 1331
Piscataway, NJ 08855-1331, USA
+1 (908) 562-3800
+1 (908) 562-1571 [FAX]

Annex F
(informative)

Sample National Profile

Editor's Note: All uses of the term ''character set'' this annex have been changed to ''coded character set'' without further diff marks.

This annex is an example of a country's needs with respect to this standard and how those needs relate to other international standards as well as national standards. The example provided is included here for informative purposes and is not a formal standard in the country in question. It is provided by the Danish Standards Association [1] and is as accurate as possible with regards to Danish needs.

F.1 (Example) Danish National Profile

This is the definition of the Danish Standards Association POSIX.2 profile. The subset of conforming implementations that provide the required characteristics below is referred to as conforming to the ''Danish Standards Association (DS) Environment Profile'' for this standard.

This profile specifies the following requirements on implementations:

(1) In POSIX.2 section 2.13.1, the limit {COLL_WEIGHTS_MAX} shall be provided with a value of 4. All other limits shall conform to at least the minimum values shown in Table 2-16.

(2) The following options shall be supported according to POSIX.2 section 2.13.2:

---

1) Further information may be obtained from the Danish Standards Association, Attn: S142u22A8 Baunegaardsvej 73, DK-2900 Hellerup, Denmark; FAX: +45 39 77 02 02; Email: `u22a8@dkuug.dk`

The data is also available electronically by anonymous FTP or FTAM at the site `dkuug.dk` in the directory `i18n`, where some other example national profiles, locales, and *charmaps* may also be found. They are also available by an archive server reached at `archive@dkuug.dk`; use '`Subject: help`'' for further information.

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

POSIX2_C_BIND	Optional.
POSIX2_C_DEV	Optional.
POSIX2_FORT_DEV	Optional.
POSIX2_FORT_RUN	Optional.
POSIX2_LOCALEDEF	Required; the system shall support the creation of locales as described in 4.35.
POSIX2_SW_DEV	Optional.

F.1.1 Danish Locale Model

Editor's Note: This subclause is offered as rationale for the current state of this example annex. It will not necessarily appear in this form in any final version of the annex.

Creating a national locale for Denmark has been a quite elaborate effort. Time and again, we thought we had reached an agreement on the locale, but then some aspect disrupted the entire work, and we more or less had to start all over.

We think we have identified the cause of these problems to a general uncertainty regarding the exact purpose of a ''national'' locale. If we look at the Danish situation (which we know pretty well by now), we have identified several levels of locales, depending on the ''complexity'' of the collating sequence (or more generally sorting different kinds of text):

(1) *Byte/machine level.* Here everything is sorted according to the character's byte value.

(2) *Character/utility level.* Here we want to work almost on the same level as (1), i.e., character by character, but obeying a (simple) collating sequence that ensures that, for example, upper- and lowercase letters are equivalent, or that national characters are sorted correctly. The characters still do not have any ''implicit'' meaning, and the comparison of two strings is still deterministic; i.e., strings that are different at level 1 are still different at level 2.

(3) *Text/application level.* Here we want to be able to search in text looking for specific words or items. The comparison is still performed on a character-by-character basis, but possibly ignoring some characters that are not important, and determinism is not important either.

(4) *Semantic/dictionary/library/phone-book level.* Entire words like ''the'' are omitted from comparisons; maybe soundex is required. This probably requires specially developed software.

Our problem has been the conflicting requirements from each of these levels, which we optimistically have tried to combine into a single national locale (ignoring level 4, however). The POSIX Locale is aimed at level 2; i.e., at a rather low level. Many of our attempts to write a national Danish locale have failed because we have actually tried to write a level 3 locale, and finding that it did not work as

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

an alternative to the default POSIX locale at level 2.

The locale we now provide is the final compromise between level 2 and level 3, by taking our latest attempt aimed at level 3, and make the comparison completely deterministic, and thus bring it down to level 2.

We also have found that we may need to include some more information in the identification of a specific locale than just the country code, the language code, and the coded character set, since what we have had most problems with was the purpose or scope of a specific locale; i.e., is it just a nationalized version of the POSIX Locale (e.g., extended with <ae>, <o/>, and <aa> at the proper positions), is it aimed at text search (ignoring certain characters), or is it on an even higher level? Many such alternative locales would certainly be useful for various classes of problems or applications, so our model for the locale name identification string includes a *<version>* parameter.

We hope by providing these comments to have clarified our intention with the locale definitions to save other countries from doing our mistakes all over.

F.2 Locale String Definition Guideline

The following guideline is used for specifying the locale identification string: [2)]

> "%2.2s_%2.2s.%s,%s", *<language>*, *<territory>* , *<coded-character-set>*, *<version>*

where *<language>* shall be taken from ISO 639 {B1} and *<territory>* shall be the two-letter country code of ISO 3166 {B4}, if possible. The *<language>* shall be specified with lowercase letters only, and the *<territory>* shall be specified in uppercase letters only. An optional *<coded-character-set>* specification may follow after a <period> for the name of the coded character set; if just a numeric specification is present, this shall represent the number of the international standard describing the coded character set. If the *<coded-character-set>* specification is not present, the encoded character-set-specific locale shall be determined by the **CHARSET** environment variable, and if this is unset or null, the encoding of ISO 8859-1 {5} shall be assumed. A parameter specifying a *<version>* of the locale may be placed after the optional *<coded-character-set>* specification, delimited by <comma>. This may be used to discriminate between different cultural needs; for instance, dictionary order versus a more systems-oriented collating order.

---

2) The guideline was inspired by the *X/Open Portability Guide* {B31}.

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

F.3 Scope of Danish National Locale

This national locale covers the Danish language in Denmark. In addition, Faroese and Greenlandic LC_TIME and LC_MESSAGES specifications have been defined; the rest of the Danish national locale shall be used for these locales as well.

This locale is designed to be coded character-set independent. It completely specifies the behavior of systems based on ISO/IEC 10646 {B11} (with ISO 6429 {B5} control character encoding) together with many 7-bit and 8-bit encoded character sets, including ISO 8859 character sets and major vendor-specific 8-bit character sets (with ISO 6429 {B5} or ISO/IEC 646 {1} control character encoding when applicable).

This locale is portable as long as the character naming in the charmap description file ISO_10646 for ISO/IEC 10646 {B11} is followed. Examples of such charmap files for ISO/IEC 10646 {B11} and ISO 8859-1 {5} are shown in F.5.1 and F.5.2.

The collating sequence is completely deterministic and is aimed for usage in system tools. Other Danish collation sequences with nondeterministic properties, which may be needed for some application programs, are not covered by this locale.

The LC_TYPE category of the locale is quite general and may be useful for other locales; also the LC_COLLATE category, though specifically Danish, may be a good template from which to generate other locales.

Following the preceding guidelines for locale names, the national Danish locale string shall be:

da_DK

F.3.1 da_DK — (Example) Danish National Locale

```
escape_char     /
comment_char    %
% Danish example national locale for the language Danish
% Source: Danish Standards Association
% Revision 1.7 1991-05-07

LC_CTYPE

digit   <0>;<1>;<2>;<3>;<4>;<5>;<6>;<7>;<8>;<9>

xdigit  <0>;<1>;<2>;<3>;<4>;<5>;<6>;<7>;<8>;<9>;/
        <A>;<B>;<C>;<D>;<E>;<F>;<a>;<b>;<c>;<d>;<e>;<f>

blank   <SP>;<HT>;<NS>

space   <SP>;<LF>;<VT>;<FF>;<CR>;<HT>;<NS>

upper   <A>;<B>;<C>;<D>;<E>;<F>;<G>;<H>;<I>;<J>;/
        <K>;<L>;<M>;<N>;<O>;<P>;<Q>;<R>;<S>;<T>;/
        <U>;<V>;<W>;<X>;<Y>;<Z>;<A!>;<A'>;<A/>>;<A?>;/
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
            <A:>;<AA>;<AE>;<C,>;<E!>;<E'>;<E/>>;<E:>;<I!>;<I'>;/                1
            <I/>>;<I:>;<D->;<N?>;<O!>;<O'>;<O/>>;<O?>;<O:>;<O//>;/              1
            <U!>;<U'>;<U/>>;<U:>;<Y'>;<TH>;<A->;<C/>>;<C.>;<E->;/               1
            <E.>;<G/>>;<G(>;<G.>;<G,>;<H/>>;<I?>;<I->;<I.>;<I;>;/               1
            <J/>>;<K,>;<H//>;<IJ>;<L.>;<L,>;<N,>;<OE>;<O->;<T//>;/              1
            <NG>;<A;>;<L//>;<L<>;<S'>;<S/>>;<S<>;<S,>;<T<>;<Z'>;/               1
            <Z<>;<Z.>;<R'>;<R,>;<A(>;<L'>;<C'>;<C<>;<E;>;<E<>;/                 1
            <D<>;<D//>;<N'>;<N<>;<U?>;<O">;<U->;<U(>;<R<>;<U0>;/                 1
            <U;>;<U">;<W/>>;<Y/>>;<T,>;<Y:>;<A<>;<A_>;<'A>;<A1>;/
            <A2>;<A3>;<B.>;<B_>;<D_>;<D.>;<D;>;<E(>;<E_>;<E?>;/
            <F.>;<G<>;<G->;<G//>;<H:>;<H.>;<H,>;<H;>;<I<>;<I(>;/
            <J(>;<K'>;<K<>;<K_>;<K.>;<K;>;<L_>;<M'>;<M.>;<N.>;/
            <N_>;<O<>;<O(>;<O_>;<O;>;<O1>;<P'>;<R.>;<R_>;<S.>;/
            <S;>;<T_>;<T.>;<U<>;<V?>;<W'>;<W.>;<W:>;<X.>;<X:>;/
            <Y!>;<Y.>;<Z/>>;<Z(>;<Z_>;<Z//>;<EZ>;<G'>;<'B>;<'D>;/
            <'G>;<'J>;<'Y>;<ED>;<IO>;<D%>;<G%>;<IE>;<DS>;<II>;/
            <YI>;<J%>;<LJ>;<NJ>;<Ts>;<KJ>;<V%>;<DZ>;<A=>;<B=>;/
            <V=>;<G=>;<D=>;<E=>;<Z%>;<Z=>;<I=>;<J=>;<K=>;<L=>;/
            <M=>;<N=>;<O=>;<P=>;<R=>;<S=>;<T=>;<U=>;<F=>;<H=>;/
            <C=>;<C%>;<S%>;<Sc>;<=">;<Y=>;<%">;<JE>;<JU>;<JA>;/
            <I3>;<A%>;<E%>;<Y%>;<I%>;<O%>;<U%>;<W%>;<A*>;<B*>;/
            <G*>;<D*>;<E*>;<Z*>;<Y*>;<H*>;<I*>;<K*>;<L*>;<M*>;/
            <N*>;<C*>;<O*>;<P*>;<R*>;<S*>;<T*>;<U*>;<F*>;<X*>;/
            <Q*>;<W*>;<J*>;<V*>

lower       <a>;<b>;<c>;<d>;<e>;<f>;<g>;<h>;<i>;<j>;/
            <k>;<l>;<m>;<n>;<o>;<p>;<q>;<r>;<s>;<t>;/
            <u>;<v>;<w>;<x>;<y>;<z>;<ss>;<a!>;<a'>;<a/>>;/
            <a?>;<a:>;<aa>;<ae>;<c,>;<e!>;<e'>;<e/>>;<e:>;<i!>;/
            <i'>;<i/>>;<i:>;<d->;<n?>;<o!>;<o'>;<o/>>;<o?>;<o:>;/
            <o//>;<u!>;<u'>;<u/>>;<u:>;<y'>;<th>;<y:>;<a->;<c/>>;/
            <c.>;<e->;<e.>;<g/>>;<g(>;<g.>;<g,>;<h/>>;<i?>;<i->;/
            <'n>;<kk>;<i;>;<j/>>;<k,>;<h//>;<i.>;<ij>;<l.>;<l,>;/
            <n,>;<oe>;<o->;<t//>;<ng>;<a;>;<l//>;<l<>;<s'>;<s/>>;/
            <s<>;<s,>;<t<>;<z'>;<z<>;<z.>;<r'>;<r,>;<a(>;<l'>;/
            <c'>;<c<>;<e;>;<e<>;<d<>;<d//>;<n'>;<n<>;<u?>;<o">;/
            <u->;<u(>;<r<>;<u0>;<u;>;<u">;<w/>>;<y/>>;<t,>;<a<>;/               1
            <a_>;<'a>;<a1>;<a2>;<a3>;<b.>;<b_>;<d_>;<d.>;<d;>;/
            <e(>;<e_>;<e?>;<f.>;<g<>;<g->;<g//>;<h:>;<h.>;<h,>;/
            <h;>;<i<>;<i(>;<j(>;<k'>;<k<>;<k_>;<k.>;<k;>;<l_>;/
            <m'>;<m.>;<n.>;<n_>;<o<>;<o(>;<o_>;<o;>;<o1>;<p'>;/
            <r.>;<r_>;<s.>;<s;>;<t_>;<t.>;<u<>;<v?>;<w'>;<w.>;/
            <w:>;<x.>;<x:>;<y!>;<y.>;<z/>>;<z(>;<z_>;<z//>;<ez>;/
            <g'>;<'b>;<'d>;<'g>;<'j>;<'y>;<ed>;<nS>;<sB>;<a=>;/
            <b=>;<v=>;<g=>;<d=>;<e=>;<z%>;<z=>;<i=>;<j=>;<k=>;/
            <l=>;<m=>;<n=>;<o=>;<p=>;<r=>;<s=>;<t=>;<u=>;<f=>;/
            <h=>;<c=>;<c%>;<s%>;<sc>;<='>;<y=>;<%'>;<je>;<ju>;/
            <ja>;<io>;<d%>;<g%>;<ie>;<ds>;<ii>;<yi>;<j%>;<lj>;/
            <nj>;<ts>;<kj>;<v%>;<dz>;<a%>;<e%>;<y%>;<i%>;<a*>;/
            <b*>;<g*>;<d*>;<e*>;<z*>;<y*>;<h*>;<i*>;<k*>;<l*>;/
            <m*>;<n*>;<c*>;<o*>;<p*>;<r*>;<*s>;<s*>;<t*>;<u*>;/
            <f*>;<x*>;<q*>;<w*>;<j*>;<v*>;<o%>;<u%>;<w%>;<A5>;/
            <I5>;<U5>;<E5>;<O5>;<tU>;<yA>;<yU>;<yO>;<wA>;<a6>;/
            <i6>;<u6>;<e6>;<o6>;<TU>;<YA>;<YU>;<YO>;<WA>;<KA>;/
            <KE>;<ff>;<fi>;<fl>;<ft>;<st>

alpha       <A>;<B>;<C>;<D>;<E>;<F>;<G>;<H>;<I>;<J>;/
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<K>;<L>;<M>;<N>;<O>;<P>;<Q>;<R>;<S>;<T>;/
<U>;<V>;<W>;<X>;<Y>;<Z>;<a>;<b>;<c>;<d>;/
<e>;<f>;<g>;<h>;<i>;<j>;<k>;<l>;<m>;<n>;/
<o>;<p>;<q>;<r>;<s>;<t>;<u>;<v>;<w>;<x>;/
<y>;<z>;<-->;<A!>;<A’>;<A/>>;<A?>;<A:>;<AA>;<AE>;/
<C,>;<E!>;<E’>;<E/>>;<E:>;<I!>;<I’>;<I/>>;<I:>;<D->;/
<N?>;<O!>;<O’>;<O/>>;<O?>;<O:>;<O//>;<U!>;<U’>;<U/>>;/
<U:>;<Y’>;<TH>;<ss>;<a!>;<a’>;<a/>>;<a?>;<a:>;<aa>;/
<ae>;<c,>;<e!>;<e’>;<e/>>;<e:>;<i!>;<i’>;<i/>>;<i:>;/
<d->;<n?>;<o!>;<o’>;<o/>>;<o?>;<o:>;<o//>;<u!>;<u’>;/
<u/>>;<u:>;<y’>;<th>;<y:>;<A->;<C/>>;<C.>;<E->;<E.>;/
<G/>>;<G(>;<a->;<c/>>;<c.>;<e->;<e.>;<g/>>;<g(>;<G.>;/
<G,>;<H/>>;<I?>;<I->;<I.>;<g.>;<g,>;<h/>>;<i?>;<i->;/
<I;>;<J/>>;<K,>;<H//>;<IJ>;<L.>;<L,>;<N,>;<OE>;<O->;/
<T//>;<NG>;<’n>;<kk>;<i;>;<j/>>;<k,>;<h//>;<i.>;<ij>;/
<l.>;<l,>;<n,>;<oe>;<o->;<t//>;<ng>;<A;>;<L//>;<L<>;/
<S’>;<S/>>;<S<>;<S,>;<T<>;<Z’>;<Z<>;<Z.>;<a;>;<l//>;/
<l<>;<s’>;<s/>>;<s<>;<s,>;<t<>;<z’>;<z<>;<z.>;<R’>;/
<R,>;<A(>;<L’>;<C’>;<C<>;<E;>;<E<>;<D<>;<D//>;<N’>;/
<N<>;<U?>;<O">;<U->;<U(>;<R<>;<U0>;<U;>;<U">;<W/>>;/ 1
<Y/>>;<T,>;<Y:>;<r’>;<r,>;<a(>;<l’>;<c’>;<c<>;<e;>;/
<e<>;<d<>;<d//>;<n’>;<n<>;<u?>;<o">;<u->;<u(>;<r<>;/
<u0>;<u;>;<u">;<w/>>;<y/>>;<t,>;<a<>;<A<>;<a_>;<A_>;/ 1
<’a>;<’A>;<a1>;<A1>;<a2>;<A2>;<a3>;<A3>;<b.>;<B.>;/
<b_>;<B_>;<d_>;<D_>;<d.>;<D.>;<d;>;<D;>;<e(>;<E(>;/
<e_>;<E_>;<e?>;<E?>;<f.>;<F.>;<g<>;<G<>;<g->;<G->;/
<g//>;<G//>;<h:>;<H:>;<h.>;<H.>;<h,>;<H,>;<h;>;<H;>;/
<i<>;<I<>;<i(>;<I(>;<j(>;<J(>;<k’>;<K’>;<k<>;<K<>;/
<k_>;<K_>;<k.>;<K.>;<k;>;<K;>;<l_>;<L_>;<m’>;<M’>;/
<m.>;<M.>;<n.>;<N.>;<n_>;<N_>;<o<>;<O<>;<o(>;<O(>;/
<o_>;<O_>;<o;>;<O;>;<o1>;<O1>;<p’>;<P’>;<r.>;<R.>;/
<r_>;<R_>;<s.>;<S.>;<s;>;<S;>;<t_>;<T_>;<t.>;<T.>;/
<u<>;<U<>;<v?>;<V?>;<w’>;<W’>;<w.>;<W.>;<w:>;<W:>;/
<x.>;<X.>;<x:>;<X:>;<y!>;<Y!>;<y.>;<Y.>;<z/>>;<Z/>>;/
<z(>;<Z(>;<z_>;<Z_>;<z//>;<Z//>;<ez>;<EZ>;<g’>;<G’>;/
<’b>;<’B>;<’d>;<’D>;<’g>;<’G>;<’j>;<’J>;<’y>;<’Y>;/
<ed>;<ED>;<nS>;<IO>;<D%>;<G%>;<IE>;<DS>;<II>;<YI>;/
<J%>;<LJ>;<NJ>;<Ts>;<KJ>;<V%>;<DZ>;<A=>;<B=>;<V=>;/
<G=>;<D=>;<E=>;<Z%>;<Z=>;<I=>;<J=>;<K=>;<L=>;<M=>;/
<N=>;<O=>;<P=>;<R=>;<S=>;<T=>;<U=>;<F=>;<H=>;<C=>;/
<C%>;<S%>;<Sc>;<=">;<Y=>;<%">;<JE>;<JU>;<JA>;<a=>;/
<b=>;<v=>;<g=>;<d=>;<e=>;<z%>;<z=>;<i=>;<j=>;<k=>;/
<l=>;<m=>;<n=>;<o=>;<p=>;<r=>;<s=>;<t=>;<u=>;<f=>;/
<h=>;<c=>;<c%>;<s%>;<sc>;<=’>;<y=>;<%’>;<je>;<ju>;/
<ja>;<io>;<d%>;<g%>;<ie>;<ds>;<ii>;<yi>;<j%>;<lj>;/
<nj>;<ts>;<kj>;<v%>;<dz>;<I3>;<A%>;<E%>;<Y%>;<I%>;/
<O%>;<U%>;<W%>;<A*>;<B*>;<G*>;<D*>;<E*>;<Z*>;<Y*>;/
<H*>;<I*>;<K*>;<L*>;<M*>;<N*>;<C*>;<O*>;<P*>;<R*>;/
<S*>;<T*>;<U*>;<F*>;<X*>;<Q*>;<W*>;<J*>;<V*>;<a%>;/
<e%>;<y%>;<i%>;<a*>;<b*>;<g*>;<d*>;<e*>;<z*>;<y*>;/
<h*>;<i*>;<k*>;<l*>;<m*>;<n*>;<c*>;<o*>;<p*>;<r*>;/
<*s>;<s*>;<t*>;<u*>;<f*>;<x*>;<q*>;<w*>;<j*>;<v*>;/
<o%>;<u%>;<w%>;<p+>;<v+>;<gf>;<H’>;<aM>;<aH>;<wH>;/
<ah>;<yH>;<a+>;<b+>;<tm>;<t+>;<tk>;<g+>;<hk>;<x+>;/
<d+>;<dk>;<r+>;<z+>;<s+>;<sn>;<c+>;<dd>;<tj>;<zH>;/
<e+>;<i+>;<f+>;<q+>;<k+>;<l+>;<m+>;<n+>;<h+>;<w+>;/
<j+>;<y+>;<A+>;<B+>;<G+>;<D+>;<H+>;<W+>;<Z+>;<X+>;/
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
250             <Tj>;<J+>;<K%>;<K+>;<L+>;<M%>;<M+>;<N%>;<N+>;<S+>;/
251             <E+>;<P%>;<P+>;<Zj>;<ZJ>;<Q+>;<R+>;<Sh>;<T+>;<b4>;/
252             <p4>;<m4>;<f4>;<d4>;<t4>;<n4>;<l4>;<g4>;<k4>;<h4>;/
253             <j4>;<q4>;<x4>;<zh>;<ch>;<sh>;<r4>;<z4>;<c4>;<s4>;/
254             <a4>;<o4>;<e4>;<eh>;<ai>;<ei>;<au>;<ou>;<an>;<en>;/
255             <aN>;<eN>;<er>;<i4>;<u4>;<iu>;<A5>;<a5>;<I5>;<i5>;/
256             <U5>;<u5>;<E5>;<e5>;<O5>;<o5>;<ka>;<ga>;<ki>;<gi>;/
257             <ku>;<gu>;<ke>;<ge>;<ko>;<go>;<sa>;<za>;<si>;<zi>;/
258             <su>;<zu>;<se>;<ze>;<so>;<zo>;<ta>;<da>;<ti>;<di>;/
259             <tU>;<tu>;<du>;<te>;<de>;<to>;<do>;<na>;<ni>;<nu>;/
260             <ne>;<no>;<ha>;<ba>;<pa>;<hi>;<bi>;<pi>;<hu>;<bu>;/
261             <pu>;<he>;<be>;<pe>;<ho>;<bo>;<po>;<ma>;<mi>;<mu>;/
262             <me>;<mo>;<yA>;<ya>;<yU>;<yu>;<yO>;<yo>;<ra>;<ri>;/
263             <ru>;<re>;<ro>;<wA>;<wa>;<wi>;<we>;<wo>;<n5>;<a6>;/
264             <A6>;<i6>;<I6>;<u6>;<U6>;<e6>;<E6>;<o6>;<O6>;<Ka>;/
265             <Ga>;<Ki>;<Gi>;<Ku>;<Gu>;<Ke>;<Ge>;<Ko>;<Go>;<Sa>;/
266             <Za>;<Si>;<Zi>;<Su>;<Zu>;<Se>;<Ze>;<So>;<Zo>;<Ta>;/
267             <Da>;<Ti>;<Di>;<TU>;<Tu>;<Du>;<Te>;<De>;<To>;<Do>;/
268             <Na>;<Ni>;<Nu>;<Ne>;<No>;<Ha>;<Ba>;<Pa>;<Hi>;<Bi>;/                1
269             <Pi>;<Hu>;<Bu>;<Pu>;<He>;<Be>;<Pe>;<Ho>;<Bo>;<Po>;/                1
270             <Ma>;<Mi>;<Mu>;<Me>;<Mo>;<YA>;<Ya>;<YU>;<Yu>;<YO>;/
271             <Yo>;<Ra>;<Ri>;<Ru>;<Re>;<Ro>;<WA>;<Wa>;<Wi>;<We>;/
272             <Wo>;<N6>;<Vu>;<KA>;<KE>;<ff>;<fi>;<fl>;<ft>;<st>;/
273             <yf>

274     cntrl   <NU>;<SH>;<SX>;<EX>;<ET>;<EQ>;<AK>;<BL>;<BS>;<HT>;/
275             <LF>;<VT>;<FF>;<CR>;<SO>;<SI>;<DL>;<D1>;<D2>;<D3>;/
276             <D4>;<NK>;<SY>;<EB>;<CN>;<EM>;<SB>;<EC>;<FS>;<GS>;/
277             <RS>;<US>;<DT>;<PA>;<HO>;<BH>;<NH>;<IN>;<NL>;<SA>;/
278             <ES>;<HS>;<HJ>;<VS>;<PD>;<PU>;<RI>;<S2>;<S3>;<DC>;/
279             <P1>;<P2>;<TS>;<CC>;<MW>;<SG>;<EG>;<SS>;<GC>;<SC>;/
280             <CI>;<ST>;<OC>;<PM>;<AC>

281     punct   <!>;<">;<Nb>;<DO>;<%>;<&>;<'>;<(>;<)>;<*>;/
282             <+>;<,>;<->;<.>;<//>;<:>;<;>;<<>;<=>;</>>;/
283             <?>;<At>;<<(>;<////>;<)/>>;<'/>>;<_>;<'!>;<(!>;<!!>;/
284             <!)>;<'?>;<!I>;<Ct>;<Pd>;<Cu>;<Ye>;<BB>;<SE>;<':>;/
285             <Co>;<-a>;<<<>;<NO>;<Rg>;<'->;<DG>;<+->;<2S>;<3S>;/
286             <''>;<My>;<PI>;<.M>;<',>;<1S>;<-o>;</>/>>;<14>;<12>;/
287             <34>;<?I>;<*X>;<-:>;<'6>;<"6>;<<->;<-!>;<-/>>;<-v>;/
288             <'9>;<"9>;<'0>;<HB>;<TM>;<Md>;<18>;<38>;<58>;<78>;/
289             <Om>;<'(>;<';>;<'<>;<'">;<'.>;<;S>;<Vs>;<1M>;<1N>;/
290             <3M>;<4M>;<6M>;<1H>;<1T>;<-1>;<-N>;<-2>;<-M>;<-3>;/
291             <'1>;<'2>;<'3>;<9'>;<9">;<.9>;<:9>;<<1>;</>1>;<<//>;/
292             <///>>;<15>;<25>;<35>;<45>;<16>;<13>;<23>;<56>;<*->;/
293             <//->;<//=>;<-X>;<%0>;<co>;<PO>;<Rx>;<AO>;<oC>;<Ml>;/
294             <Fm>;<Tl>;<TR>;<MX>;<Mb>;<Mx>;<XX>;<OK>;<M2>;<!2>;/
295             <=2>;<Ca>;<..>;<.3>;<:3>;<.:>;<:.>;<-+>;<!=>;<=3>;/
296             <?1>;<?2>;<?->;<?=>;<=<>;</>=>;<0(>;<00>;<PP>;<-T>;/
297             <-L>;<-V>;<AN>;<OR>;<.P>;<dP>;<f(>;<In>;<Io>;<RT>;/
298             <*P>;<+Z>;<FA>;<TE>;<GF>;<DE>;<NB>;<(U>;<)U>;<(C>;/
299             <)C>;<(_>;<)_>;<(->;<-)>;<</>>;<UD>;<Ub>;<<=>;<=/>>;/
300             <==>;<//0>;<OL>;<0u>;<0U>;<SU>;<0:>;<OS>;<fS>;<Or>;/
301             <SR>;<uT>;<UT>;<dT>;<Dt>;<PL>;<PR>;<*1>;<*2>;<VV>;/
302             <HH>;<DR>;<LD>;<UR>;<UL>;<VR>;<VL>;<DH>;<UH>;<VH>;/
303             <TB>;<LB>;<FB>;<sB>;<EH>;<vv>;<hh>;<dr>;<dl>;<ur>;/
304             <ul>;<vr>;<vl>;<dh>;<uh>;<vh>;<.S>;<:S>;<?S>;<lB>;/
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
305             <RB>;<cC>;<cD>;<Dr>;<Dl>;<Ur>;<Ul>;<Vr>;<Vl>;<dH>;/
306             <uH>;<vH>;<Ob>;<Sb>;<Sn>;<Pt>;<NI>;<cH>;<cS>;<dR>;/
307             <dL>;<uR>;<uL>;<vR>;<vL>;<Dh>;<Uh>;<Vh>;<0m>;<0M>;/
308             <Ic>;<SM>;<CG>;<Ci>;<(A>;</>V>;<!<>;<<*>;<!/>>;<*/>>;/
309             <<7>;<7<>;</>7>;<7/>>;<I2>;<0.>;<HI>;<:>;<FD>;<LZ>;/
310             <BD>;<1R>;<2R>;<3R>;<4R>;<5R>;<6R>;<7R>;<8R>;<9R>;/
311             <aR>;<bR>;<cR>;<N0>;<i3>;<;;>;<,,>;<!*>;<?*>;<;'>;/
312             <,'>;<;!>;<,!>;<?;>;<?,>;<!:>;<?:>;<'%>;<,+>;<;+>;/
313             <?+>;<++>;<:+>;<"+>;<=+>;<//+>;<'+>;<1+>;<3+>;<0+>;/
314             <IS>;<,_>;<._>;<+">;<+_>;<*_>;<;_>;<0_>;<<+>;</>+>;/
315             <<'>;</>'>;<<">;</>">;<(">;<)">;<=//>;<=_>;<('>;<)'>;/
316             <KM>;<"5>;<05>;<*5>;<+5>;<-6>;<*6>;<+6>;<Iu>;<Il>;/
317             <__>;<"!>;<"'>;<"/>>;<"?>;<"->;<"(>;<".>;<":>;<"//>;/                    1
318             <"0>;<",>;<"_>;<"">;<"<>;<";>;<"=>;<"1>;<"2>;<Fd>;/
319             <Bd>;<Fl>;<Li>;<//f>;<0s>;<1s>;<2s>;<3s>;<4s>;<5s>;/
320             <6s>;<7s>;<8s>;<9s>;<0S>;<4S>;<5S>;<6S>;<7S>;<8S>;/
321             <9S>;<+S>;<-S>;<1h>;<2h>;<3h>;<4h>;<1j>;<2j>;<3j>;/
322             <4j>;<UA>;<UB>;<yr>;<.6>;<<6>;</>6>;<,6>;<&6>;<(S>;/
323             <)S>

324     tolower (<'A>,<'a>); (<'B>,<'b>); (<'D>,<'d>); (<'G>,<'g>); (<'J>,<'j>);/
325             (<'Y>,<'y>); (<A>,<a>); (<A!>,<a!>); (<A'>,<a'>); (<A(>,<a(>);/           1
326             (<A->,<a->); (<A1>,<a1>); (<A2>,<a2>); (<A3>,<a3>); (<A:>,<a:>);/
327             (<A;>,<a;>); (<A<>,<a<>); (<A/>>,<a/>>); (<A?>,<a?>); (<AA>,<aa>);/
328             (<AE>,<ae>); (<A_>,<a_>); (<B>,<b>); (<B.>,<b.>); (<B_>,<b_>);/
329             (<C>,<c>); (<C'>,<c'>); (<C,>,<c,>); (<C.>,<c.>); (<C<>,<c<>);/
330             (<C/>>,<c/>>); (<D>,<d>); (<D->,<d->); (<D.>,<d.>); (<D//>,<d//>);/
331             (<D;>,<d;>); (<D<>,<d<>); (<D_>,<d_>); (<E>,<e>); (<E!>,<e!>);/
332             (<E'>,<e'>); (<E(>,<e(>); (<E->,<e->); (<E.>,<e.>); (<E:>,<e:>);/
333             (<E;>,<e;>); (<E<>,<e<>); (<E/>>,<e/>>); (<E?>,<e?>); (<ED>,<ed>);/
334             (<EZ>,<ez>); (<E_>,<e_>); (<F>,<f>); (<F.>,<f.>);/
335             (<G>,<ft>); (<G'>,<g'>); (<G(>,<g(>); (<G,>,<g,>);/
336             (<G->,<g->); (<G.>,<g.>); (<G//>,<g//>); (<G<>,<g<>); (<G/>>,<g/>>);/
337             (<H>,<h>); (<H,>,<h,>); (<H.>,<h.>); (<H//>,<h//>); (<H:>,<h:>);/
338             (<H;>,<h;>); (<H/>>,<h/>>); (<I>,<i>); (<I!>,<i!>); (<I'>,<i'>);/
339             (<I(>,<i(>); (<I->,<i->); (<I.>,<i.>); (<I:>,<i:>); (<I;>,<i;>);/
340             (<I<>,<i<>); (<I/>>,<i/>>); (<I?>,<i?>); (<IJ>,<ij>); (<J>,<j>);/
341             (<J(>,<j(>); (<J/>>,<j/>>); (<K>,<k>); (<K'>,<k'>); (<K,>,<k,>);/
342             (<K.>,<k.>); (<K;>,<k;>); (<K<>,<k<>); (<K_>,<k_>);/
343             (<L>,<l>); (<L'>,<l'>); (<L,>,<l,>); (<L.>,<l.>); (<L//>,<l//>);/
344             (<L<>,<l<>); (<L_>,<l_>); (<M>,<m>); (<M'>,<m'>); (<M.>,<m.>);/
345             (<N>,<n>); (<N'>,<n'>); (<N,>,<n,>); (<N.>,<n.>); (<N<>,<n<>);/
346             (<N?>,<n?>); (<NG>,<ng>); (<N_>,<n_>); (<O>,<o>); (<O!>,<o!>);/
347             (<O">,<o">); (<O'>,<o'>); (<O(>,<o(>); (<O->,<o->); (<O//>,<o//>);/
348             (<O1>,<o1>); (<O:>,<o:>); (<O;>,<o;>); (<O<>,<o<>); (<O/>>,<o/>>);/
349             (<O?>,<o?>); (<OE>,<oe>); (<O_>,<o_>); (<P>,<p>); (<P'>,<p'>);/
350             (<Q>,<q>); (<R>,<r>); (<R'>,<r'>); (<R,>,<r,>); (<R.>,<r.>);/
351             (<R<>,<r<>); (<R_>,<r_>); (<S>,<s>); (<S'>,<s'>); (<S,>,<s,>);/
352             (<S.>,<s.>); (<S;>,<s;>); (<S<>,<s<>); (<S/>>,<s/>>); (<T>,<st>);/
353             (<T,>,<t>); (<T.>,<t.>); (<T//>,<t//>); (<T<>,<t<>);/
354             (<TH>,<th>); (<T_>,<t_>); (<U>,<u>); (<U!>,<u!>); (<U">,<u">);/
355             (<U'>,<u'>); (<U(>,<u(>); (<U->,<u->); (<U0>,<u0>); (<U:>,<u:>);/        1
356             (<U;>,<u;>); (<U<>,<u<>); (<U/>>,<u/>>); (<U?>,<u?>); (<V>,<v>);/
357             (<V?>,<v?>); (<W>,<w>); (<W'>,<w'>); (<W.>,<w.>); (<W:>,<w:>);/
358             (<W/>>,<w/>>); (<X>,<x>); (<X.>,<x.>); (<X:>,<x:>); (<Y>,<y>);/
359             (<Y!>,<y!>); (<Y'>,<y'>); (<Y.>,<y.>); (<Y:>,<y:>); (<Y/>>,<y/>>);/
360             (<Z>,<z>); (<Z'>,<z'>); (<Z(>,<z(>); (<Z.>,<z.>); (<Z//>,<z//>);/
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
361             (<Z<>,<z<>); (<Z/>>,<z/>>); (<Z_>,<z_>); (<%">,<%'>); (<=">,<='>);/
362             (<A=>,<a=>); (<B=>,<b=>); (<C%>,<c%>); (<C=>,<c=>); (<D%>,<d%>);/
363             (<D=>,<d=>); (<DS>,<ds>); (<DZ>,<dz>); (<E=>,<e=>); (<F=>,<f=>);/
364             (<G%>,<g%>); (<G=>,<g=>); (<H=>,<h=>); (<I=>,<i=>); (<IE>,<ie>);/
365             (<II>,<ii>); (<IO>,<io>); (<J%>,<j%>); (<J=>,<j=>); (<JA>,<ja>);/
366             (<JE>,<je>); (<JU>,<ju>); (<K=>,<k=>); (<KJ>,<kj>); (<L=>,<l=>);/
367             (<LJ>,<lj>); (<M=>,<m=>); (<N=>,<n=>); (<NJ>,<nj>); (<O=>,<o=>);/
368             (<P=>,<p=>); (<R=>,<r=>); (<S%>,<s%>); (<S=>,<s=>); (<Sc>,<sc>);/
369             (<T=>,<t=>); (<Ts>,<ts>); (<U=>,<u=>); (<V=>,<v=>); (<Y=>,<y=>);/
370             (<YI>,<yi>); (<Z%>,<z%>); (<Z=>,<z=>); (<A%>,<a%>); (<A*>,<a*>);/
371             (<B*>,<b*>); (<C*>,<c*>); (<D*>,<d*>); (<E%>,<e%>); (<E*>,<e*>);/
372             (<F*>,<f*>); (<G*>,<g*>); (<H*>,<h*>); (<I%>,<i%>); (<I*>,<i*>);/
373             (<J*>,<j*>); (<K*>,<k*>); (<L*>,<l*>); (<M*>,<m*>); (<N*>,<n*>);/
374             (<O%>,<o%>); (<O*>,<o*>); (<P*>,<p*>); (<Q*>,<q*>); (<R*>,<r*>);/
375             (<S*>,<s*>); (<T*>,<t*>); (<U%>,<u%>); (<U*>,<u*>); (<V*>,<v*>);/
376             (<W%>,<w%>); (<W*>,<w*>); (<X*>,<x*>); (<Y%>,<y%>); (<Y*>,<y*>);/
377             (<Z*>,<z*>)

378     toupper (<'a>,<'A>); (<'b>,<'B>); (<'d>,<'D>); (<'g>,<'G>); (<'j>,<'J>);/
379             (<'y>,<'Y>); (<a>,<A>); (<a!>,<A!>); (<a'>,<A'>); (<a(>,<A(>);/                1
380             (<a->,<A->); (<a1>,<A1>); (<a2>,<A2>); (<a3>,<A3>); (<a:>,<A:>);/
381             (<a;>,<A;>); (<a<>,<A<>); (<a/>>,<A/>>); (<a?>,<A?>); (<aa>,<AA>);/
382             (<ae>,<AE>); (<a_>,<A_>); (<b>,<B>); (<b.>,<B.>); (<b_>,<B_>);/
383             (<c>,<C>); (<c'>,<C'>); (<c,>,<C,>); (<c.>,<C.>); (<c<>,<C<>);/
384             (<c/>>,<C/>>); (<d>,<D>); (<d->,<D->); (<d.>,<D.>); (<d//>,<D//>);/
385             (<d;>,<D;>); (<d<>,<D<>); (<d_>,<D_>); (<e>,<E>); (<e!>,<E!>);/
386             (<e'>,<E'>); (<e(>,<E(>); (<e->,<E->); (<e.>,<E.>); (<e:>,<E:>);/
387             (<e;>,<E;>); (<e<>,<E<>); (<e/>>,<E/>>); (<e?>,<E?>); (<ed>,<ED>);/
388             (<ez>,<EZ>); (<e_>,<E_>); (<f>,<F>); (<f.>,<F.>);/
389             (<ft>,<G>); (<g'>,<G'>); (<g(>,<G(>); (<g,>,<G,>);/
390             (<g->,<G->); (<g.>,<G.>); (<g//>,<G//>); (<g<>,<G<>); (<g/>>,<G/>>);/
391             (<h>,<H>); (<h,>,<H,>); (<h.>,<H.>); (<h//>,<H//>); (<h:>,<H:>);/
392             (<h;>,<H;>); (<h/>>,<H/>>); (<i>,<I>); (<i!>,<I!>); (<i'>,<I'>);/
393             (<i(>,<I(>); (<i->,<I->); (<i.>,<I.>); (<i:>,<I:>); (<i;>,<I;>);/
394             (<i<>,<I<>); (<i/>>,<I/>>); (<i?>,<I?>); (<ij>,<IJ>); (<j>,<J>);/
395             (<j(>,<J(>); (<j/>>,<J/>>); (<k>,<K>); (<k'>,<K'>); (<k,>,<K,>);/
396             (<k.>,<K.>); (<k;>,<K;>); (<k<>,<K<>); (<k_>,<K_>);/
397             (<l>,<L>); (<l'>,<L'>); (<l,>,<L,>); (<l.>,<L.>); (<l//>,<L//>);/
398             (<l<>,<L<>); (<l_>,<L_>); (<m>,<M>); (<m'>,<M'>); (<m.>,<M.>);/
399             (<n>,<N>); (<n'>,<N'>); (<n,>,<N,>); (<n.>,<N.>); (<n<>,<N<>);/
400             (<n?>,<N?>); (<ng>,<NG>); (<n_>,<N_>); (<o>,<O>); (<o!>,<O!>);/
401             (<o">,<O">); (<o'>,<O'>); (<o(>,<O(>); (<o->,<O->); (<o//>,<O//>);/
402             (<o1>,<O1>); (<o:>,<O:>); (<o;>,<O;>); (<o<>,<O<>); (<o/>>,<O/>>);/
403             (<o?>,<O?>); (<oe>,<OE>); (<o_>,<O_>); (<p>,<P>); (<p'>,<P'>);/
404             (<q>,<Q>); (<r>,<R>); (<r'>,<R'>); (<r,>,<R,>); (<r.>,<R.>);/
405             (<r<>,<R<>); (<r_>,<R_>); (<s>,<S>); (<s'>,<S'>); (<s,>,<S,>);/
406             (<s.>,<S.>); (<s;>,<S;>); (<s<>,<S<>); (<s/>>,<S/>>); (<st>,<T>);/
407             (<t>,<T,>); (<t.>,<T.>); (<t//>,<T//>); (<t<>,<T<>);/
408             (<th>,<TH>); (<t_>,<T_>); (<u>,<U>); (<u!>,<U!>); (<u">,<U">);/
409             (<u'>,<U'>); (<u(>,<U(>); (<u->,<U->); (<u0>,<U0>); (<u:>,<U:>);/              1
410             (<u;>,<U;>); (<u<>,<U<>); (<u/>>,<U/>>); (<u?>,<U?>); (<v>,<V>);/
411             (<v?>,<V?>); (<w>,<W>); (<w'>,<W'>); (<w.>,<W.>); (<w:>,<W:>);/
412             (<w/>>,<W/>>); (<x>,<X>); (<x.>,<X.>); (<x:>,<X:>); (<y>,<Y>);/
413             (<y!>,<Y!>); (<y'>,<Y'>); (<y.>,<Y.>); (<y:>,<Y:>); (<y/>>,<Y/>>);/
414             (<z>,<Z>); (<z'>,<Z'>); (<z(>,<Z(>); (<z.>,<Z.>); (<z//>,<Z//>);/
415             (<z<>,<Z<>); (<z/>>,<Z/>>); (<z_>,<Z_>); (<%'>,<%">); (<='>,<=">);/
416             (<a=>,<A=>); (<b=>,<B=>); (<c%>,<C%>); (<c=>,<C=>); (<d%>,<D%>);/
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
417             (<d=>,<D=>); (<ds>,<DS>); (<dz>,<DZ>); (<e=>,<E=>); (<f=>,<F=>);/
418             (<g%>,<G%>); (<g=>,<G=>); (<h=>,<H=>); (<i=>,<I=>); (<ie>,<IE>);/
419             (<ii>,<II>); (<io>,<IO>); (<j%>,<J%>); (<j=>,<J=>); (<ja>,<JA>);/
420             (<je>,<JE>); (<ju>,<JU>); (<k=>,<K=>); (<kj>,<KJ>); (<l=>,<L=>);/
421             (<lj>,<LJ>); (<m=>,<M=>); (<n=>,<N=>); (<nj>,<NJ>); (<o=>,<O=>);/
422             (<p=>,<P=>); (<r=>,<R=>); (<s%>,<S%>); (<s=>,<S=>); (<sc>,<Sc>);/
423             (<t=>,<T=>); (<ts>,<Ts>); (<u=>,<U=>); (<v=>,<V=>); (<y=>,<Y=>);/
424             (<yi>,<YI>); (<z%>,<Z%>); (<z=>,<Z=>); (<a%>,<A%>); (<a*>,<A*>);/
425             (<b*>,<B*>); (<c*>,<C*>); (<d*>,<D*>); (<e%>,<E%>); (<e*>,<E*>);/
426             (<f*>,<F*>); (<g*>,<G*>); (<h*>,<H*>); (<i%>,<I%>); (<i*>,<I*>);/
427             (<j*>,<J*>); (<k*>,<K*>); (<l*>,<L*>); (<m*>,<M*>); (<n*>,<N*>);/
428             (<o%>,<O%>); (<o*>,<O*>); (<p*>,<P*>); (<q*>,<Q*>); (<r*>,<R*>);/
429             (<s*>,<S*>); (<*s>,<S*>); (<t*>,<T*>); (<u%>,<U%>); (<u*>,<U*>);/      1
430             (<v*>,<V*>); (<w%>,<W%>); (<w*>,<W*>); (<x*>,<X*>); (<y%>,<Y%>);/      1
431             (<y*>,<Y*>); (<z*>,<Z*>)                                               1

432     END LC_CTYPE

433     LC_COLLATE

434     % Ordering algorithm:                                                          1
435     %  1. Spaces and hyphen (but not soft hyphen) before punctuation               1
436     %     characters, punctuation characters before numbers,                       1
437     %     numbers before letters.                                                  1
438     %  2. Letters with diacritical marks are members of equivalence classes        1
439     %  3. Upper case letters before corresponding lower case letter.               1
440     %  4. Specials are ignored when comparing letters, but then they are considered 1
441     %  5. The alphabets are sorted in the order of appearance in ISO 10646:        1
442     %     Latin, Cyrillic, Greek, Arabic and Hebrew.                               1
443     %  6. In Danish, the letter combination ‘aa’ is equivalent to ‘<aa>’           1
444     %                                                                              1
445     % The ordering algorithm is in accordance with Danish Standard DS 377         1
446     % and the Danish Orthography Dictionary (Retskrivningsordbogen, 1986).        1
447     % It is also in accordance with Faroese and Greenlandic orthography.          1

448     collating-element <A-A> from <A><A>                                            1
449     collating-element <a-a> from <a><a>                                            1
450     collating-element <A-a> from <A><a>                                            1
451     collating-element <s-s> from <s><s>                                            1
452     collating-element <i-j> from <i><j>                                            1
453     collating-element <I-J> from <I><J>                                            1
454     collating-element <o-e> from <o><e>                                            1
455     collating-element <O-E> from <O><E>                                            1
456     collating-element <t-h> from <t><h>                                            1
457     collating-element <T-H> from <T><H>                                            1
458     collating-element <n-g> from <n><g>                                            1
459     collating-element <N-G> from <N><G>                                            1

460     % collating symbols, <CAPITAL> or <SMALL> letters first                        1
461     % <CAPITAL> letters before <SMALL> letters                                     1

462     collating-symbol <CAPITAL>
463     collating-symbol <BOTH>
464     collating-symbol <SMALL>

465     collating-symbol <NO-ACCENT>
466     collating-symbol <ACUTE>
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
collating-symbol <GRAVE>
collating-symbol <CIRCUMFLEX>
collating-symbol <TILDE>
collating-symbol <MACRON>
collating-symbol <BREVE>
collating-symbol <DOT>
collating-symbol <DIAERESIS>
collating-symbol <CEDILLA>
collating-symbol <UNDERLINE>
collating-symbol <STROKE>
collating-symbol <DOUBLE-ACUTE>
collating-symbol <OGONEK>
collating-symbol <CARON>
collating-symbol <CYRILLIC>
collating-symbol <GREEK>
collating-symbol <ALPHA-1>
collating-symbol <ALPHA-2>
collating-symbol <PRECEDED-BY-APOSTROPHE>
collating-symbol <SPECIAL>
collating-symbol <ACC0>
collating-symbol <ACC1>
collating-symbol <ACC2>
collating-symbol <ACC3>
collating-symbol <ACC11>
collating-symbol <ACC12>

% letter;accent;case;specials                                    1

order_start forward;backward;forward;forward

<CAPITAL>
<BOTH>
<SMALL>

<NO-ACCENT>
<ACUTE>
<GRAVE>
<CIRCUMFLEX>
<TILDE>
<MACRON>
<BREVE>
<DOT>
<DIAERESIS>
<CEDILLA>
<UNDERLINE>
<STROKE>
<DOUBLE-ACUTE>
<OGONEK>
<CARON>
<CYRILLIC>
<GREEK>
<ALPHA-1>
<ALPHA-2>
<PRECEDED-BY-APOSTROPHE>
<SPECIAL>
<ACC0>
<ACC1>
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
520  <ACC2>
521  <ACC3>
522  <ACC11>
523  <ACC12>

524  <SP>    <SP>
525  <NS>    <SP>
526  <HT>    <SP>
527  <VT>    <SP>
528  <CR>    <SP>
529  <LF>    <SP>
530  <FF>    <SP>
531  <->     <SP>
532  <//>    <SP>
533  <!>     IGNORE;IGNORE;IGNORE
534  <">     IGNORE;IGNORE;IGNORE
535  <Nb>    IGNORE;IGNORE;IGNORE
536  <DO>    IGNORE;IGNORE;IGNORE
537  <%>     IGNORE;IGNORE;IGNORE
538  <&>     IGNORE;IGNORE;IGNORE
539  <'>     IGNORE;IGNORE;IGNORE
540  <(>     IGNORE;IGNORE;IGNORE
541  <)>     IGNORE;IGNORE;IGNORE
542  <*>     IGNORE;IGNORE;IGNORE
543  <+>     IGNORE;IGNORE;IGNORE
544  <,>     IGNORE;IGNORE;IGNORE
545  <.>     IGNORE;IGNORE;IGNORE
546  <:>     IGNORE;IGNORE;IGNORE
547  <;>     IGNORE;IGNORE;IGNORE
548  <<>     IGNORE;IGNORE;IGNORE
549  <=>     IGNORE;IGNORE;IGNORE
550  </>>    IGNORE;IGNORE;IGNORE
551  <?>     IGNORE;IGNORE;IGNORE
552  <At>    IGNORE;IGNORE;IGNORE
553  <<(>    IGNORE;IGNORE;IGNORE
554  <////>  IGNORE;IGNORE;IGNORE
555  <)/>>   IGNORE;IGNORE;IGNORE
556  <'/>>   IGNORE;IGNORE;IGNORE
557  <_>     IGNORE;IGNORE;IGNORE
558  <'!>    IGNORE;IGNORE;IGNORE
559  <(!>    IGNORE;IGNORE;IGNORE
560  <!!>    IGNORE;IGNORE;IGNORE
561  <!)>    IGNORE;IGNORE;IGNORE
562  <'?>    IGNORE;IGNORE;IGNORE
563  <!I>    IGNORE;IGNORE;IGNORE
564  <Ct>    IGNORE;IGNORE;IGNORE
565  <Pd>    IGNORE;IGNORE;IGNORE
566  <Cu>    IGNORE;IGNORE;IGNORE
567  <Ye>    IGNORE;IGNORE;IGNORE
568  <BB>    IGNORE;IGNORE;IGNORE
569  <SE>    IGNORE;IGNORE;IGNORE
570  <':>    IGNORE;IGNORE;IGNORE
571  <Co>    IGNORE;IGNORE;IGNORE
572  <-a>    IGNORE;IGNORE;IGNORE
573  <<<>    IGNORE;IGNORE;IGNORE
574  <NO>    IGNORE;IGNORE;IGNORE
575  <Rg>    IGNORE;IGNORE;IGNORE
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
576     <'->    IGNORE;IGNORE;IGNORE
577     <DG>    IGNORE;IGNORE;IGNORE
578     <+->    IGNORE;IGNORE;IGNORE
579     <''>    IGNORE;IGNORE;IGNORE
580     <My>    IGNORE;IGNORE;IGNORE
581     <PI>    IGNORE;IGNORE;IGNORE
582     <.M>    IGNORE;IGNORE;IGNORE
583     <',>    IGNORE;IGNORE;IGNORE
584     <-o>    IGNORE;IGNORE;IGNORE
585     </>/>>  IGNORE;IGNORE;IGNORE
586     <14>    IGNORE;IGNORE;IGNORE
587     <12>    IGNORE;IGNORE;IGNORE
588     <34>    IGNORE;IGNORE;IGNORE
589     <?I>    IGNORE;IGNORE;IGNORE
590     <*X>    IGNORE;IGNORE;IGNORE
591     <-:>    IGNORE;IGNORE;IGNORE
592     <'6>    IGNORE;IGNORE;IGNORE
593     <"6>    IGNORE;IGNORE;IGNORE
594     <-!>    IGNORE;IGNORE;IGNORE
595     <-v>    IGNORE;IGNORE;IGNORE
596     <'9>    IGNORE;IGNORE;IGNORE
597     <"9>    IGNORE;IGNORE;IGNORE
598     <'0>    IGNORE;IGNORE;IGNORE
599     <HB>    IGNORE;IGNORE;IGNORE
600     <TM>    IGNORE;IGNORE;IGNORE
601     <Md>    IGNORE;IGNORE;IGNORE
602     <18>    IGNORE;IGNORE;IGNORE
603     <38>    IGNORE;IGNORE;IGNORE
604     <58>    IGNORE;IGNORE;IGNORE
605     <78>    IGNORE;IGNORE;IGNORE
606     <Om>    IGNORE;IGNORE;IGNORE
607     <'(>    IGNORE;IGNORE;IGNORE
608     <';>    IGNORE;IGNORE;IGNORE
609     <'<>    IGNORE;IGNORE;IGNORE
610     <'">    IGNORE;IGNORE;IGNORE
611     <'.>    IGNORE;IGNORE;IGNORE
612     <;S>    IGNORE;IGNORE;IGNORE
613     <Vs>    IGNORE;IGNORE;IGNORE
614     <1M>    IGNORE;IGNORE;IGNORE
615     <1N>    IGNORE;IGNORE;IGNORE
616     <3M>    IGNORE;IGNORE;IGNORE
617     <4M>    IGNORE;IGNORE;IGNORE
618     <6M>    IGNORE;IGNORE;IGNORE
619     <1H>    IGNORE;IGNORE;IGNORE
620     <1T>    IGNORE;IGNORE;IGNORE
621     <-1>    IGNORE;IGNORE;IGNORE
622     <-N>    IGNORE;IGNORE;IGNORE
623     <-2>    IGNORE;IGNORE;IGNORE
624     <-M>    IGNORE;IGNORE;IGNORE
625     <-3>    IGNORE;IGNORE;IGNORE
626     <'1>    IGNORE;IGNORE;IGNORE
627     <'2>    IGNORE;IGNORE;IGNORE
628     <'3>    IGNORE;IGNORE;IGNORE
629     <9'>    IGNORE;IGNORE;IGNORE
630     <9">    IGNORE;IGNORE;IGNORE
631     <.9>    IGNORE;IGNORE;IGNORE
632     <:9>    IGNORE;IGNORE;IGNORE
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
633     <<1>    IGNORE;IGNORE;IGNORE
634     </>1>   IGNORE;IGNORE;IGNORE
635     <15>    IGNORE;IGNORE;IGNORE
636     <25>    IGNORE;IGNORE;IGNORE
637     <35>    IGNORE;IGNORE;IGNORE
638     <45>    IGNORE;IGNORE;IGNORE
639     <16>    IGNORE;IGNORE;IGNORE
640     <13>    IGNORE;IGNORE;IGNORE
641     <23>    IGNORE;IGNORE;IGNORE
642     <56>    IGNORE;IGNORE;IGNORE
643     <*->    IGNORE;IGNORE;IGNORE
644     <//->   IGNORE;IGNORE;IGNORE
645     <//=>   IGNORE;IGNORE;IGNORE
646     <-X>    IGNORE;IGNORE;IGNORE
647     <%0>    IGNORE;IGNORE;IGNORE
648     <co>    IGNORE;IGNORE;IGNORE
649     <PO>    IGNORE;IGNORE;IGNORE
650     <Rx>    IGNORE;IGNORE;IGNORE
651     <AO>    IGNORE;IGNORE;IGNORE
652     <oC>    IGNORE;IGNORE;IGNORE
653     <Ml>    IGNORE;IGNORE;IGNORE
654     <Fm>    IGNORE;IGNORE;IGNORE
655     <Tl>    IGNORE;IGNORE;IGNORE
656     <TR>    IGNORE;IGNORE;IGNORE
657     <MX>    IGNORE;IGNORE;IGNORE
658     <Mb>    IGNORE;IGNORE;IGNORE
659     <Mx>    IGNORE;IGNORE;IGNORE
660     <XX>    IGNORE;IGNORE;IGNORE
661     <OK>    IGNORE;IGNORE;IGNORE
662     <M2>    IGNORE;IGNORE;IGNORE
663     <!2>    IGNORE;IGNORE;IGNORE
664     <=2>    IGNORE;IGNORE;IGNORE
665     <Ca>    IGNORE;IGNORE;IGNORE
666     <..>    IGNORE;IGNORE;IGNORE
667     <.3>    IGNORE;IGNORE;IGNORE
668     <:3>    IGNORE;IGNORE;IGNORE
669     <.:>    IGNORE;IGNORE;IGNORE
670     <:.>    IGNORE;IGNORE;IGNORE
671     <-+>    IGNORE;IGNORE;IGNORE
672     <!=>    IGNORE;IGNORE;IGNORE
673     <=3>    IGNORE;IGNORE;IGNORE
674     <?1>    IGNORE;IGNORE;IGNORE
675     <?2>    IGNORE;IGNORE;IGNORE
676     <?->    IGNORE;IGNORE;IGNORE
677     <?=>    IGNORE;IGNORE;IGNORE
678     <=<>    IGNORE;IGNORE;IGNORE
679     </>=>   IGNORE;IGNORE;IGNORE
680     <0(>    IGNORE;IGNORE;IGNORE
681     <00>    IGNORE;IGNORE;IGNORE
682     <PP>    IGNORE;IGNORE;IGNORE
683     <-T>    IGNORE;IGNORE;IGNORE
684     <-L>    IGNORE;IGNORE;IGNORE
685     <-V>    IGNORE;IGNORE;IGNORE
686     <AN>    IGNORE;IGNORE;IGNORE
687     <OR>    IGNORE;IGNORE;IGNORE
688     <.P>    IGNORE;IGNORE;IGNORE
689     <dP>    IGNORE;IGNORE;IGNORE
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
690     <f(>    IGNORE;IGNORE;IGNORE
691     <In>    IGNORE;IGNORE;IGNORE
692     <Io>    IGNORE;IGNORE;IGNORE
693     <RT>    IGNORE;IGNORE;IGNORE
694     <*P>    IGNORE;IGNORE;IGNORE
695     <+Z>    IGNORE;IGNORE;IGNORE
696     <FA>    IGNORE;IGNORE;IGNORE
697     <TE>    IGNORE;IGNORE;IGNORE
698     <GF>    IGNORE;IGNORE;IGNORE
699     <DE>    IGNORE;IGNORE;IGNORE
700     <NB>    IGNORE;IGNORE;IGNORE
701     <(U>    IGNORE;IGNORE;IGNORE
702     <)U>    IGNORE;IGNORE;IGNORE
703     <(C>    IGNORE;IGNORE;IGNORE
704     <)C>    IGNORE;IGNORE;IGNORE
705     <(_>    IGNORE;IGNORE;IGNORE
706     <)_>    IGNORE;IGNORE;IGNORE
707     <(->    IGNORE;IGNORE;IGNORE
708     <-)>    IGNORE;IGNORE;IGNORE
709     <</>>   IGNORE;IGNORE;IGNORE
710     <UD>    IGNORE;IGNORE;IGNORE
711     <Ub>    IGNORE;IGNORE;IGNORE
712     <<=>    IGNORE;IGNORE;IGNORE
713     <=/>>   IGNORE;IGNORE;IGNORE
714     <==>    IGNORE;IGNORE;IGNORE
715     <//0>   IGNORE;IGNORE;IGNORE
716     <OL>    IGNORE;IGNORE;IGNORE
717     <0u>    IGNORE;IGNORE;IGNORE
718     <0U>    IGNORE;IGNORE;IGNORE
719     <SU>    IGNORE;IGNORE;IGNORE
720     <0:>    IGNORE;IGNORE;IGNORE
721     <OS>    IGNORE;IGNORE;IGNORE
722     <fS>    IGNORE;IGNORE;IGNORE
723     <Or>    IGNORE;IGNORE;IGNORE
724     <SR>    IGNORE;IGNORE;IGNORE
725     <uT>    IGNORE;IGNORE;IGNORE
726     <UT>    IGNORE;IGNORE;IGNORE
727     <dT>    IGNORE;IGNORE;IGNORE
728     <Dt>    IGNORE;IGNORE;IGNORE
729     <PL>    IGNORE;IGNORE;IGNORE
730     <PR>    IGNORE;IGNORE;IGNORE
731     <*1>    IGNORE;IGNORE;IGNORE
732     <*2>    IGNORE;IGNORE;IGNORE
733     <VV>    IGNORE;IGNORE;IGNORE
734     <HH>    IGNORE;IGNORE;IGNORE
735     <DR>    IGNORE;IGNORE;IGNORE
736     <LD>    IGNORE;IGNORE;IGNORE
737     <UR>    IGNORE;IGNORE;IGNORE
738     <UL>    IGNORE;IGNORE;IGNORE
739     <VR>    IGNORE;IGNORE;IGNORE
740     <VL>    IGNORE;IGNORE;IGNORE
741     <DH>    IGNORE;IGNORE;IGNORE
742     <UH>    IGNORE;IGNORE;IGNORE
743     <VH>    IGNORE;IGNORE;IGNORE
744     <TB>    IGNORE;IGNORE;IGNORE
745     <LB>    IGNORE;IGNORE;IGNORE
746     <FB>    IGNORE;IGNORE;IGNORE
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
747     <sB>    IGNORE;IGNORE;IGNORE
748     <EH>    IGNORE;IGNORE;IGNORE
749     <vv>    IGNORE;IGNORE;IGNORE
750     <hh>    IGNORE;IGNORE;IGNORE
751     <dr>    IGNORE;IGNORE;IGNORE
752     <dl>    IGNORE;IGNORE;IGNORE
753     <ur>    IGNORE;IGNORE;IGNORE
754     <ul>    IGNORE;IGNORE;IGNORE
755     <vr>    IGNORE;IGNORE;IGNORE
756     <vl>    IGNORE;IGNORE;IGNORE
757     <dh>    IGNORE;IGNORE;IGNORE
758     <uh>    IGNORE;IGNORE;IGNORE
759     <vh>    IGNORE;IGNORE;IGNORE
760     <.S>    IGNORE;IGNORE;IGNORE
761     <:S>    IGNORE;IGNORE;IGNORE
762     <?S>    IGNORE;IGNORE;IGNORE
763     <lB>    IGNORE;IGNORE;IGNORE
764     <RB>    IGNORE;IGNORE;IGNORE
765     <cC>    IGNORE;IGNORE;IGNORE
766     <cD>    IGNORE;IGNORE;IGNORE
767     <Dr>    IGNORE;IGNORE;IGNORE
768     <Dl>    IGNORE;IGNORE;IGNORE
769     <Ur>    IGNORE;IGNORE;IGNORE
770     <Ul>    IGNORE;IGNORE;IGNORE
771     <Vr>    IGNORE;IGNORE;IGNORE
772     <Vl>    IGNORE;IGNORE;IGNORE
773     <dH>    IGNORE;IGNORE;IGNORE
774     <uH>    IGNORE;IGNORE;IGNORE
775     <vH>    IGNORE;IGNORE;IGNORE
776     <Ob>    IGNORE;IGNORE;IGNORE
777     <Sb>    IGNORE;IGNORE;IGNORE
778     <Sn>    IGNORE;IGNORE;IGNORE
779     <Pt>    IGNORE;IGNORE;IGNORE
780     <NI>    IGNORE;IGNORE;IGNORE
781     <cH>    IGNORE;IGNORE;IGNORE
782     <cS>    IGNORE;IGNORE;IGNORE
783     <dR>    IGNORE;IGNORE;IGNORE
784     <dL>    IGNORE;IGNORE;IGNORE
785     <uR>    IGNORE;IGNORE;IGNORE
786     <uL>    IGNORE;IGNORE;IGNORE
787     <vR>    IGNORE;IGNORE;IGNORE
788     <vL>    IGNORE;IGNORE;IGNORE
789     <Dh>    IGNORE;IGNORE;IGNORE
790     <Uh>    IGNORE;IGNORE;IGNORE
791     <Vh>    IGNORE;IGNORE;IGNORE
792     <0m>    IGNORE;IGNORE;IGNORE
793     <0M>    IGNORE;IGNORE;IGNORE
794     <Ic>    IGNORE;IGNORE;IGNORE
795     <SM>    IGNORE;IGNORE;IGNORE
796     <CG>    IGNORE;IGNORE;IGNORE
797     <Ci>    IGNORE;IGNORE;IGNORE
798     <(A>    IGNORE;IGNORE;IGNORE
799     </>V>   IGNORE;IGNORE;IGNORE
800     <!<>    IGNORE;IGNORE;IGNORE
801     <<*>    IGNORE;IGNORE;IGNORE
802     <!/>>   IGNORE;IGNORE;IGNORE
803     <*/>>   IGNORE;IGNORE;IGNORE
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
804     <<7>    IGNORE;IGNORE;IGNORE
805     <7<>    IGNORE;IGNORE;IGNORE
806     </>7>   IGNORE;IGNORE;IGNORE
807     <7/>>   IGNORE;IGNORE;IGNORE
808     <I2>    IGNORE;IGNORE;IGNORE
809     <0.>    IGNORE;IGNORE;IGNORE
810     <HI>    IGNORE;IGNORE;IGNORE
811     <::>    IGNORE;IGNORE;IGNORE
812     <FD>    IGNORE;IGNORE;IGNORE
813     <LZ>    IGNORE;IGNORE;IGNORE
814     <BD>    IGNORE;IGNORE;IGNORE
815     <1R>    IGNORE;IGNORE;IGNORE
816     <2R>    IGNORE;IGNORE;IGNORE
817     <3R>    IGNORE;IGNORE;IGNORE
818     <4R>    IGNORE;IGNORE;IGNORE
819     <5R>    IGNORE;IGNORE;IGNORE
820     <6R>    IGNORE;IGNORE;IGNORE
821     <7R>    IGNORE;IGNORE;IGNORE
822     <8R>    IGNORE;IGNORE;IGNORE
823     <9R>    IGNORE;IGNORE;IGNORE
824     <aR>    IGNORE;IGNORE;IGNORE
825     <bR>    IGNORE;IGNORE;IGNORE
826     <cR>    IGNORE;IGNORE;IGNORE
827     <N0>    IGNORE;IGNORE;IGNORE
828     <i3>    IGNORE;IGNORE;IGNORE
829     <;;>    IGNORE;IGNORE;IGNORE
830     <,,>    IGNORE;IGNORE;IGNORE
831     <!*>    IGNORE;IGNORE;IGNORE
832     <?*>    IGNORE;IGNORE;IGNORE
833     <;'>    IGNORE;IGNORE;IGNORE
834     <,'>    IGNORE;IGNORE;IGNORE
835     <;!>    IGNORE;IGNORE;IGNORE
836     <,!>    IGNORE;IGNORE;IGNORE
837     <?;>    IGNORE;IGNORE;IGNORE
838     <?,>    IGNORE;IGNORE;IGNORE
839     <!:>    IGNORE;IGNORE;IGNORE
840     <?:>    IGNORE;IGNORE;IGNORE
841     <'%>    IGNORE;IGNORE;IGNORE
842     <,+>    IGNORE;IGNORE;IGNORE
843     <;+>    IGNORE;IGNORE;IGNORE
844     <?+>    IGNORE;IGNORE;IGNORE
845     <++>    IGNORE;IGNORE;IGNORE
846     <:+>    IGNORE;IGNORE;IGNORE
847     <"+>    IGNORE;IGNORE;IGNORE
848     <=+>    IGNORE;IGNORE;IGNORE
849     <//+>   IGNORE;IGNORE;IGNORE
850     <'+>    IGNORE;IGNORE;IGNORE
851     <1+>    IGNORE;IGNORE;IGNORE
852     <3+>    IGNORE;IGNORE;IGNORE
853     <0+>    IGNORE;IGNORE;IGNORE
854     <IS>    IGNORE;IGNORE;IGNORE
855     <,_>    IGNORE;IGNORE;IGNORE
856     <._>    IGNORE;IGNORE;IGNORE
857     <+">    IGNORE;IGNORE;IGNORE
858     <+_>    IGNORE;IGNORE;IGNORE
859     <*_>    IGNORE;IGNORE;IGNORE
860     <;_>    IGNORE;IGNORE;IGNORE
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<0_>    IGNORE;IGNORE;IGNORE
<<+>    IGNORE;IGNORE;IGNORE
</>+>   IGNORE;IGNORE;IGNORE
<<'>    IGNORE;IGNORE;IGNORE
</>'>   IGNORE;IGNORE;IGNORE
<<">    IGNORE;IGNORE;IGNORE
</>">   IGNORE;IGNORE;IGNORE
<(">    IGNORE;IGNORE;IGNORE
<)">    IGNORE;IGNORE;IGNORE
<=//>   IGNORE;IGNORE;IGNORE
<=_>    IGNORE;IGNORE;IGNORE
<('>    IGNORE;IGNORE;IGNORE
<)'>    IGNORE;IGNORE;IGNORE
<KM>    IGNORE;IGNORE;IGNORE
<"5>    IGNORE;IGNORE;IGNORE
<05>    IGNORE;IGNORE;IGNORE
<*5>    IGNORE;IGNORE;IGNORE
<+5>    IGNORE;IGNORE;IGNORE
<-6>    IGNORE;IGNORE;IGNORE
<*6>    IGNORE;IGNORE;IGNORE
<+6>    IGNORE;IGNORE;IGNORE
<Iu>    IGNORE;IGNORE;IGNORE
<Il>    IGNORE;IGNORE;IGNORE
<NU>    IGNORE;IGNORE;IGNORE
<SH>    IGNORE;IGNORE;IGNORE
<SX>    IGNORE;IGNORE;IGNORE
<EX>    IGNORE;IGNORE;IGNORE
<ET>    IGNORE;IGNORE;IGNORE
<EQ>    IGNORE;IGNORE;IGNORE
<AK>    IGNORE;IGNORE;IGNORE
<BL>    IGNORE;IGNORE;IGNORE
<BS>    IGNORE;IGNORE;IGNORE
<SO>    IGNORE;IGNORE;IGNORE
<SI>    IGNORE;IGNORE;IGNORE
<DL>    IGNORE;IGNORE;IGNORE
<D1>    IGNORE;IGNORE;IGNORE
<D2>    IGNORE;IGNORE;IGNORE
<D3>    IGNORE;IGNORE;IGNORE
<D4>    IGNORE;IGNORE;IGNORE
<NK>    IGNORE;IGNORE;IGNORE
<SY>    IGNORE;IGNORE;IGNORE
<EB>    IGNORE;IGNORE;IGNORE
<CN>    IGNORE;IGNORE;IGNORE
<EM>    IGNORE;IGNORE;IGNORE
<SB>    IGNORE;IGNORE;IGNORE
<EC>    IGNORE;IGNORE;IGNORE
<FS>    IGNORE;IGNORE;IGNORE
<GS>    IGNORE;IGNORE;IGNORE
<RS>    IGNORE;IGNORE;IGNORE
<US>    IGNORE;IGNORE;IGNORE
<DT>    IGNORE;IGNORE;IGNORE
<PA>    IGNORE;IGNORE;IGNORE
<HO>    IGNORE;IGNORE;IGNORE
<BH>    IGNORE;IGNORE;IGNORE
<NH>    IGNORE;IGNORE;IGNORE
<IN>    IGNORE;IGNORE;IGNORE
<NL>    IGNORE;IGNORE;IGNORE
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<SA>    IGNORE;IGNORE;IGNORE
<ES>    IGNORE;IGNORE;IGNORE
<HS>    IGNORE;IGNORE;IGNORE
<HJ>    IGNORE;IGNORE;IGNORE
<VS>    IGNORE;IGNORE;IGNORE
<PD>    IGNORE;IGNORE;IGNORE
<PU>    IGNORE;IGNORE;IGNORE
<RI>    IGNORE;IGNORE;IGNORE
<S2>    IGNORE;IGNORE;IGNORE
<S3>    IGNORE;IGNORE;IGNORE
<DC>    IGNORE;IGNORE;IGNORE
<P1>    IGNORE;IGNORE;IGNORE
<P2>    IGNORE;IGNORE;IGNORE
<TS>    IGNORE;IGNORE;IGNORE
<CC>    IGNORE;IGNORE;IGNORE
<MW>    IGNORE;IGNORE;IGNORE
<SG>    IGNORE;IGNORE;IGNORE
<EG>    IGNORE;IGNORE;IGNORE
<SS>    IGNORE;IGNORE;IGNORE
<GC>    IGNORE;IGNORE;IGNORE
<SC>    IGNORE;IGNORE;IGNORE
<CI>    IGNORE;IGNORE;IGNORE
<ST>    IGNORE;IGNORE;IGNORE
<OC>    IGNORE;IGNORE;IGNORE
<PM>    IGNORE;IGNORE;IGNORE
<AC>    IGNORE;IGNORE;IGNORE
<__>    IGNORE;IGNORE;IGNORE                                    1
<"!>    IGNORE;IGNORE;IGNORE
<"'>    IGNORE;IGNORE;IGNORE
<"/>>   IGNORE;IGNORE;IGNORE
<"?>    IGNORE;IGNORE;IGNORE
<"->    IGNORE;IGNORE;IGNORE
<"(>    IGNORE;IGNORE;IGNORE
<".>    IGNORE;IGNORE;IGNORE
<":>    IGNORE;IGNORE;IGNORE
<"//>   IGNORE;IGNORE;IGNORE
<"0>    IGNORE;IGNORE;IGNORE
<",>    IGNORE;IGNORE;IGNORE
<"_>    IGNORE;IGNORE;IGNORE
<"">    IGNORE;IGNORE;IGNORE
<"<>    IGNORE;IGNORE;IGNORE
<";>    IGNORE;IGNORE;IGNORE
<"=>    IGNORE;IGNORE;IGNORE
<"1>    IGNORE;IGNORE;IGNORE
<"2>    IGNORE;IGNORE;IGNORE
<Fd>    IGNORE;IGNORE;IGNORE
<Bd>    IGNORE;IGNORE;IGNORE
<Fl>    IGNORE;IGNORE;IGNORE
<Li>    IGNORE;IGNORE;IGNORE
<//f>   IGNORE;IGNORE;IGNORE
<0s>    IGNORE;IGNORE;IGNORE
<1s>    IGNORE;IGNORE;IGNORE
<2s>    IGNORE;IGNORE;IGNORE
<3s>    IGNORE;IGNORE;IGNORE
<4s>    IGNORE;IGNORE;IGNORE
<5s>    IGNORE;IGNORE;IGNORE
<6s>    IGNORE;IGNORE;IGNORE
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<7s>    IGNORE;IGNORE;IGNORE
<8s>    IGNORE;IGNORE;IGNORE
<9s>    IGNORE;IGNORE;IGNORE
<0S>    IGNORE;IGNORE;IGNORE
<4S>    IGNORE;IGNORE;IGNORE
<5S>    IGNORE;IGNORE;IGNORE
<6S>    IGNORE;IGNORE;IGNORE
<7S>    IGNORE;IGNORE;IGNORE
<8S>    IGNORE;IGNORE;IGNORE
<9S>    IGNORE;IGNORE;IGNORE
<+S>    IGNORE;IGNORE;IGNORE
<-S>    IGNORE;IGNORE;IGNORE
<1h>    IGNORE;IGNORE;IGNORE
<2h>    IGNORE;IGNORE;IGNORE
<3h>    IGNORE;IGNORE;IGNORE
<4h>    IGNORE;IGNORE;IGNORE
<1j>    IGNORE;IGNORE;IGNORE
<2j>    IGNORE;IGNORE;IGNORE
<3j>    IGNORE;IGNORE;IGNORE
<4j>    IGNORE;IGNORE;IGNORE
<UA>    IGNORE;IGNORE;IGNORE
<UB>    IGNORE;IGNORE;IGNORE
<yr>    IGNORE;IGNORE;IGNORE
<.6>    IGNORE;IGNORE;IGNORE
<<6>    IGNORE;IGNORE;IGNORE
</>6>   IGNORE;IGNORE;IGNORE
<,6>    IGNORE;IGNORE;IGNORE
<&6>    IGNORE;IGNORE;IGNORE
<(S>    IGNORE;IGNORE;IGNORE
<)S>    IGNORE;IGNORE;IGNORE
<UNDEFINED>     IGNORE;IGNORE;IGNORE
<0>
<1>     <1>
<1S>    <1>
<2>     <2>
<2S>    <2>
<3>     <3>
<3S>    <3>
<4>
<5>
<6>
<7>
<8>
<9>
<A>     <A>;<NO-ACCENT>;<CAPITAL>
<a>     <A>;<NO-ACCENT>;<SMALL>
<A'>    <A>;<ACUTE>;<CAPITAL>
<a'>    <A>;<ACUTE>;<SMALL>
<A!>    <A>;<GRAVE>;<CAPITAL>
<a!>    <A>;<GRAVE>;<SMALL>
<A/>>   <A>;<CIRCUMFLEX>;<CAPITAL>
<a/>>   <A>;<CIRCUMFLEX>;<SMALL>
<A?>    <A>;<TILDE>;<CAPITAL>
<a?>    <A>;<TILDE>;<SMALL>
<A->    <A>;<MACRON>;<CAPITAL>
<a->    <A>;<MACRON>;<SMALL>
<A(>    <A>;<BREVE>;<CAPITAL>
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<a(>    <A>;<BREVE>;<SMALL>
<A_>    <A>;<UNDERLINE>;<CAPITAL>
<a_>    <A>;<UNDERLINE>;<SMALL>
<A;>    <A>;<OGONEK>;<CAPITAL>
<a;>    <A>;<OGONEK>;<SMALL>
<A<>    <A>;<CARON>;<CAPITAL>
<a<>    <A>;<CARON>;<SMALL>
<'A>    <A>;<PRECEDED-BY-APOSTROPHE>;<CAPITAL>
<'a>    <A>;<PRECEDED-BY-APOSTROPHE>;<SMALL>
<A1>    <A>;<ACC1>;<CAPITAL>
<a1>    <A>;<ACC1>;<SMALL>
<A2>    <A>;<ACC2>;<CAPITAL>
<a2>    <A>;<ACC2>;<SMALL>
<B>     <B>;<NO-ACCENT>;<CAPITAL>
<b>     <B>;<NO-ACCENT>;<SMALL>
<B.>    <B>;<DOT>;<CAPITAL>
<b.>    <B>;<DOT>;<SMALL>
<B_>    <B>;<UNDERLINE>;<CAPITAL>
<b_>    <B>;<UNDERLINE>;<SMALL>
<'B>    <B>;<PRECEDED-BY-APOSTROPHE>;<CAPITAL>
<'b>    <B>;<PRECEDED-BY-APOSTROPHE>;<SMALL>
<C>     <C>;<NO-ACCENT>;<CAPITAL>
<c>     <C>;<NO-ACCENT>;<SMALL>
<C'>    <C>;<ACUTE>;<CAPITAL>
<c'>    <C>;<ACUTE>;<SMALL>
<C/>>   <C>;<CIRCUMFLEX>;<CAPITAL>
<c/>>   <C>;<CIRCUMFLEX>;<SMALL>
<C.>    <C>;<DOT>;<CAPITAL>
<c.>    <C>;<DOT>;<SMALL>
<C,>    <C>;<CEDILLA>;<CAPITAL>
<c,>    <C>;<CEDILLA>;<SMALL>
<C<>    <C>;<CARON>;<CAPITAL>
<c<>    <C>;<CARON>;<SMALL>
<D>     <D>;<NO-ACCENT>;<CAPITAL>
<d>     <D>;<NO-ACCENT>;<SMALL>
<D.>    <D>;<DOT>;<CAPITAL>
<d.>    <D>;<DOT>;<SMALL>
<D_>    <D>;<UNDERLINE>;<CAPITAL>
<d_>    <D>;<UNDERLINE>;<SMALL>
<D//>   <D>;<STROKE>;<CAPITAL>
<d//>   <D>;<STROKE>;<SMALL>
<D;>    <D>;<OGONEK>;<CAPITAL>
<d;>    <D>;<OGONEK>;<SMALL>
<D<>    <D>;<CARON>;<CAPITAL>
<d<>    <D>;<CARON>;<SMALL>
<'D>    <D>;<PRECEDED-BY-APOSTROPHE>;<CAPITAL>
<'d>    <D>;<PRECEDED-BY-APOSTROPHE>;<SMALL>
<D->    <D>;<SPECIAL>;<CAPITAL>
<d->    <D>;<SPECIAL>;<SMALL>
<E>     <E>;<NO-ACCENT>;<CAPITAL>
<e>     <E>;<NO-ACCENT>;<SMALL>
<E'>    <E>;<ACUTE>;<CAPITAL>
<e'>    <E>;<ACUTE>;<SMALL>
<E!>    <E>;<GRAVE>;<CAPITAL>
<e!>    <E>;<GRAVE>;<SMALL>
<E/>>   <E>;<CIRCUMFLEX>;<CAPITAL>
<e/>>   <E>;<CIRCUMFLEX>;<SMALL>
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<E?>    <E>;<TILDE>;<CAPITAL>
<e?>    <E>;<TILDE>;<SMALL>
<E->    <E>;<MACRON>;<CAPITAL>
<e->    <E>;<MACRON>;<SMALL>
<E(>    <E>;<BREVE>;<CAPITAL>
<e(>    <E>;<BREVE>;<SMALL>
<E.>    <E>;<DOT>;<CAPITAL>
<e.>    <E>;<DOT>;<SMALL>
<E:>    <E>;<DIAERESIS>;<CAPITAL>
<e:>    <E>;<DIAERESIS>;<SMALL>
<E_>    <E>;<UNDERLINE>;<CAPITAL>
<e_>    <E>;<UNDERLINE>;<SMALL>
<E;>    <E>;<OGONEK>;<CAPITAL>
<e;>    <E>;<OGONEK>;<SMALL>
<E<>    <E>;<CARON>;<CAPITAL>
<e<>    <E>;<CARON>;<SMALL>
<F>     <F>;<NO-ACCENT>;<CAPITAL>
<f>     <F>;<NO-ACCENT>;<SMALL>
<F.>    <F>;<DOT>;<CAPITAL>
<f.>    <F>;<DOT>;<SMALL>
<ff>    <FF+>;<SPECIAL>;<SMALL>
<fi>    <FI+>;<SPECIAL>;<SMALL>
<fl>    <FL+>;<SPECIAL>;<SMALL>
<ft>    <FT+>;<SPECIAL>;<SMALL>
<G>     <G>;<NO-ACCENT>;<CAPITAL>
<g>     <G>;<NO-ACCENT>;<SMALL>
<G'>    <G>;<ACUTE>;<CAPITAL>
<g'>    <G>;<ACUTE>;<SMALL>
<G/>>   <G>;<CIRCUMFLEX>;<CAPITAL>
<g/>>   <G>;<CIRCUMFLEX>;<SMALL>
<G->    <G>;<MACRON>;<CAPITAL>
<g->    <G>;<MACRON>;<SMALL>
<G(>    <G>;<BREVE>;<CAPITAL>
<g(>    <G>;<BREVE>;<SMALL>
<G.>    <G>;<DOT>;<CAPITAL>
<g.>    <G>;<DOT>;<SMALL>
<G,>    <G>;<CEDILLA>;<CAPITAL>
<g,>    <G>;<CEDILLA>;<SMALL>
<G//>   <G>;<STROKE>;<CAPITAL>
<g//>   <G>;<STROKE>;<SMALL>
<G<>    <G>;<CARON>;<CAPITAL>
<g<>    <G>;<CARON>;<SMALL>
<'G>    <G>;<PRECEDED-BY-APOSTROPHE>;<CAPITAL>
<'g>    <G>;<PRECEDED-BY-APOSTROPHE>;<SMALL>
<H>     <H>;<NO-ACCENT>;<CAPITAL>
<h>     <H>;<NO-ACCENT>;<SMALL>
<H/>>   <H>;<CIRCUMFLEX>;<CAPITAL>
<h/>>   <H>;<CIRCUMFLEX>;<SMALL>
<H.>    <H>;<DOT>;<CAPITAL>
<h.>    <H>;<DOT>;<SMALL>
<H:>    <H>;<DIAERESIS>;<CAPITAL>
<h:>    <H>;<DIAERESIS>;<SMALL>
<H,>    <H>;<CEDILLA>;<CAPITAL>
<h,>    <H>;<CEDILLA>;<SMALL>
<H//>   <H>;<STROKE>;<CAPITAL>
<h//>   <H>;<STROKE>;<SMALL>
<H;>    <H>;<OGONEK>;<CAPITAL>
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<h;>    <H>;<OGONEK>;<SMALL>
<I>     <I>;<NO-ACCENT>;<CAPITAL>
<i>     <I>;<NO-ACCENT>;<SMALL>
<I'>    <I>;<ACUTE>;<CAPITAL>
<i'>    <I>;<ACUTE>;<SMALL>
<I!>    <I>;<GRAVE>;<CAPITAL>
<i!>    <I>;<GRAVE>;<SMALL>
<I/>>   <I>;<CIRCUMFLEX>;<CAPITAL>
<i/>>   <I>;<CIRCUMFLEX>;<SMALL>
<I?>    <I>;<TILDE>;<CAPITAL>
<i?>    <I>;<TILDE>;<SMALL>
<I->    <I>;<MACRON>;<CAPITAL>
<i->    <I>;<MACRON>;<SMALL>
<I(>    <I>;<BREVE>;<CAPITAL>
<i(>    <I>;<BREVE>;<SMALL>
<I.>    <I>;<DOT>;<CAPITAL>
<i.>    <I>;<DOT>;<SMALL>
<I:>    <I>;<DIAERESIS>;<CAPITAL>
<i:>    <I>;<DIAERESIS>;<SMALL>
<I;>    <I>;<OGONEK>;<CAPITAL>
<i;>    <I>;<OGONEK>;<SMALL>
<I<>    <I>;<CARON>;<CAPITAL>
<i<>    <I>;<CARON>;<SMALL>
<I-J>   <I><J>;<I-J><I-J>;<CAPITAL><CAPITAL>
<i-j>   <I><J>;<I-J><I-J>;<SMALL><SMALL>
<IJ>    <I><J>;<IJ><IJ>;<CAPITAL><CAPITAL>
<ij>    <I><J>;<IJ><IJ>;<SMALL><SMALL>
<J>     <J>;<NO-ACCENT>;<CAPITAL>
<j>     <J>;<NO-ACCENT>;<SMALL>
<J/>>   <J>;<CIRCUMFLEX>;<CAPITAL>
<j/>>   <J>;<CIRCUMFLEX>;<SMALL>
<J(>    <J>;<BREVE>;<CAPITAL>
<j(>    <J>;<BREVE>;<SMALL>
<'J>    <J>;<PRECEDED-BY-APOSTROPHE>;<CAPITAL>
<'j>    <J>;<PRECEDED-BY-APOSTROPHE>;<SMALL>
<K>     <K>;<NO-ACCENT>;<CAPITAL>
<k>     <K>;<NO-ACCENT>;<SMALL>
<K'>    <K>;<ACUTE>;<CAPITAL>
<k'>    <K>;<ACUTE>;<SMALL>
<K.>    <K>;<DOT>;<CAPITAL>
<k.>    <K>;<DOT>;<SMALL>
<K,>    <K>;<CEDILLA>;<CAPITAL>
<k,>    <K>;<CEDILLA>;<SMALL>
<K_>    <K>;<UNDERLINE>;<CAPITAL>
<k_>    <K>;<UNDERLINE>;<SMALL>
<K;>    <K>;<OGONEK>;<CAPITAL>
<k;>    <K>;<OGONEK>;<SMALL>
<K<>    <K>;<CARON>;<CAPITAL>
<k<>    <K>;<CARON>;<SMALL>
<L>     <L>;<NO-ACCENT>;<CAPITAL>
<l>     <L>;<NO-ACCENT>;<SMALL>
<L'>    <L>;<ACUTE>;<CAPITAL>
<l'>    <L>;<ACUTE>;<SMALL>
<L.>    <L>;<DOT>;<CAPITAL>
<l.>    <L>;<DOT>;<SMALL>
<L,>    <L>;<CEDILLA>;<CAPITAL>
<l,>    <L>;<CEDILLA>;<SMALL>
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<L_>    <L>;<UNDERLINE>;<CAPITAL>
<l_>    <L>;<UNDERLINE>;<SMALL>
<L//>   <L>;<STROKE>;<CAPITAL>
<l//>   <L>;<STROKE>;<SMALL>
<L<>    <L>;<CARON>;<CAPITAL>
<l<>    <L>;<CARON>;<SMALL>
<M>     <M>;<NO-ACCENT>;<CAPITAL>
<m>     <M>;<NO-ACCENT>;<SMALL>
<M'>    <M>;<ACUTE>;<CAPITAL>
<m'>    <M>;<ACUTE>;<SMALL>
<M.>    <M>;<DOT>;<CAPITAL>
<m.>    <M>;<DOT>;<SMALL>
<N>     <N>;<NO-ACCENT>;<CAPITAL>
<n>     <N>;<NO-ACCENT>;<SMALL>
<N'>    <N>;<ACUTE>;<CAPITAL>
<n'>    <N>;<ACUTE>;<SMALL>
<N?>    <N>;<TILDE>;<CAPITAL>
<n?>    <N>;<TILDE>;<SMALL>
<N.>    <N>;<DOT>;<CAPITAL>
<n.>    <N>;<DOT>;<SMALL>
<N,>    <N>;<CEDILLA>;<CAPITAL>
<n,>    <N>;<CEDILLA>;<SMALL>
<N_>    <N>;<UNDERLINE>;<CAPITAL>
<n_>    <N>;<UNDERLINE>;<SMALL>
<N<>    <N>;<CARON>;<CAPITAL>
<n<>    <N>;<CARON>;<SMALL>
<'n>    <N>;<PRECEDED-BY-APOSTROPHE>;<SMALL>
<N-G>   <N><G>;<N-G><N-G>;<CAPITAL><CAPITAL>
<n-g>   <N><G>;<N-G><N-G>;<SMALL><SMALL>
<NG>    <N><G>;<NG><NG>;<CAPITAL><CAPITAL>
<ng>    <N><G>;<NG><NG>;<SMALL><SMALL>
<O>     <O>;<NO-ACCENT>;<CAPITAL>
<o>     <O>;<NO-ACCENT>;<SMALL>
<O'>    <O>;<ACUTE>;<CAPITAL>
<o'>    <O>;<ACUTE>;<SMALL>
<O!>    <O>;<GRAVE>;<CAPITAL>
<o!>    <O>;<GRAVE>;<SMALL>
<O/>>   <O>;<CIRCUMFLEX>;<CAPITAL>
<o/>>   <O>;<CIRCUMFLEX>;<SMALL>
<O?>    <O>;<TILDE>;<CAPITAL>
<o?>    <O>;<TILDE>;<SMALL>
<O->    <O>;<MACRON>;<CAPITAL>
<o->    <O>;<MACRON>;<SMALL>
<O(>    <O>;<BREVE>;<CAPITAL>
<o(>    <O>;<BREVE>;<SMALL>
<O_>    <O>;<UNDERLINE>;<CAPITAL>
<o_>    <O>;<UNDERLINE>;<SMALL>
<O;>    <O>;<OGONEK>;<CAPITAL>
<o;>    <O>;<OGONEK>;<SMALL>
<O<>    <O>;<CARON>;<CAPITAL>
<o<>    <O>;<CARON>;<SMALL>
<O1>    <O>;<ACC1>;<CAPITAL>
<o1>    <O>;<ACC1>;<SMALL>
<O-E>   <O><E>;<O-E><O-E>;<CAPITAL><CAPITAL>
<o-e>   <O><E>;<O-E><O-E>;<SMALL><SMALL>
<OE>    <O><E>;<OE><OE>;<CAPITAL><CAPITAL>
<oe>    <O><E>;<OE><OE>;<SMALL><SMALL>
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<P>     <P>;<NO-ACCENT>;<CAPITAL>
<p>     <P>;<NO-ACCENT>;<SMALL>
<P'>    <P>;<ACUTE>;<CAPITAL>
<p'>    <P>;<ACUTE>;<SMALL>
<Q>     <Q>;<NO-ACCENT>;<CAPITAL>
<q>     <Q>;<NO-ACCENT>;<SMALL>
<kk>    <Q>;<SPECIAL>;<SMALL>
<R>     <R>;<NO-ACCENT>;<CAPITAL>
<r>     <R>;<NO-ACCENT>;<SMALL>
<R'>    <R>;<ACUTE>;<CAPITAL>
<r'>    <R>;<ACUTE>;<SMALL>
<R.>    <R>;<DOT>;<CAPITAL>
<r.>    <R>;<DOT>;<SMALL>
<R,>    <R>;<CEDILLA>;<CAPITAL>
<r,>    <R>;<CEDILLA>;<SMALL>
<R_>    <R>;<UNDERLINE>;<CAPITAL>
<r_>    <R>;<UNDERLINE>;<SMALL>
<R<>    <R>;<CARON>;<CAPITAL>
<r<>    <R>;<CARON>;<SMALL>
<S>     <S>;<NO-ACCENT>;<CAPITAL>
<s>     <S>;<NO-ACCENT>;<SMALL>
<S'>    <S>;<ACUTE>;<CAPITAL>
<s'>    <S>;<ACUTE>;<SMALL>
<S/>>   <S>;<CIRCUMFLEX>;<CAPITAL>
<s/>>   <S>;<CIRCUMFLEX>;<SMALL>
<S.>    <S>;<DOT>;<CAPITAL>
<s.>    <S>;<DOT>;<SMALL>
<S,>    <S>;<CEDILLA>;<CAPITAL>
<s,>    <S>;<CEDILLA>;<SMALL>
<S;>    <S>;<OGONEK>;<CAPITAL>
<s;>    <S>;<OGONEK>;<SMALL>
<S<>    <S>;<CARON>;<CAPITAL>
<s<>    <S>;<CARON>;<SMALL>
<ss>    <S><S>;<ss><ss>;<SMALL><SMALL>                                  1
<s-s>   <S><S>;<s-s><s-s>;<SMALL><SMALL>                                1
<st>    <ST+>;<SPECIAL>;<SMALL>
<T>     <T>;<NO-ACCENT>;<CAPITAL>
<t>     <T>;<NO-ACCENT>;<SMALL>
<T.>    <T>;<DOT>;<CAPITAL>
<t.>    <T>;<DOT>;<SMALL>
<T,>    <T>;<CEDILLA>;<CAPITAL>
<t,>    <T>;<CEDILLA>;<SMALL>
<T_>    <T>;<UNDERLINE>;<CAPITAL>
<t_>    <T>;<UNDERLINE>;<SMALL>
<T//>   <T>;<STROKE>;<CAPITAL>
<t//>   <T>;<STROKE>;<SMALL>
<T<>    <T>;<CARON>;<CAPITAL>
<t<>    <T>;<CARON>;<SMALL>
<T-H>   <T><H>;<T-H><T-H>;<CAPITAL><CAPITAL>
<t-h>   <T><H>;<T-H><T-H>;<SMALL><SMALL>
<TH>    <T><H>;<TH><TH>;<CAPITAL><CAPITAL>
<th>    <T><H>;<TH><TH>;<SMALL><SMALL>
<U>     <U>;<NO-ACCENT>;<CAPITAL>
<u>     <U>;<NO-ACCENT>;<SMALL>
<U'>    <U>;<ACUTE>;<CAPITAL>
<u'>    <U>;<ACUTE>;<SMALL>
<U!>    <U>;<GRAVE>;<CAPITAL>
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<u!>    <U>;<GRAVE>;<SMALL>
<U/>>   <U>;<CIRCUMFLEX>;<CAPITAL>
<u/>>   <U>;<CIRCUMFLEX>;<SMALL>
<U?>    <U>;<TILDE>;<CAPITAL>
<u?>    <U>;<TILDE>;<SMALL>
<U->    <U>;<MACRON>;<CAPITAL>
<u->    <U>;<MACRON>;<SMALL>
<U(>    <U>;<BREVE>;<CAPITAL>
<u(>    <U>;<BREVE>;<SMALL>
<U;>    <U>;<OGONEK>;<CAPITAL>                                  1
<u;>    <U>;<OGONEK>;<SMALL>
<U<>    <U>;<CARON>;<CAPITAL>
<u<>    <U>;<CARON>;<SMALL>
<U0>    <U>;<RING>;<CAPITAL>                                    1
<u0>    <U>;<RING>;<SMALL>                                      1
<V>     <V>;<NO-ACCENT>;<CAPITAL>
<v>     <V>;<NO-ACCENT>;<SMALL>
<V?>    <V>;<TILDE>;<CAPITAL>
<v?>    <V>;<TILDE>;<SMALL>
<W>     <W>;<NO-ACCENT>;<CAPITAL>
<w>     <W>;<NO-ACCENT>;<SMALL>
<W'>    <W>;<ACUTE>;<CAPITAL>
<w'>    <W>;<ACUTE>;<SMALL>
<W/>>   <W>;<CIRCUMFLEX>;<CAPITAL>
<w/>>   <W>;<CIRCUMFLEX>;<SMALL>
<W.>    <W>;<DOT>;<CAPITAL>
<w.>    <W>;<DOT>;<SMALL>
<W:>    <W>;<DIAERESIS>;<CAPITAL>
<w:>    <W>;<DIAERESIS>;<SMALL>
<X>     <X>;<NO-ACCENT>;<CAPITAL>
<x>     <X>;<NO-ACCENT>;<SMALL>
<X.>    <X>;<DOT>;<CAPITAL>
<x.>    <X>;<DOT>;<SMALL>
<X:>    <X>;<DIAERESIS>;<CAPITAL>
<x:>    <X>;<DIAERESIS>;<SMALL>
<Y>     <Y>;<NO-ACCENT>;<CAPITAL>
<y>     <Y>;<NO-ACCENT>;<SMALL>
<Y'>    <Y>;<ACUTE>;<CAPITAL>
<y'>    <Y>;<ACUTE>;<SMALL>
<Y!>    <Y>;<GRAVE>;<CAPITAL>
<y!>    <Y>;<GRAVE>;<SMALL>
<Y/>>   <Y>;<CIRCUMFLEX>;<CAPITAL>
<y/>>   <Y>;<CIRCUMFLEX>;<SMALL>
<Y.>    <Y>;<DOT>;<CAPITAL>
<y.>    <Y>;<DOT>;<SMALL>
<'Y>    <Y>;<PRECEDED-BY-APOSTROPHE>;<CAPITAL>
<'y>    <Y>;<PRECEDED-BY-APOSTROPHE>;<SMALL>
% <U:> and <U"> are treated as <Y> in Danish                    1
<U:>    <Y>;<ACC11>;<CAPITAL>
<u:>    <Y>;<ACC11>;<SMALL>
<U">    <Y>;<ACC12>;<CAPITAL>
<u">    <Y>;<ACC12>;<SMALL>
<Z>     <Z>;<NO-ACCENT>;<CAPITAL>
<z>     <Z>;<NO-ACCENT>;<SMALL>
<Z'>    <Z>;<ACUTE>;<CAPITAL>
<z'>    <Z>;<ACUTE>;<SMALL>
<Z/>>   <Z>;<CIRCUMFLEX>;<CAPITAL>
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<z/>>   <Z>;<CIRCUMFLEX>;<SMALL>
<Z(>    <Z>;<BREVE>;<CAPITAL>
<z(>    <Z>;<BREVE>;<SMALL>
<Z.>    <Z>;<DOT>;<CAPITAL>
<z.>    <Z>;<DOT>;<SMALL>
<Z_>    <Z>;<UNDERLINE>;<CAPITAL>
<z_>    <Z>;<UNDERLINE>;<SMALL>
<Z//>   <Z>;<STROKE>;<CAPITAL>
<z//>   <Z>;<STROKE>;<SMALL>
<Z<>    <Z>;<CARON>;<CAPITAL>
<z<>    <Z>;<CARON>;<SMALL>
% <AE> is treated as a separate letter in Danish                    1
<AE>    <AE>;<NO-ACCENT>;<CAPITAL>
<ae>    <AE>;<NO-ACCENT>;<SMALL>
<A:>    <AE>;<DIAERESIS>;<CAPITAL>
<a:>    <AE>;<DIAERESIS>;<SMALL>
<A3>    <AE>;<ACC3>;<CAPITAL>
<a3>    <AE>;<ACC3>;<SMALL>
% <O//> is treated as a separate letter in Danish                   1
<O//>   <O//>;<NO-ACCENT>;<CAPITAL>
<o//>   <O//>;<NO-ACCENT>;<SMALL>
<O:>    <O//>;<DIAERESIS>;<CAPITAL>
<o:>    <O//>;<DIAERESIS>;<SMALL>
<O">    <O//>;<DOUBLE-ACUTE>;<CAPITAL>
<o">    <O//>;<DOUBLE-ACUTE>;<SMALL>
% <AA> is treated as a separate letter in Danish                    1
<AA>    <AA>;<NO-ACCENT>;<CAPITAL>
<aa>    <AA>;<NO-ACCENT>;<SMALL>
<A-A>   <AA>;<ACC1>;<CAPITAL>
<A-a>   <AA>;<ACC1>;<BOTH>
<a-a>   <AA>;<ACC1>;<SMALL>

<A=>    <A=>;<CYRILLIC>;<CAPITAL>
<a=>    <A=>;<CYRILLIC>;<SMALL>
<B=>    <B=>;<CYRILLIC>;<CAPITAL>
<b=>    <B=>;<CYRILLIC>;<SMALL>
<V=>    <V=>;<CYRILLIC>;<CAPITAL>
<v=>    <V=>;<CYRILLIC>;<SMALL>
<G=>    <G=>;<CYRILLIC>;<CAPITAL>
<g=>    <G=>;<CYRILLIC>;<SMALL>
<G%>    <G=>;<ALPHA-1>;<CAPITAL>
<g%>    <G=>;<ALPHA-1>;<SMALL>
<D=>    <D=>;<CYRILLIC>;<CAPITAL>
<d=>    <D=>;<CYRILLIC>;<SMALL>
<D%>    <D%>;<ALPHA-1>;<CAPITAL>
<d%>    <D%>;<ALPHA-1>;<SMALL>
<E=>    <E=>;<CYRILLIC>;<CAPITAL>
<e=>    <E=>;<CYRILLIC>;<SMALL>
<IO>    <E=>;<SPECIAL>;<CAPITAL>
<io>    <E=>;<SPECIAL>;<SMALL>
<IE>    <IE>;<SPECIAL>;<CAPITAL>
<ie>    <IE>;<SPECIAL>;<SMALL>
<Z%>    <Z%>;<ALPHA-1>;<CAPITAL>
<z%>    <Z%>;<ALPHA-1>;<SMALL>
<Z=>    <Z=>;<CYRILLIC>;<CAPITAL>
<z=>    <Z=>;<CYRILLIC>;<SMALL>
<DS>    <DS>;<SPECIAL>;<CAPITAL>                                   1
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<ds>    <DS>;<SPECIAL>;<SMALL>
<I=>    <I=>;<CYRILLIC>;<CAPITAL>
<i=>    <I=>;<CYRILLIC>;<SMALL>
<II>    <II>;<SPECIAL>;<CAPITAL>
<ii>    <II>;<SPECIAL>;<SMALL>
<YI>    <II>;<ALPHA-1>;<CAPITAL>
<yi>    <II>;<ALPHA-1>;<SMALL>
<J%>    <J%>;<ALPHA-1>;<CAPITAL>
<j%>    <J%>;<ALPHA-1>;<SMALL>
<J=>    <J=>;<CYRILLIC>;<CAPITAL>
<j=>    <J=>;<CYRILLIC>;<SMALL>
<K=>    <K=>;<CYRILLIC>;<CAPITAL>
<k=>    <K=>;<CYRILLIC>;<SMALL>
<KJ>    <K=>;<SPECIAL>;<CAPITAL>
<kj>    <K=>;<SPECIAL>;<SMALL>
<L=>    <L=>;<CYRILLIC>;<CAPITAL>
<l=>    <L=>;<CYRILLIC>;<SMALL>
<LJ>    <LJ>;<SPECIAL>;<CAPITAL>
<lj>    <LJ>;<SPECIAL>;<SMALL>
<M=>    <M=>;<CYRILLIC>;<CAPITAL>
<m=>    <M=>;<CYRILLIC>;<SMALL>
<N=>    <N=>;<CYRILLIC>;<CAPITAL>
<n=>    <N=>;<CYRILLIC>;<SMALL>
<NJ>    <NJ>;<SPECIAL>;<CAPITAL>
<nj>    <NJ>;<SPECIAL>;<SMALL>
<O=>    <O=>;<CYRILLIC>;<CAPITAL>
<o=>    <O=>;<CYRILLIC>;<SMALL>
<P=>    <P=>;<CYRILLIC>;<CAPITAL>
<p=>    <P=>;<CYRILLIC>;<SMALL>
<R=>    <R=>;<CYRILLIC>;<CAPITAL>
<r=>    <R=>;<CYRILLIC>;<SMALL>
<S=>    <S=>;<CYRILLIC>;<CAPITAL>
<s=>    <S=>;<CYRILLIC>;<SMALL>
<T=>    <T=>;<CYRILLIC>;<CAPITAL>
<t=>    <T=>;<CYRILLIC>;<SMALL>
<Ts>    <Ts>;<SPECIAL>;<CAPITAL>
<ts>    <Ts>;<SPECIAL>;<SMALL>
<U=>    <U=>;<CYRILLIC>;<CAPITAL>
<u=>    <U=>;<CYRILLIC>;<SMALL>
<V%>    <V%>;<ALPHA-1>;<CAPITAL>
<v%>    <V%>;<ALPHA-1>;<SMALL>
<F=>    <F=>;<CYRILLIC>;<CAPITAL>
<f=>    <F=>;<CYRILLIC>;<SMALL>
<H=>    <H=>;<CYRILLIC>;<CAPITAL>
<h=>    <H=>;<CYRILLIC>;<SMALL>
<C=>    <C=>;<CYRILLIC>;<CAPITAL>
<c=>    <C=>;<CYRILLIC>;<SMALL>
<C%>    <C%>;<ALPHA-1>;<CAPITAL>
<c%>    <C%>;<ALPHA-1>;<SMALL>
<DZ>    <DZ>;<SPECIAL>;<CAPITAL>
<dz>    <DZ>;<SPECIAL>;<SMALL>
<S%>    <S%>;<ALPHA-1>;<CAPITAL>
<s%>    <S%>;<ALPHA-1>;<SMALL>
<Sc>    <Sc>;<SPECIAL>;<CAPITAL>
<sc>    <Sc>;<SPECIAL>;<SMALL>
<='>    <='>;<ACUTE>;<SMALL>
<=">    <='>;<DOUBLE-ACUTE>;<CAPITAL>
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<Y=>    <Y=>;<CYRILLIC>;<CAPITAL>
<y=>    <Y=>;<CYRILLIC>;<SMALL>
<%'>    <%'>;<ACUTE>;<SMALL>
<%">    <%'>;<DOUBLE-ACUTE>;<CAPITAL>
<JE>    <JE>;<SPECIAL>;<CAPITAL>
<je>    <JE>;<SPECIAL>;<SMALL>
<JU>    <JU>;<SPECIAL>;<CAPITAL>
<ju>    <JU>;<SPECIAL>;<SMALL>
<JA>    <JA>;<SPECIAL>;<CAPITAL>
<ja>    <JA>;<SPECIAL>;<SMALL>
<A*>    <A*>;<GREEK>;<CAPITAL>                                  1
<a*>    <A*>;<GREEK>;<SMALL>
<A%>    <A*>;<ALPHA-1>;<CAPITAL>
<a%>    <A*>;<ALPHA-1>;<SMALL>
<B*>    <B*>;<GREEK>;<CAPITAL>
<b*>    <B*>;<GREEK>;<SMALL>
<G*>    <G*>;<GREEK>;<CAPITAL>
<g*>    <G*>;<GREEK>;<SMALL>
<D*>    <D*>;<GREEK>;<CAPITAL>
<d*>    <D*>;<GREEK>;<SMALL>
<E*>    <E*>;<GREEK>;<CAPITAL>
<e*>    <E*>;<GREEK>;<SMALL>
<E%>    <E*>;<ALPHA-1>;<CAPITAL>
<e%>    <E*>;<ALPHA-1>;<SMALL>
<Z*>    <Z*>;<GREEK>;<CAPITAL>
<z*>    <Z*>;<GREEK>;<SMALL>
<Y*>    <Y*>;<GREEK>;<CAPITAL>
<y*>    <Y*>;<GREEK>;<SMALL>
<Y%>    <Y*>;<ALPHA-1>;<CAPITAL>
<y%>    <Y*>;<ALPHA-1>;<SMALL>
<H*>    <H*>;<GREEK>;<CAPITAL>
<h*>    <H*>;<GREEK>;<SMALL>
<I*>    <I*>;<GREEK>;<CAPITAL>                                  1
<J*>    <I*>;<GREEK>;<CAPITAL>                                  1
<i*>    <I*>;<GREEK>;<SMALL>                                    1
<j*>    <I*>;<GREEK>;<SMALL>                                    1
<I%>    <I*>;<ALPHA-1>;<CAPITAL>                                1
<i%>    <I*>;<ALPHA-1>;<SMALL>                                  1
<K*>    <K*>;<GREEK>;<CAPITAL>                                  1
<k*>    <K*>;<GREEK>;<SMALL>                                    1
<L*>    <L*>;<GREEK>;<CAPITAL>                                  1
<l*>    <L*>;<GREEK>;<SMALL>                                    1
<M*>    <M*>;<GREEK>;<CAPITAL>                                  1
<m*>    <M*>;<GREEK>;<SMALL>                                    1
<N*>    <N*>;<GREEK>;<CAPITAL>                                  1
<n*>    <N*>;<GREEK>;<SMALL>                                    1
<C*>    <C*>;<GREEK>;<CAPITAL>                                  1
<c*>    <C*>;<GREEK>;<SMALL>                                    1
<O*>    <O*>;<GREEK>;<CAPITAL>
<o*>    <O*>;<GREEK>;<SMALL>
<O%>    <O*>;<ALPHA-1>;<CAPITAL>
<o%>    <O*>;<ALPHA-1>;<SMALL>
<P*>    <P*>;<GREEK>;<CAPITAL>
<p*>    <P*>;<GREEK>;<SMALL>
<R*>    <R*>;<GREEK>;<CAPITAL>
<r*>    <R*>;<GREEK>;<SMALL>
<S*>    <S*>;<GREEK>;<CAPITAL>
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<s*>    <S*>;<GREEK>;<SMALL>
<*s>    <S*>;<SPECIAL>;<SMALL>
<T*>    <T*>;<GREEK>;<CAPITAL>
<t*>    <T*>;<GREEK>;<SMALL>
<U*>    <U*>;<GREEK>;<CAPITAL>
<V*>    <U*>;<GREEK>;<CAPITAL>
<u*>    <U*>;<GREEK>;<SMALL>
<v*>    <U*>;<GREEK>;<SMALL>
<U%>    <U*>;<ALPHA-1>;<CAPITAL>
<u%>    <U*>;<ALPHA-1>;<SMALL>
<F*>    <F*>;<GREEK>;<CAPITAL>
<f*>    <F*>;<GREEK>;<SMALL>
<X*>    <X*>;<GREEK>;<CAPITAL>
<x*>    <X*>;<GREEK>;<SMALL>
<Q*>    <Q*>;<GREEK>;<CAPITAL>
<q*>    <Q*>;<GREEK>;<SMALL>
<W*>    <W*>;<GREEK>;<CAPITAL>
<w*>    <W*>;<GREEK>;<SMALL>
<W%>    <W*>;<ALPHA-1>;<CAPITAL>
<w%>    <W*>;<ALPHA-1>;<SMALL>
<p+>
<v+>
<gf>
<H'>
<aM>
<aH>
<wH>
<ah>
<yH>
<a+>
<b+>
<tm>
<t+>
<tk>
<g+>
<hk>
<x+>
<d+>
<dk>
<r+>
<z+>
<s+>
<sn>
<c+>
<dd>
<tj>
<zH>
<e+>
<i+>
<f+>
<q+>
<k+>
<l+>
<m+>
<n+>
<h+>
<w+>
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<j+>
<y+>
<yf>
<A+>
<B+>
<G+>
<D+>
<H+>
<W+>
<Z+>
<X+>
<Tj>
<J+>
<K%>
<K+>
<L+>
<M%>
<M+>
<N%>
<N+>
<S+>
<E+>
<P%>
<P+>
<Zj>
<ZJ>
<Q+>
<R+>
<Sh>
<T+>
<b4>
<p4>
<m4>
<f4>
<d4>
<t4>
<n4>
<l4>
<g4>
<k4>
<h4>
<j4>
<q4>
<x4>
<zh>
<ch>
<sh>
<r4>
<z4>
<c4>
<s4>
<a4>
<o4>
<e4>
<eh>
<ai>
<ei>
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<au>
<ou>
<an>
<en>
<aN>
<eN>
<er>
<i4>
<u4>
<iu>
<A5>
<a5>
<I5>
<i5>
<U5>
<u5>
<E5>
<e5>
<O5>
<o5>
<ka>
<ga>
<ki>
<gi>
<ku>
<gu>
<ke>
<ge>
<ko>
<go>
<sa>
<za>
<si>
<zi>
<su>
<zu>
<se>
<ze>
<so>
<zo>
<ta>
<da>
<ti>
<di>
<tU>
<tu>
<du>
<te>
<de>
<to>
<do>
<na>
<ni>
<nu>
<ne>
<no>
<ha>
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<ba>
<pa>
<hi>
<bi>
<pi>
<hu>
<bu>
<pu>
<he>
<be>
<pe>
<ho>
<bo>
<po>
<ma>
<mi>
<mu>
<me>
<mo>
<yA>
<ya>
<yU>
<yu>
<yO>
<yo>
<ra>
<ri>
<ru>
<re>
<ro>
<wA>
<wa>
<wi>
<we>
<wo>
<n5>
<a6>
<A6>
<i6>
<I6>
<u6>
<U6>
<e6>
<E6>
<o6>
<O6>
<Ka>
<Ga>
<Ki>
<Gi>
<Ku>
<Gu>
<Ke>
<Ge>
<Ko>
<Go>
<Sa>
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<Za>
<Si>
<Zi>
<Su>
<Zu>
<Se>
<Ze>
<So>
<Zo>
<Ta>
<Da>
<Ti>
<Di>
<TU>
<Tu>
<Du>
<Te>
<De>
<To>
<Do>
<Na>
<Ni>
<Nu>
<Ne>
<No>
<Ha>
<Ba>
<Pa>
<Hi>
<Bi>
<Pi>
<Hu>
<Bu>
<Pu>
<He>
<Be>
<Pe>
<Ho>
<Bo>
<Po>
<Ma>
<Mi>
<Mu>
<Me>
<Mo>
<YA>
<Ya>
<YU>
<Yu>
<YO>
<Yo>
<Ra>
<Ri>
<Ru>
<Re>
<Ro>
<WA>
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
1829    <Wa>
1830    <Wi>
1831    <We>
1832    <Wo>
1833    <N6>
1834    <Vu>
1835    <KA>
1836    <KE>

1837    order_end

1838    END LC_COLLATE

1839    LC_MONETARY

1840    % int_curr_symbol according to ISO 4217                                  1
1841    int_curr_symbol         "DKK "                                           1
1842    currency_symbol         "kr."                                            1
1843    mon_decimal_point       <,>
1844    mon_thousands_sep       <.>
1845    mon_grouping            3;0
1846    positive_sign           ""
1847    negative_sign           <->
1848    int_frac_digits         2
1849    frac_digits             2
1850    p_cs_precedes           1
1851    p_sep_by_space          1
1852    n_cs_precedes           1
1853    n_sep_by_space          1
1854    p_sign_posn             4
1855    n_sign_posn             4

1856    END LC_MONETARY

1857    LC_NUMERIC

1858    decimal_point           <,>
1859    thousands_sep           <.>
1860    grouping                3;0

1861    END LC_NUMERIC

1862    LC_TIME

1863    abday       "s<o//>n";"man";"tir";"ons";"tor";"fre";"l<o//>r"             1
1864    day         "s<o//>ndag";"mandag";"tirsdag";"onsdag";/                   1
1865                "torsdag";"fredag";"l<o//>rdag"                              1
1866    abmon       "jan";"feb";"mar";"apr";"maj";"jun";/                        1
1867                "jul";"aug";"sep";"okt";"nov";"dec"                          1
1868    mon         "januar";"februar";"marts";"april";"maj";"juni";/            1
1869                "juli";"august";"september";"oktober";"november";"december"  1
1870    d_t_fmt     "%a %d %b %Y %T %Z"                                          1
1871    d_fmt       "%d %b %Y"                                                   1
1872    t_fmt       "%T"                                                         1

1873    % The AM/PM notation is not used in Denmark and thus not allowed.        1
1874    am_pm       "";""
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
t_fmt_ampm  ""

END LC_TIME

LC_MESSAGES

% Must be careful to avoid interpreting "nej" (no) as "ja" (yes).

% yesexpr     "^[[:blank:]]*[JjYy][[:alpha:]]*"
% noexpr      "^[[:blank:]]*[Nn][[:alpha:]]*"

yesexpr     "<'//><<(><<(>:blank:<)//><)//>*<<(>JjYy<)//>/
<<(><<(>:alpha:<)//><)//>*"
noexpr      "<'//><<(><<(>:blank:<)//><)//>*<<(>Nn<)//>/
<<(><<(>:alpha:<)//><)//>*"

END LC_MESSAGES
```

F.3.2 `fo_DK` — (Example) Faroese `LC_TIME` and `LC_MESSAGES`

```
escape_char  /
comment_char %
% Danish example national locale for the Faroese language
% Source: Danish Standards Association
% Revision: 1.7 1991-04-26
%
% Only LC_TIME and LC_MESSAGES are specified here, else use the da_DK locale

LC_CTYPE
copy da_DK
END LC_CTYPE

LC_COLLATE
copy da_DK
END LC_COLLATE

LC_MONETARY
copy da_DK
END LC_MONETARY

LC_NUMERIC
copy da_DK
END LC_NUMERIC

LC_TIME

abday       "sun";"m<a'>n";"t<y'>s";"mik";"h<o'>s";"fr<i'>";"ley"
day         "sunnudagur";"m<a'>nadagur";"t<y'>sdagur";/
            "mikudagur";"h<o'>sdagur";"fr<i'>ggjadagur";"leygardagur"
abmon       "jan";"feb";"mar";"apr";"mai";"jun";/
            "jul";"aug";"sep";"okt";"nov";"des"
mon         "januar";"februar";"mars";"apr<i'>l";"mai";"juni";/
            "juli";"august";"september";"oktober";"november";"desember"
d_t_fmt     "%a %d %b %Y %T %Z"
d_fmt       "%d %b %Y"
t_fmt       "%T"
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
am_pm       "";""
t_fmt_ampm  ""

END LC_TIME

LC_MESSAGES

% Must be careful to avoid interpreting "nej"/"nei" (no) as "ja" (yes).

% yesexpr     "^[[:blank:]]*[JjYy][[:alpha:]]*"
% noexpr      "^[[:blank:]]*[Nn][[:alpha:]]*"

yesexpr     "<’/>><<(><<(>:blank:<)/>><)/>>*<<(>JjYy<)/>>/
<<(><<(>:alpha:<)/>><)/>>*"
noexpr      "<’/>><<(><<(>:blank:<)/>><)/>>*<<(>Nn<)/>>/
<<(><<(>:alpha:<)/>><)/>>*"

END LC_MESSAGES
```

F.3.3 `kl_DK` — (Example) Greenlandic `LC_TIME` and `LC_MESSAGES`

```
escape_char /
comment_char %
% Danish example national locale for the Greenlandic language
% Source: Danish Standards Association
% Revision: 1.7 1991-04-26
%
% Only LC_TIME and LC_MESSAGES are specified here, else use the da_DK locale

LC_CTYPE
copy da_DK
END LC_CTYPE

LC_COLLATE
copy da_DK
END LC_COLLATE

LC_MONETARY
copy da_DK
END LC_MONETARY

LC_NUMERIC
copy da_DK
END LC_NUMERIC

LC_TIME

abday       "sab";"ata";"mar";"pin";"sis";"tal";"arf"
day         "sabaat";"ataasinngorneq";"marlunngorneq";"pingasunngorneq";/
            "sisamanngorneq";"tallimanngorneq";"arfininngorneq"
abmon       "jan";"feb";"mar";"apr";"maj";"jun";/
            "jul";"aug";"sep";"okt";"nov";"dec"
mon         "januari";"februari";"martsi";"aprili";"maji";"juni";/
            "juli";"augustusi";"septemberi";"oktoberi";"novemberi";"decemberi"
d_t_fmt     "%a %d %b %Y %T %Z"
d_fmt       "%d %b %Y"
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
t_fmt       "%T"
am_pm       "";""
t_fmt_ampm  ""

END LC_TIME

LC_MESSAGES

% Must be careful to avoid interpreting "namik"/"nej" (no) as "aap"/"ja" (yes).

% yesexpr     "^[[:blank:]]*[JjYyAa][[:alpha:]]*"
% noexpr      "^[[:blank:]]*[Nn][[:alpha:]]*"

yesexpr     "<'/>><<(><<(>:blank:<)/>><)/>>*<<(>JjYyAa<)/>>/
<<(><<(>:alpha:<)/>><)/>>*"
noexpr      "<'/>><<(><<(>:blank:<)/>><)/>>*<<(>Nn<)/>>/
<<(><<(>:alpha:<)/>><)/>>*"

END LC_MESSAGES
```

F.4 Character Mnemonics Guidelines

This clause presents guidelines for character mnemonics in a minimal coded character set. These guidelines are used within this sample annex and are recommended for other national profiles.

F.4.1 Aim of Character Mnemonics

The aim of the mnemonics is to be able to represent all characters in all standard coded character sets in any standard coded character set.

The usage of the character mnemonics is primarily intended within computer operating systems, programming languages, and applications and this work with character mnemonics is the current state of work that has been presented to the ISO working group responsible for these computer related issues, namely the ISO/IEC JTC 1/SC22 special working group on coded character set usage.

F.4.2 Covered Coded Character Sets

All characters in the standard coded character sets will be given a mnemonic to be represented in the minimal character set. The minimal coded character set is defined as the basic character set of ISO 646 {1}, where 12 positions are left undefined. The standard coded character sets are taken as the sum of all ISO-defined or ISO-registered coded character sets.

The most significant ISO coded character set is the ISO 10646 {B11} coded character set, whose aim is to code in 32 bits all characters in the world. These guidelines can be seen as assigning mnemonic attributes to most characters in ISO 10646 {B11}, currently at the DIS stage.

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

Other ISO coded character sets covered include all parts of ISO 8859 {B9} ISO 6937-2 {B6}, and all ISO 646 {1} conforming coded character sets in the ISO character set registry managed by ECMA according to ISO 4873 {4}. Some non-ISO coded character sets are also covered for convenience.

F.4.3 Character Mnemonics Classes

The character mnemonics are classified into two groups:

(1) A group with two-character mnemonics—Primarily intended for alphabetic scripts like Latin, Greek, Cyrillian, Hebrew, and Arabic, and special characters.

(2) A group with variable-length mnemonics—Primarily intended for nonalphabetic scripts like Japanese and Chinese. These mnemonics will have a unique lead-in and lead-out symbol.

All mnemonics are given a long descriptive name, written in the reference coded character set and taken from ISO 10646 {B11}, if possible.

F.4.4 Two-Character Mnemonics

The two-character mnemonics include various accented Latin letters, Greek, Cyrillic, Hebrew, Arabic, Hiragana, Katakana, and Bopomofo. Some special characters also are included. Almost all ISO or ISO-registered 7- and 8-bit coded character sets are covered with these two-character mnemonics.

The two characters are chosen so the graphical appearence in the reference set resembles as much as possible (within the possibilities available) the graphical appearance of the character. The basic coded character set of ISO 646 {1} is used as the reference set, as described previously.

The characters in the reference coded character set are chosen to represent themselves. They may be considered as two-character mnemonics where the second character is a space.

Control character mnemonics are chosen according to ISO 2047 {B3} and ISO 6429 {B5}.

Letters, including Greek, Cyrillic, Arabic, and Hebrew, are represented with the base letter as the first letter, and the second letter represents an accent or relation to a non-Latin script. Non-Latin letters are transliterated to Latin letters, following transliteration standards as closely as possible.

After a letter, the second character signifies the following:

exclamation-mark	!	grave	
apostrophe	'	acute accent	
greater-than-sign	>	circumflex accent	

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

question-mark	?	tilde
hyphen-minus	-	macron
left-parenthesis	(	breve
full-stop	.	dot above/ring above
colon	:	diaeresis
comma	,	cedilla
underline	_	underline
solidus	/	stroke
quotation-mark	"	double acute accent
semicolon	;	ogonek
less-than-sign	<	caron
equals	=	Cyrillian
asterisk	*	Greek
percent-sign	%	Greek/Cyrillian special
plus	+	smalls: Arabic, capitals: Hebrew
four	4	Bopomofo
five	5	Hiragana
six	6	Katakana

Special characters are encoded with some mnemonic value. These are not systematic throughout, but most mnemonics start with a special character of the reference set. Special characters with some sort of reference to the reference coded character set normally have this character as the first character in the mnemonic.

F.4.5 Variable-Length Character Mnemonics

The variable-length character mnemonics are meant primarily for the ideographic characters in larger Asian coded character sets. To have the mnemonics as short as possible, which both saves storage and is easier to type, a short name is preferred. Considering the Chinese standard GB 2312 {B14} and the Japanese standards JIS X0208 {B15} and JIS X0212 {B16}, they are all given by row and column numbers between 1 and 99. So two positions for row and column and a coded character set identifier of one character would be almost as short as possible. The following coded character set identifiers are defined:

c	GB 2312 {B14}
j	JIS X0208 {B15}
J	JIS X0212 {B16}
k	KS C 5601 {B17}

The first idea was to have a name in Latin describing the pronunciation, but that is not possible according to Asian sources.

The variable-length character mnemonics can also be used for some Latin letters with more than one accent or other special characters that are used less frequently.

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

F.5 (Example) Danish Charmap Files

The (example) Danish locale is coded character-set independent, as it is defined in terms of symbolic character names. Symbolic character names are defined for about 1 300 characters, covering many coded character sets. It is not necessary to have all these characters present in the actual encoding character set because absent characters simply can be ignored. But specifying the locale with symbolic character names ensures a uniform collating sequence of the present characters, regardless of the encoded character set. The more complicated locale should not imply less efficient code at running time, although generating the locale tables could take a longer time.

Danish Standards provides several charmap files, of which the `ISO_10646` is the prime charmap, as it defines all the character names. It is expected, however, that the `ISO_8859-1` charmap would be of more current interest. The charmaps are quite general, and might be used for other countries' locales without change.

See the guidelines for character mnemonics in F.4 for guidance in reading these charmap files.

F.5.1 `ISO_10646` Charmap

```
# ISO/IEC DIS 10646: 1990 charmap based on ISO/IEC JTC1/SC2/WG2 N666
# Only a part of the 10646 encoding is tabled here

<escape_char> /
<mb_cur_max> 4
CHARMAP
<NUL>                   /d000/d128/d128/d128    NULL (NUL)                      1
<SOH>                   /d001/d128/d128/d128    START OF HEADING (SOH)          1
<STX>                   /d002/d128/d128/d128    START OF TEXT (STX)             1
<ETX>                   /d003/d128/d128/d128    END OF TEXT (ETX)               1
<EOT>                   /d004/d128/d128/d128    END OF TRANSMISSION (EOT)       1
<ENQ>                   /d005/d128/d128/d128    ENQUIRY (ENQ)                   1
<ACK>                   /d006/d128/d128/d128    ACKNOWLEDGE (ACK)               1
<alert>                 /d007/d128/d128/d128    BELL (BEL)                      1
<BEL>                   /d007/d128/d128/d128    BELL (BEL)                      1
<backspace>             /d008/d128/d128/d128    BACKSPACE (BS)                  1
<tab>                   /d009/d128/d128/d128    CHARACTER TABULATION (HT)       1
<newline>               /d010/d128/d128/d128    LINE FEED (LF)                  1
<vertical-tab>          /d011/d128/d128/d128    LINE TABULATION (VT)            1
<form-feed>             /d012/d128/d128/d128    FORM FEED (FF)                  1
<carriage-return>       /d013/d128/d128/d128    CARRIAGE RETURN (CR)            1
<DLE>                   /d016/d128/d128/d128    DATALINK ESCAPE (DLE)           1
<DC1>                   /d017/d128/d128/d128    DEVICE CONTROL ONE (DC1)        1
<DC2>                   /d018/d128/d128/d128    DEVICE CONTROL TWO (DC2)        1
<DC3>                   /d019/d128/d128/d128    DEVICE CONTROL THREE (DC3)      1
<DC4>                   /d020/d128/d128/d128    DEVICE CONTROL FOUR (DC4)       1
<NAK>                   /d021/d128/d128/d128    NEGATIVE ACKNOWLEDGE (NAK)      1
<SYN>                   /d022/d128/d128/d128    SYNCHRONOUS IDLE (SYN)          1
<ETB>                   /d023/d128/d128/d128    END OF TRANSMISSION BLOCK (ETB) 1
<CAN>                   /d024/d128/d128/d128    CANCEL (CAN)                    1
<SUB>                   /d026/d128/d128/d128    SUBSTITUTE (SUB)                1
<ESC>                   /d027/d128/d128/d128    ESCAPE (ESC)                    1
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<IS4>                   /d028/d128/d128/d128    FILE SEPARATOR (IS4)          1
<IS3>                   /d029/d128/d128/d128    GROUP SEPARATOR (IS3)         1
<intro>                 /d029/d128/d128/d128    GROUP SEPARATOR (IS3)         1
<IS2>                   /d030/d128/d128/d128    RECORD SEPARATOR (IS2)        1
<IS1>                   /d031/d128/d128/d128    UNIT SEPARATOR (IS1)          1
<DEL>                   /d127/d128/d128/d128    DELETE (DEL)                  1
<space>                 /d032/d032/d032/d032    SPACE
<exclamation-mark>      /d032/d032/d032/d033    EXCLAMATION MARK
<quotation-mark>        /d032/d032/d032/d034    QUOTATION MARK
<number-sign>           /d032/d032/d032/d035    NUMBER SIGN
<dollar-sign>           /d032/d032/d032/d036    DOLLAR SIGN
<percent-sign>          /d032/d032/d032/d037    PERCENT SIGN
<ampersand>             /d032/d032/d032/d038    AMPERSAND
<apostrophe>            /d032/d032/d032/d039    APOSTROPHE
<left-parenthesis>      /d032/d032/d032/d040    LEFT PARENTHESIS
<right-parenthesis>     /d032/d032/d032/d041    RIGHT PARENTHESIS
<asterisk>              /d032/d032/d032/d042    ASTERISK
<plus-sign>             /d032/d032/d032/d043    PLUS SIGN
<comma>                 /d032/d032/d032/d044    COMMA
<hyphen>                /d032/d032/d032/d045    HYPHEN-MINUS
<hyphen-minus>          /d032/d032/d032/d045    HYPHEN-MINUS
<period>                /d032/d032/d032/d046    FULL STOP
<full-stop>             /d032/d032/d032/d046    FULL STOP
<slash>                 /d032/d032/d032/d047    SOLIDUS
<solidus>               /d032/d032/d032/d047    SOLIDUS
<zero>                  /d032/d032/d032/d048    DIGIT ZERO
<one>                   /d032/d032/d032/d049    DIGIT ONE
<two>                   /d032/d032/d032/d050    DIGIT TWO
<three>                 /d032/d032/d032/d051    DIGIT THREE
<four>                  /d032/d032/d032/d052    DIGIT FOUR
<five>                  /d032/d032/d032/d053    DIGIT FIVE
<six>                   /d032/d032/d032/d054    DIGIT SIX
<seven>                 /d032/d032/d032/d055    DIGIT SEVEN
<eight>                 /d032/d032/d032/d056    DIGIT EIGHT
<nine>                  /d032/d032/d032/d057    DIGIT NINE
<colon>                 /d032/d032/d032/d058    COLON
<semicolon>             /d032/d032/d032/d059    SEMICOLON
<less-than-sign>        /d032/d032/d032/d060    LESS-THAN SIGN
<equals-sign>           /d032/d032/d032/d061    EQUALS SIGN
<greater-than-sign>     /d032/d032/d032/d062    GREATER-THAN SIGN
<question-mark>         /d032/d032/d032/d063    QUESTION MARK
<commercial-at>         /d032/d032/d032/d064    COMMERCIAL AT
<left-square-bracket>   /d032/d032/d032/d091    LEFT SQUARE BRACKET
<reverse-solidus>       /d032/d032/d032/d092    REVERSE SOLIDUS
<backslash>             /d032/d032/d032/d092    REVERSE SOLIDUS
<right-square-bracket>  /d032/d032/d032/d093    RIGHT SQUARE BRACKET
<circumflex-accent>     /d032/d032/d032/d094    CIRCUMFLEX ACCENT
<low-line>              /d032/d032/d032/d095    LOW LINE
<underscore>            /d032/d032/d032/d095    LOW LINE
<grave-accent>          /d032/d032/d032/d096    GRAVE ACCENT
<left-curly-bracket>    /d032/d032/d032/d123    LEFT CURLY BRACKET
<vertical-line>         /d032/d032/d032/d124    VERTICAL LINE
<right-curly-bracket>   /d032/d032/d032/d125    RIGHT CURLY BRACKET
<tilde>                 /d032/d032/d032/d126    TILDE
<SP>    /d032/d032/d032/d032    SPACE
<!>     /d032/d032/d032/d033    EXCLAMATION MARK
<">     /d032/d032/d032/d034    QUOTATION MARK
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<Nb>    /d032/d032/d032/d035    NUMBER SIGN
<DO>    /d032/d032/d032/d036    DOLLAR SIGN
<%>     /d032/d032/d032/d037    PERCENT SIGN
<&>     /d032/d032/d032/d038    AMPERSAND
<'>     /d032/d032/d032/d039    APOSTROPHE
<(>     /d032/d032/d032/d040    LEFT PARENTHESIS
<)>     /d032/d032/d032/d041    RIGHT PARENTHESIS
<*>     /d032/d032/d032/d042    ASTERISK
<+>     /d032/d032/d032/d043    PLUS SIGN
<,>     /d032/d032/d032/d044    COMMA
<->     /d032/d032/d032/d045    HYPHEN-MINUS
<.>     /d032/d032/d032/d046    FULL STOP
<//>    /d032/d032/d032/d047    SOLIDUS
<0>     /d032/d032/d032/d048    DIGIT ZERO
<1>     /d032/d032/d032/d049    DIGIT ONE
<2>     /d032/d032/d032/d050    DIGIT TWO
<3>     /d032/d032/d032/d051    DIGIT THREE
<4>     /d032/d032/d032/d052    DIGIT FOUR
<5>     /d032/d032/d032/d053    DIGIT FIVE
<6>     /d032/d032/d032/d054    DIGIT SIX
<7>     /d032/d032/d032/d055    DIGIT SEVEN
<8>     /d032/d032/d032/d056    DIGIT EIGHT
<9>     /d032/d032/d032/d057    DIGIT NINE
<:>     /d032/d032/d032/d058    COLON
<;>     /d032/d032/d032/d059    SEMICOLON
<<>     /d032/d032/d032/d060    LESS-THAN SIGN
<=>     /d032/d032/d032/d061    EQUALS SIGN
</>>    /d032/d032/d032/d062    GREATER-THAN SIGN
<?>     /d032/d032/d032/d063    QUESTION MARK
<At>    /d032/d032/d032/d064    COMMERCIAL AT
<A>     /d032/d032/d032/d065    LATIN CAPITAL LETTER A
<B>     /d032/d032/d032/d066    LATIN CAPITAL LETTER B
<C>     /d032/d032/d032/d067    LATIN CAPITAL LETTER C
<D>     /d032/d032/d032/d068    LATIN CAPITAL LETTER D
<E>     /d032/d032/d032/d069    LATIN CAPITAL LETTER E
<F>     /d032/d032/d032/d070    LATIN CAPITAL LETTER F
<G>     /d032/d032/d032/d071    LATIN CAPITAL LETTER G
<H>     /d032/d032/d032/d072    LATIN CAPITAL LETTER H
<I>     /d032/d032/d032/d073    LATIN CAPITAL LETTER I
<J>     /d032/d032/d032/d074    LATIN CAPITAL LETTER J
<K>     /d032/d032/d032/d075    LATIN CAPITAL LETTER K
<L>     /d032/d032/d032/d076    LATIN CAPITAL LETTER L
<M>     /d032/d032/d032/d077    LATIN CAPITAL LETTER M
<N>     /d032/d032/d032/d078    LATIN CAPITAL LETTER N
<O>     /d032/d032/d032/d079    LATIN CAPITAL LETTER O
<P>     /d032/d032/d032/d080    LATIN CAPITAL LETTER P
<Q>     /d032/d032/d032/d081    LATIN CAPITAL LETTER Q
<R>     /d032/d032/d032/d082    LATIN CAPITAL LETTER R
<S>     /d032/d032/d032/d083    LATIN CAPITAL LETTER S
<T>     /d032/d032/d032/d084    LATIN CAPITAL LETTER T
<U>     /d032/d032/d032/d085    LATIN CAPITAL LETTER U
<V>     /d032/d032/d032/d086    LATIN CAPITAL LETTER V
<W>     /d032/d032/d032/d087    LATIN CAPITAL LETTER W
<X>     /d032/d032/d032/d088    LATIN CAPITAL LETTER X
<Y>     /d032/d032/d032/d089    LATIN CAPITAL LETTER Y
<Z>     /d032/d032/d032/d090    LATIN CAPITAL LETTER Z
<<(>    /d032/d032/d032/d091    LEFT SQUARE BRACKET
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<////>  /d032/d032/d032/d092    REVERSE SOLIDUS
<)/>>   /d032/d032/d032/d093    RIGHT SQUARE BRACKET
<'/>>   /d032/d032/d032/d094    CIRCUMFLEX ACCENT
<_>     /d032/d032/d032/d095    LOW LINE
<'!>    /d032/d032/d032/d096    GRAVE ACCENT
<a>     /d032/d032/d032/d097    LATIN SMALL LETTER A
<b>     /d032/d032/d032/d098    LATIN SMALL LETTER B
<c>     /d032/d032/d032/d099    LATIN SMALL LETTER C
<d>     /d032/d032/d032/d100    LATIN SMALL LETTER D
<e>     /d032/d032/d032/d101    LATIN SMALL LETTER E
<f>     /d032/d032/d032/d102    LATIN SMALL LETTER F
<g>     /d032/d032/d032/d103    LATIN SMALL LETTER G
<h>     /d032/d032/d032/d104    LATIN SMALL LETTER H
<i>     /d032/d032/d032/d105    LATIN SMALL LETTER I
<j>     /d032/d032/d032/d106    LATIN SMALL LETTER J
<k>     /d032/d032/d032/d107    LATIN SMALL LETTER K
<l>     /d032/d032/d032/d108    LATIN SMALL LETTER L
<m>     /d032/d032/d032/d109    LATIN SMALL LETTER M
<n>     /d032/d032/d032/d110    LATIN SMALL LETTER N
<o>     /d032/d032/d032/d111    LATIN SMALL LETTER O
<p>     /d032/d032/d032/d112    LATIN SMALL LETTER P
<q>     /d032/d032/d032/d113    LATIN SMALL LETTER Q
<r>     /d032/d032/d032/d114    LATIN SMALL LETTER R
<s>     /d032/d032/d032/d115    LATIN SMALL LETTER S
<t>     /d032/d032/d032/d116    LATIN SMALL LETTER T
<u>     /d032/d032/d032/d117    LATIN SMALL LETTER U
<v>     /d032/d032/d032/d118    LATIN SMALL LETTER V
<w>     /d032/d032/d032/d119    LATIN SMALL LETTER W
<x>     /d032/d032/d032/d120    LATIN SMALL LETTER X
<y>     /d032/d032/d032/d121    LATIN SMALL LETTER Y
<z>     /d032/d032/d032/d122    LATIN SMALL LETTER Z
<(!>    /d032/d032/d032/d123    LEFT CURLY BRACKET
<!!>    /d032/d032/d032/d124    VERTICAL LINE
<!)>    /d032/d032/d032/d125    RIGHT CURLY BRACKET
<'?>    /d032/d032/d032/d126    TILDE
<NS>    /d032/d032/d032/d160    NO-BREAK SPACE
<!I>    /d032/d032/d032/d161    INVERTED EXCLAMATION MARK
<Ct>    /d032/d032/d032/d162    CENT SIGN
<Pd>    /d032/d032/d032/d163    POUND SIGN
<Cu>    /d032/d032/d032/d164    CURRENCY SIGN
<Ye>    /d032/d032/d032/d165    YEN SIGN
<BB>    /d032/d032/d032/d166    BROKEN BAR
<SE>    /d032/d032/d032/d167    SECTION SIGN
<':>    /d032/d032/d032/d168    DIAERESIS
<Co>    /d032/d032/d032/d169    COPYRIGHT SIGN
<-a>    /d032/d032/d032/d170    FEMININE ORDINAL INDICATOR
<<<>    /d032/d032/d032/d171    LEFT POINTING DOUBLE ANGLE QUOTATION MARK
<NO>    /d032/d032/d032/d172    NOT SIGN
<-->    /d032/d032/d032/d173    SOFT HYPHEN
<Rg>    /d032/d032/d032/d174    REGISTERED SIGN
<'->    /d032/d032/d032/d175    MACRON
<DG>    /d032/d032/d032/d176    DEGREE SIGN
<+->    /d032/d032/d032/d177    PLUS-MINUS SIGN
<2S>    /d032/d032/d032/d178    SUPERSCRIPT TWO
<3S>    /d032/d032/d032/d179    SUPERSCRIPT THREE
<''>    /d032/d032/d032/d180    ACUTE ACCENT
<My>    /d032/d032/d032/d181    MICRO SIGN
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<PI>     /d032/d032/d032/d182    PILCROW SIGN
<.M>     /d032/d032/d032/d183    MIDDLE DOT
<',>     /d032/d032/d032/d184    CEDILLA
<1S>     /d032/d032/d032/d185    SUPERSCRIPT ONE
<-o>     /d032/d032/d032/d186    MASCULINE ORDINAL INDICATOR
</>>>>   /d032/d032/d032/d187    RIGHT POINTING DOUBLE ANGLE QUOTATION MARK
<14>     /d032/d032/d032/d188    VULGAR FRACTION ONE QUARTER
<12>     /d032/d032/d032/d189    VULGAR FRACTION ONE HALF
<34>     /d032/d032/d032/d190    VULGAR FRACTION THREE QUARTERS
<?I>     /d032/d032/d032/d191    INVERTED QUESTION MARK
<A!>     /d032/d032/d032/d192    LATIN CAPITAL LETTER A WITH GRAVE
<A'>     /d032/d032/d032/d193    LATIN CAPITAL LETTER A WITH ACUTE
<A/>>    /d032/d032/d032/d194    LATIN CAPITAL LETTER A WITH CIRCUMFLEX
<A?>     /d032/d032/d032/d195    LATIN CAPITAL LETTER A WITH TILDE
<A:>     /d032/d032/d032/d196    LATIN CAPITAL LETTER A WITH DIAERESIS
<AA>     /d032/d032/d032/d197    LATIN CAPITAL LETTER A WITH RING ABOVE
<AE>     /d032/d032/d032/d198    LATIN CAPITAL LETTER AE
<C,>     /d032/d032/d032/d199    LATIN CAPITAL LETTER C WITH CEDILLA
<E!>     /d032/d032/d032/d200    LATIN CAPITAL LETTER E WITH GRAVE
<E'>     /d032/d032/d032/d201    LATIN CAPITAL LETTER E WITH ACUTE
<E/>>    /d032/d032/d032/d202    LATIN CAPITAL LETTER E WITH CIRCUMFLEX
<E:>     /d032/d032/d032/d203    LATIN CAPITAL LETTER E WITH DIAERESIS
<I!>     /d032/d032/d032/d204    LATIN CAPITAL LETTER I WITH GRAVE
<I'>     /d032/d032/d032/d205    LATIN CAPITAL LETTER I WITH ACUTE
<I/>>    /d032/d032/d032/d206    LATIN CAPITAL LETTER I WITH CIRCUMFLEX
<I:>     /d032/d032/d032/d207    LATIN CAPITAL LETTER I WITH DIAERESIS
<D->     /d032/d032/d032/d208    LATIN CAPITAL LETTER ETH (Icelandic)
<N?>     /d032/d032/d032/d209    LATIN CAPITAL LETTER N WITH TILDE
<O!>     /d032/d032/d032/d210    LATIN CAPITAL LETTER O WITH GRAVE
<O'>     /d032/d032/d032/d211    LATIN CAPITAL LETTER O WITH ACUTE
<O/>>    /d032/d032/d032/d212    LATIN CAPITAL LETTER O WITH CIRCUMFLEX
<O?>     /d032/d032/d032/d213    LATIN CAPITAL LETTER O WITH TILDE
<O:>     /d032/d032/d032/d214    LATIN CAPITAL LETTER O WITH DIAERESIS
<*X>     /d032/d032/d032/d215    MULTIPLICATION SIGN
<O//>    /d032/d032/d032/d216    LATIN CAPITAL LETTER O WITH STROKE
<U!>     /d032/d032/d032/d217    LATIN CAPITAL LETTER U WITH GRAVE
<U'>     /d032/d032/d032/d218    LATIN CAPITAL LETTER U WITH ACUTE
<U/>>    /d032/d032/d032/d219    LATIN CAPITAL LETTER U WITH CIRCUMFLEX
<U:>     /d032/d032/d032/d220    LATIN CAPITAL LETTER U WITH DIAERESIS
<Y'>     /d032/d032/d032/d221    LATIN CAPITAL LETTER Y WITH ACUTE
<TH>     /d032/d032/d032/d222    LATIN CAPITAL LETTER THORN (Icelandic)
<ss>     /d032/d032/d032/d223    LATIN SMALL LETTER SHARP S (German)
<a!>     /d032/d032/d032/d224    LATIN SMALL LETTER A WITH GRAVE
<a'>     /d032/d032/d032/d225    LATIN SMALL LETTER A WITH ACUTE
<a/>>    /d032/d032/d032/d226    LATIN SMALL LETTER A WITH CIRCUMFLEX
<a?>     /d032/d032/d032/d227    LATIN SMALL LETTER A WITH TILDE
<a:>     /d032/d032/d032/d228    LATIN SMALL LETTER A WITH DIAERESIS
<aa>     /d032/d032/d032/d229    LATIN SMALL LETTER A WITH RING ABOVE
<ae>     /d032/d032/d032/d230    LATIN SMALL LETTER AE
<c,>     /d032/d032/d032/d231    LATIN SMALL LETTER C WITH CEDILLA
<e!>     /d032/d032/d032/d232    LATIN SMALL LETTER E WITH GRAVE
<e'>     /d032/d032/d032/d233    LATIN SMALL LETTER E WITH ACUTE
<e/>>    /d032/d032/d032/d234    LATIN SMALL LETTER E WITH CIRCUMFLEX
<e:>     /d032/d032/d032/d235    LATIN SMALL LETTER E WITH DIAERESIS
<i!>     /d032/d032/d032/d236    LATIN SMALL LETTER I WITH GRAVE
<i'>     /d032/d032/d032/d237    LATIN SMALL LETTER I WITH ACUTE
<i/>>    /d032/d032/d032/d238    LATIN SMALL LETTER I WITH CIRCUMFLEX
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<i:>    /d032/d032/d032/d239    LATIN SMALL LETTER I WITH DIAERESIS
<d->    /d032/d032/d032/d240    LATIN SMALL LETTER ETH (Icelandic)
<n?>    /d032/d032/d032/d241    LATIN SMALL LETTER N WITH TILDE
<o!>    /d032/d032/d032/d242    LATIN SMALL LETTER O WITH GRAVE
<o'>    /d032/d032/d032/d243    LATIN SMALL LETTER O WITH ACUTE
<o/>>   /d032/d032/d032/d244    LATIN SMALL LETTER O WITH CIRCUMFLEX
<o?>    /d032/d032/d032/d245    LATIN SMALL LETTER O WITH TILDE
<o:>    /d032/d032/d032/d246    LATIN SMALL LETTER O WITH DIAERESIS
<-:>    /d032/d032/d032/d247    DIVISION SIGN
<o//>   /d032/d032/d032/d248    LATIN SMALL LETTER O WITH STROKE
<u!>    /d032/d032/d032/d249    LATIN SMALL LETTER U WITH GRAVE
<u'>    /d032/d032/d032/d250    LATIN SMALL LETTER U WITH ACUTE
<u/>>   /d032/d032/d032/d251    LATIN SMALL LETTER U WITH CIRCUMFLEX
<u:>    /d032/d032/d032/d252    LATIN SMALL LETTER U WITH DIAERESIS
<y'>    /d032/d032/d032/d253    LATIN SMALL LETTER Y WITH ACUTE
<th>    /d032/d032/d032/d254    LATIN SMALL LETTER THORN (Icelandic)
<y:>    /d032/d032/d032/d255    LATIN SMALL LETTER Y WITH DIAERESIS
<A->    /d032/d032/d033/d033    LATIN CAPITAL LETTER A WITH MACRON
<C/>>   /d032/d032/d033/d034    LATIN CAPITAL LETTER C WITH CIRCUMFLEX
<C.>    /d032/d032/d033/d035    LATIN CAPITAL LETTER C WITH DOT ABOVE
<E->    /d032/d032/d033/d036    LATIN CAPITAL LETTER E WITH MACRON
<E.>    /d032/d032/d033/d037    LATIN CAPITAL LETTER E WITH DOT ABOVE
<G/>>   /d032/d032/d033/d039    LATIN CAPITAL LETTER G WITH CIRCUMFLEX
<'6>    /d032/d032/d033/d041    LEFT SINGLE QUOTATION MARK
<"6>    /d032/d032/d033/d042    LEFT DOUBLE QUOTATION MARK
<G(>    /d032/d032/d033/d043    LATIN CAPITAL LETTER G WITH BREVE
<<->    /d032/d032/d033/d044    LEFTWARD ARROW
<-!>    /d032/d032/d033/d045    UPWARD ARROW
<-/>>   /d032/d032/d033/d046    RIGHTWARD ARROW
<-v>    /d032/d032/d033/d047    DOWNWARD ARROW
<a->    /d032/d032/d033/d049    LATIN SMALL LETTER A WITH MACRON
<c/>>   /d032/d032/d033/d050    LATIN SMALL LETTER C WITH CIRCUMFLEX
<c.>    /d032/d032/d033/d051    LATIN SMALL LETTER C WITH DOT ABOVE
<e->    /d032/d032/d033/d052    LATIN SMALL LETTER E WITH MACRON
<e.>    /d032/d032/d033/d053    LATIN SMALL LETTER E WITH DOT ABOVE
<g/>>   /d032/d032/d033/d055    LATIN SMALL LETTER G WITH CIRCUMFLEX
<'9>    /d032/d032/d033/d057    RIGHT SINGLE QUOTATION MARK
<"9>    /d032/d032/d033/d058    RIGHT DOUBLE QUOTATION MARK
<g(>    /d032/d032/d033/d059    LATIN SMALL LETTER G WITH BREVE
<G.>    /d032/d032/d033/d065    LATIN CAPITAL LETTER G WITH DOT ABOVE
<G,>    /d032/d032/d033/d066    LATIN CAPITAL LETTER G WITH CEDILLA
<H/>>   /d032/d032/d033/d067    LATIN CAPITAL LETTER H WITH CIRCUMFLEX
<I?>    /d032/d032/d033/d070    LATIN CAPITAL LETTER I WITH TILDE
<I->    /d032/d032/d033/d071    LATIN CAPITAL LETTER I WITH MACRON
<I.>    /d032/d032/d033/d072    LATIN CAPITAL LETTER I WITH DOT ABOVE
<'0>    /d032/d032/d033/d074    RING ABOVE
<HB>    /d032/d032/d033/d080    HORIZONTAL BAR
<g.>    /d032/d032/d033/d081    LATIN SMALL LETTER G WITH DOT ABOVE
<g,>    /d032/d032/d033/d082    LATIN SMALL LETTER G WITH CEDILLA
<h/>>   /d032/d032/d033/d083    LATIN SMALL LETTER H WITH CIRCUMFLEX
<TM>    /d032/d032/d033/d084    TRADE MARK SIGN
<Md>    /d032/d032/d033/d085    MUSIC NOTE
<i?>    /d032/d032/d033/d086    LATIN SMALL LETTER I WITH TILDE
<i->    /d032/d032/d033/d087    LATIN SMALL LETTER I WITH MACRON
<18>    /d032/d032/d033/d092    VULGAR FRACTION ONE EIGHTH
<38>    /d032/d032/d033/d093    VULGAR FRACTION THREE EIGHTHS
<58>    /d032/d032/d033/d094    VULGAR FRACTION FIVE EIGHTHS
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<78>    /d032/d032/d033/d095    VULGAR FRACTION SEVEN EIGHTHS
<Om>    /d032/d032/d033/d096    OHM SIGN
<I;>    /d032/d032/d033/d097    LATIN CAPITAL LETTER I WITH OGONEK
<J/>>   /d032/d032/d033/d098    LATIN CAPITAL LETTER J WITH CIRCUMFLEX
<K,>    /d032/d032/d033/d099    LATIN CAPITAL LETTER K WITH CEDILLA
<H//>   /d032/d032/d033/d100    LATIN CAPITAL LETTER H WITH STROKE
<IJ>    /d032/d032/d033/d102    LATIN CAPITAL LIGATURE IJ
<L.>    /d032/d032/d033/d103    LATIN CAPITAL LETTER L WITH MIDDLE DOT
<L,>    /d032/d032/d033/d104    LATIN CAPITAL LETTER L WITH CEDILLA
<N,>    /d032/d032/d033/d105    LATIN CAPITAL LETTER N WITH CEDILLA
<OE>    /d032/d032/d033/d106    LATIN CAPITAL LIGATURE OE
<O->    /d032/d032/d033/d107    LATIN CAPITAL LETTER O WITH MACRON
<T//>   /d032/d032/d033/d109    LATIN CAPITAL LETTER T WITH STROKE
<NG>    /d032/d032/d033/d110    LATIN CAPITAL LETTER ENG (Lappish)
<'n>    /d032/d032/d033/d111    LATIN SMALL LETTER N PRECEDED BY APOSTROPHE
<kk>    /d032/d032/d033/d112    LATIN SMALL LETTER KRA (Greenlandic)
<i;>    /d032/d032/d033/d113    LATIN SMALL LETTER I WITH OGONEK
<j/>>   /d032/d032/d033/d114    LATIN SMALL LETTER J WITH CIRCUMFLEX
<k,>    /d032/d032/d033/d115    LATIN SMALL LETTER K WITH CEDILLA
<h//>   /d032/d032/d033/d116    LATIN SMALL LETTER H WITH STROKE
<i.>    /d032/d032/d033/d117    LATIN SMALL LETTER I WITH NO DOT
<ij>    /d032/d032/d033/d118    LATIN SMALL LIGATURE IJ
<l.>    /d032/d032/d033/d119    LATIN SMALL LETTER L WITH MIDDLE DOT
<l,>    /d032/d032/d033/d120    LATIN SMALL LETTER L WITH CEDILLA
<n,>    /d032/d032/d033/d121    LATIN SMALL LETTER N WITH CEDILLA
<oe>    /d032/d032/d033/d122    LATIN SMALL LIGATURE OE
<o->    /d032/d032/d033/d123    LATIN SMALL LETTER O WITH MACRON
<t//>   /d032/d032/d033/d125    LATIN SMALL LETTER T WITH STROKE
<ng>    /d032/d032/d033/d126    LATIN SMALL LETTER ENG
<A;>    /d032/d032/d033/d161    LATIN CAPITAL LETTER A WITH OGONEK
<'(>    /d032/d032/d033/d162    BREVE
<L//>   /d032/d032/d033/d163    LATIN CAPITAL LETTER L WITH STROKE
<L<>    /d032/d032/d033/d165    LATIN CAPITAL LETTER L WITH CARON
<S'>    /d032/d032/d033/d166    LATIN CAPITAL LETTER S WITH ACUTE
<S/>>   /d032/d032/d033/d168    LATIN CAPITAL LETTER S WITH CIRCUMFLEX
<S<>    /d032/d032/d033/d169    LATIN CAPITAL LETTER S WITH CARON
<S,>    /d032/d032/d033/d170    LATIN CAPITAL LETTER S WITH CEDILLA
<T<>    /d032/d032/d033/d171    LATIN CAPITAL LETTER T WITH CARON
<Z'>    /d032/d032/d033/d172    LATIN CAPITAL LETTER Z WITH ACUTE
<Z<>    /d032/d032/d033/d174    LATIN CAPITAL LETTER Z WITH CARON
<Z.>    /d032/d032/d033/d175    LATIN CAPITAL LETTER Z WITH DOT ABOVE
<a;>    /d032/d032/d033/d177    LATIN SMALL LETTER A WITH OGONEK
<';>    /d032/d032/d033/d178    OGONEK
<l//>   /d032/d032/d033/d179    LATIN SMALL LETTER L WITH STROKE
<l<>    /d032/d032/d033/d181    LATIN SMALL LETTER L WITH CARON
<s'>    /d032/d032/d033/d182    LATIN SMALL LETTER S WITH ACUTE
<'<>    /d032/d032/d033/d183    CARON
<s/>>   /d032/d032/d033/d184    LATIN SMALL LETTER S WITH CIRCUMFLEX
<s<>    /d032/d032/d033/d185    LATIN SMALL LETTER S WITH CARON
<s,>    /d032/d032/d033/d186    LATIN SMALL LETTER S WITH CEDILLA
<t<>    /d032/d032/d033/d187    LATIN SMALL LETTER T WITH CARON
<z'>    /d032/d032/d033/d188    LATIN SMALL LETTER Z WITH ACUTE
<'">    /d032/d032/d033/d189    DOUBLE ACUTE ACCENT
<z<>    /d032/d032/d033/d190    LATIN SMALL LETTER Z WITH CARON
<z.>    /d032/d032/d033/d191    LATIN SMALL LETTER Z WITH DOT ABOVE
<R'>    /d032/d032/d033/d192    LATIN CAPITAL LETTER R WITH ACUTE
<R,>    /d032/d032/d033/d193    LATIN CAPITAL LETTER R WITH CEDILLA
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<A(>    /d032/d032/d033/d195    LATIN CAPITAL LETTER A WITH BREVE
<L'>    /d032/d032/d033/d197    LATIN CAPITAL LETTER L WITH ACUTE
<C'>    /d032/d032/d033/d198    LATIN CAPITAL LETTER C WITH ACUTE
<C<>    /d032/d032/d033/d200    LATIN CAPITAL LETTER C WITH CARON
<E;>    /d032/d032/d033/d202    LATIN CAPITAL LETTER E WITH OGONEK
<E<>    /d032/d032/d033/d204    LATIN CAPITAL LETTER E WITH CARON
<D<>    /d032/d032/d033/d207    LATIN CAPITAL LETTER D WITH CARON
<D//>   /d032/d032/d033/d208    LATIN CAPITAL LETTER D WITH STROKE
<N'>    /d032/d032/d033/d209    LATIN CAPITAL LETTER N WITH ACUTE
<N<>    /d032/d032/d033/d210    LATIN CAPITAL LETTER N WITH CARON
<U?>    /d032/d032/d033/d212    LATIN CAPITAL LETTER U WITH TILDE
<O">    /d032/d032/d033/d213    LATIN CAPITAL LETTER O WITH DOUBLE ACUTE
<U->    /d032/d032/d033/d214    LATIN CAPITAL LETTER U WITH MACRON
<U(>    /d032/d032/d033/d215    LATIN CAPITAL LETTER U WITH BREVE
<R<>    /d032/d032/d033/d216    LATIN CAPITAL LETTER R WITH CARON
<U0>    /d032/d032/d033/d217    LATIN CAPITAL LETTER U WITH RING ABOVE          1
<U;>    /d032/d032/d033/d218    LATIN CAPITAL LETTER U WITH OGONEK
<U">    /d032/d032/d033/d219    LATIN CAPITAL LETTER U WITH DOUBLE ACUTE
<W/>>   /d032/d032/d033/d220    LATIN CAPITAL LETTER W WITH CIRCUMFLEX
<Y/>>   /d032/d032/d033/d221    LATIN CAPITAL LETTER Y WITH CIRCUMFLEX
<T,>    /d032/d032/d033/d222    LATIN CAPITAL LETTER T WITH CEDILLA
<Y:>    /d032/d032/d033/d223    LATIN CAPITAL LETTER Y WITH DIAERESIS
<r'>    /d032/d032/d033/d224    LATIN SMALL LETTER R WITH ACUTE
<r,>    /d032/d032/d033/d225    LATIN SMALL LETTER R WITH CEDILLA
<a(>    /d032/d032/d033/d227    LATIN SMALL LETTER A WITH BREVE
<l'>    /d032/d032/d033/d229    LATIN SMALL LETTER L WITH ACUTE
<c'>    /d032/d032/d033/d230    LATIN SMALL LETTER C WITH ACUTE
<c<>    /d032/d032/d033/d232    LATIN SMALL LETTER C WITH CARON
<e;>    /d032/d032/d033/d234    LATIN SMALL LETTER E WITH OGONEK
<e<>    /d032/d032/d033/d236    LATIN SMALL LETTER E WITH CARON
<d<>    /d032/d032/d033/d239    LATIN SMALL LETTER D WITH CARON
<d//>   /d032/d032/d033/d240    LATIN SMALL LETTER D WITH STROKE
<n'>    /d032/d032/d033/d241    LATIN SMALL LETTER N WITH ACUTE
<n<>    /d032/d032/d033/d242    LATIN SMALL LETTER N WITH CARON
<u?>    /d032/d032/d033/d244    LATIN SMALL LETTER U WITH TILDE
<o">    /d032/d032/d033/d245    LATIN SMALL LETTER O WITH DOUBLE ACUTE
<u->    /d032/d032/d033/d246    LATIN SMALL LETTER U WITH MACRON
<u(>    /d032/d032/d033/d247    LATIN SMALL LETTER U WITH BREVE
<r<>    /d032/d032/d033/d248    LATIN SMALL LETTER R WITH CARON
<u0>    /d032/d032/d033/d249    LATIN SMALL LETTER U WITH RING ABOVE          1
<u;>    /d032/d032/d033/d250    LATIN SMALL LETTER U WITH OGONEK
<u">    /d032/d032/d033/d251    LATIN SMALL LETTER U WITH DOUBLE ACUTE
<w/>>   /d032/d032/d033/d252    LATIN SMALL LETTER W WITH CIRCUMFLEX
<y/>>   /d032/d032/d033/d253    LATIN SMALL LETTER Y WITH CIRCUMFLEX
<t,>    /d032/d032/d033/d254    LATIN SMALL LETTER T WITH CEDILLA
<'.>    /d032/d032/d033/d255    DOT ABOVE
<a<>    /d032/d032/d034/d032    LATIN SMALL LETTER A WITH CARON
<A<>    /d032/d032/d034/d033    LATIN CAPITAL LETTER A WITH CARON
<a_>    /d032/d032/d034/d034    LATIN SMALL LETTER A WITH LINE BELOW
<A_>    /d032/d032/d034/d035    LATIN CAPITAL LETTER A WITH LINE BELOW
<'a>    /d032/d032/d034/d048    LATIN SMALL LETTER A PRECEDED BY APOSTROPHE
<'A>    /d032/d032/d034/d049    LATIN CAPITAL LETTER A PRECEDED BY APOSTROPHE
<a1>    /d032/d032/d034/d052    LATIN SMALL LETTER A WITH MACRON AND DIAERESIS
<A1>    /d032/d032/d034/d053    LATIN CAPITAL LETTER A WITH MACRON AND DIAERESIS
<a2>    /d032/d032/d034/d054    LATIN SMALL LETTER A WITH MACRON AND DOT ABOVE
<A2>    /d032/d032/d034/d055    LATIN CAPITAL LETTER A WITH MACRON AND DOT ABOVE
<a3>    /d032/d032/d034/d056    LATIN SMALL LETTER AE WITH MACRON
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<A3>    /d032/d032/d034/d057    LATIN CAPITAL LETTER AE WITH MACRON
<b.>    /d032/d032/d034/d086    LATIN SMALL LETTER B WITH DOT ABOVE
<B.>    /d032/d032/d034/d087    LATIN CAPITAL LETTER B WITH DOT ABOVE
<b_>    /d032/d032/d034/d088    LATIN SMALL LETTER B WITH LINE BELOW
<B_>    /d032/d032/d034/d089    LATIN CAPITAL LETTER B WITH LINE BELOW
<d_>    /d032/d032/d034/d096    LATIN SMALL LETTER D WITH LINE BELOW
<D_>    /d032/d032/d034/d097    LATIN CAPITAL LETTER D WITH LINE BELOW
<d.>    /d032/d032/d034/d098    LATIN SMALL LETTER D WITH DOT BELOW
<D.>    /d032/d032/d034/d099    LATIN CAPITAL LETTER D WITH DOT BELOW
<d;>    /d032/d032/d034/d100    LATIN SMALL LETTER D WITH OGONEK
<D;>    /d032/d032/d034/d101    LATIN CAPITAL LETTER D WITH OGONEK
<e(>    /d032/d032/d034/d106    LATIN SMALL LETTER E WITH BREVE
<E(>    /d032/d032/d034/d107    LATIN CAPITAL LETTER E WITH BREVE
<e_>    /d032/d032/d034/d108    LATIN SMALL LETTER E WITH LINE BELOW
<E_>    /d032/d032/d034/d109    LATIN CAPITAL LETTER E WITH LINE BELOW
<;S>    /d032/d032/d034/d126    HIGH OGONEK
<e?>    /d032/d032/d034/d168    LATIN SMALL LETTER E WITH TILDE
<E?>    /d032/d032/d034/d169    LATIN CAPITAL LETTER E WITH TILDE
<f.>    /d032/d032/d034/d180    LATIN SMALL LETTER F WITH DOT ABOVE
<F.>    /d032/d032/d034/d181    LATIN CAPITAL LETTER F WITH DOT ABOVE
<g<>    /d032/d032/d034/d182    LATIN SMALL LETTER G WITH CARON
<G<>    /d032/d032/d034/d183    LATIN CAPITAL LETTER G WITH CARON
<g->    /d032/d032/d034/d184    LATIN SMALL LETTER G WITH MACRON
<G->    /d032/d032/d034/d185    LATIN CAPITAL LETTER G WITH MACRON
<g//>   /d032/d032/d034/d188    LATIN SMALL LETTER G WITH STROKE
<G//>   /d032/d032/d034/d189    LATIN CAPITAL LETTER G WITH STROKE
<h:>    /d032/d032/d034/d192    LATIN SMALL LETTER H WITH DIAERESIS
<H:>    /d032/d032/d034/d193    LATIN CAPITAL LETTER H WITH DIAERESIS
<h.>    /d032/d032/d034/d194    LATIN SMALL LETTER H WITH DOT ABOVE
<H.>    /d032/d032/d034/d195    LATIN CAPITAL LETTER H WITH DOT ABOVE
<h,>    /d032/d032/d034/d196    LATIN SMALL LETTER H WITH CEDILLA
<H,>    /d032/d032/d034/d197    LATIN CAPITAL LETTER H WITH CEDILLA
<h;>    /d032/d032/d034/d198    LATIN SMALL LETTER H WITH OGONEK
<H;>    /d032/d032/d034/d199    LATIN CAPITAL LETTER H WITH OGONEK
<i<>    /d032/d032/d034/d204    LATIN SMALL LETTER I WITH CARON
<I<>    /d032/d032/d034/d205    LATIN CAPITAL LETTER I WITH CARON
<i(>    /d032/d032/d034/d206    LATIN SMALL LETTER I WITH BREVE
<I(>    /d032/d032/d034/d207    LATIN CAPITAL LETTER I WITH BREVE
<j(>    /d032/d032/d034/d224    LATIN SMALL LETTER J WITH BREVE
<J(>    /d032/d032/d034/d225    LATIN CAPITAL LETTER J WITH BREVE
<k'>    /d032/d032/d034/d226    LATIN SMALL LETTER K WITH ACUTE
<K'>    /d032/d032/d034/d227    LATIN CAPITAL LETTER K WITH ACUTE
<k<>    /d032/d032/d034/d228    LATIN SMALL LETTER K WITH CARON
<K<>    /d032/d032/d034/d229    LATIN CAPITAL LETTER K WITH CARON
<k_>    /d032/d032/d034/d230    LATIN SMALL LETTER K WITH LINE BELOW
<K_>    /d032/d032/d034/d231    LATIN CAPITAL LETTER K WITH LINE BELOW
<k.>    /d032/d032/d034/d232    LATIN SMALL LETTER K WITH DOT BELOW
<K.>    /d032/d032/d034/d233    LATIN CAPITAL LETTER K WITH DOT BELOW
<k;>    /d032/d032/d034/d234    LATIN SMALL LETTER K WITH OGONEK
<K;>    /d032/d032/d034/d235    LATIN CAPITAL LETTER K WITH OGONEK
<l_>    /d032/d032/d034/d240    LATIN SMALL LETTER L WITH LINE BELOW
<L_>    /d032/d032/d034/d241    LATIN CAPITAL LETTER L WITH LINE BELOW
<m'>    /d032/d032/d034/d248    LATIN SMALL LETTER M WITH ACUTE
<M'>    /d032/d032/d034/d249    LATIN CAPITAL LETTER M WITH ACUTE
<m.>    /d032/d032/d034/d250    LATIN SMALL LETTER M WITH DOT ABOVE
<M.>    /d032/d032/d034/d251    LATIN CAPITAL LETTER M WITH DOT ABOVE
<n.>    /d032/d032/d035/d034    LATIN SMALL LETTER N WITH DOT ABOVE
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<N.>    /d032/d032/d035/d035    LATIN CAPITAL LETTER N WITH DOT ABOVE
<n_>    /d032/d032/d035/d038    LATIN SMALL LETTER N WITH LINE BELOW
<N_>    /d032/d032/d035/d039    LATIN CAPITAL LETTER N WITH LINE BELOW
<o<>    /d032/d032/d035/d046    LATIN SMALL LETTER O WITH CARON
<O<>    /d032/d032/d035/d047    LATIN CAPITAL LETTER O WITH CARON
<o(>    /d032/d032/d035/d048    LATIN SMALL LETTER O WITH BREVE
<O(>    /d032/d032/d035/d049    LATIN CAPITAL LETTER O WITH BREVE
<o_>    /d032/d032/d035/d050    LATIN SMALL LETTER O WITH LINE BELOW
<O_>    /d032/d032/d035/d051    LATIN CAPITAL LETTER O WITH LINE BELOW
<o;>    /d032/d032/d035/d064    LATIN SMALL LETTER O WITH OGONEK
<O;>    /d032/d032/d035/d065    LATIN CAPITAL LETTER O WITH OGONEK
<o1>    /d032/d032/d035/d068    LATIN SMALL LETTER O WITH MACRON AND OGONEK
<O1>    /d032/d032/d035/d069    LATIN CAPITAL LETTER O WITH MACRON AND OGONEK
<p'>    /d032/d032/d035/d098    LATIN SMALL LETTER P WITH ACUTE
<P'>    /d032/d032/d035/d099    LATIN CAPITAL LETTER P WITH ACUTE
<r.>    /d032/d032/d035/d100    LATIN SMALL LETTER R WITH DOT ABOVE
<R.>    /d032/d032/d035/d101    LATIN CAPITAL LETTER R WITH DOT ABOVE
<r_>    /d032/d032/d035/d102    LATIN SMALL LETTER R WITH LINE BELOW
<R_>    /d032/d032/d035/d103    LATIN CAPITAL LETTER R WITH LINE BELOW
<s.>    /d032/d032/d035/d110    LATIN SMALL LETTER S WITH DOT ABOVE
<S.>    /d032/d032/d035/d111    LATIN CAPITAL LETTER S WITH DOT ABOVE
<s;>    /d032/d032/d035/d114    LATIN SMALL LETTER S WITH OGONEK
<S;>    /d032/d032/d035/d115    LATIN CAPITAL LETTER S WITH OGONEK
<t_>    /d032/d032/d035/d160    LATIN SMALL LETTER T WITH LINE BELOW
<T_>    /d032/d032/d035/d161    LATIN CAPITAL LETTER T WITH LINE BELOW
<t.>    /d032/d032/d035/d162    LATIN SMALL LETTER T WITH DOT BELOW
<T.>    /d032/d032/d035/d163    LATIN CAPITAL LETTER T WITH DOT BELOW
<u<>    /d032/d032/d035/d170    LATIN SMALL LETTER U WITH CARON
<U<>    /d032/d032/d035/d171    LATIN CAPITAL LETTER U WITH CARON
<v?>    /d032/d032/d035/d214    LATIN SMALL LETTER V WITH TILDE
<V?>    /d032/d032/d035/d215    LATIN CAPITAL LETTER V WITH TILDE
<w'>    /d032/d032/d035/d220    LATIN SMALL LETTER W WITH ACUTE
<W'>    /d032/d032/d035/d221    LATIN CAPITAL LETTER W WITH ACUTE
<w.>    /d032/d032/d035/d222    LATIN SMALL LETTER W WITH DOT ABOVE
<W.>    /d032/d032/d035/d223    LATIN CAPITAL LETTER W WITH DOT ABOVE
<w:>    /d032/d032/d035/d224    LATIN SMALL LETTER W WITH DIAERESIS
<W:>    /d032/d032/d035/d225    LATIN CAPITAL LETTER W WITH DIAERESIS
<x.>    /d032/d032/d035/d230    LATIN SMALL LETTER X WITH DOT ABOVE
<X.>    /d032/d032/d035/d231    LATIN CAPITAL LETTER X WITH DOT ABOVE
<x:>    /d032/d032/d035/d232    LATIN SMALL LETTER X WITH DIAERESIS
<X:>    /d032/d032/d035/d233    LATIN CAPITAL LETTER X WITH DIAERESIS
<y!>    /d032/d032/d035/d236    LATIN SMALL LETTER Y WITH GRAVE
<Y!>    /d032/d032/d035/d237    LATIN CAPITAL LETTER Y WITH GRAVE
<y.>    /d032/d032/d035/d238    LATIN SMALL LETTER Y WITH DOT ABOVE
<Y.>    /d032/d032/d035/d239    LATIN CAPITAL LETTER Y WITH DOT ABOVE
<z/>>   /d032/d032/d035/d244    LATIN SMALL LETTER Z WITH CIRCUMFLEX
<Z/>>   /d032/d032/d035/d245    LATIN CAPITAL LETTER Z WITH CIRCUMFLEX
<z(>    /d032/d032/d035/d246    LATIN SMALL LETTER Z WITH BREVE
<Z(>    /d032/d032/d035/d247    LATIN CAPITAL LETTER Z WITH BREVE
<z_>    /d032/d032/d035/d248    LATIN SMALL LETTER Z WITH LINE BELOW
<Z_>    /d032/d032/d035/d249    LATIN CAPITAL LETTER Z WITH LINE BELOW
<z//>   /d032/d032/d035/d252    LATIN SMALL LETTER Z WITH STROKE
<Z//>   /d032/d032/d035/d253    LATIN CAPITAL LETTER Z WITH STROKE
<ez>    /d032/d032/d035/d254    LATIN SMALL LETTER EZH WITH CARON
<EZ>    /d032/d032/d035/d255    LATIN CAPITAL LETTER EZH WITH CARON
<g'>    /d032/d032/d036/d033    LATIN SMALL LETTER G WITH ACUTE
<G'>    /d032/d032/d036/d034    LATIN CAPITAL LETTER G WITH ACUTE
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<'b>    /d032/d032/d036/d084    LATIN SMALL LETTER B PRECEDED BY APOSTROPHE
<'B>    /d032/d032/d036/d085    LATIN CAPITAL LETTER B PRECEDED BY APOSTROPHE
<'d>    /d032/d032/d036/d096    LATIN SMALL LETTER D PRECEDED BY APOSTROPHE
<'D>    /d032/d032/d036/d097    LATIN CAPITAL LETTER D PRECEDED BY APOSTROPHE
<'g>    /d032/d032/d036/d162    LATIN SMALL LETTER G PRECEDED BY APOSTROPHE
<'G>    /d032/d032/d036/d163    LATIN CAPITAL LETTER G PRECEDED BY APOSTROPHE
<'j>    /d032/d032/d036/d174    LATIN SMALL LETTER J PRECEDED BY APOSTROPHE
<'J>    /d032/d032/d036/d175    LATIN CAPITAL LETTER J PRECEDED BY APOSTROPHE
<'y>    /d032/d032/d036/d235    LATIN SMALL LETTER Y PRECEDED BY APOSTROPHE
<'Y>    /d032/d032/d036/d236    LATIN CAPITAL LETTER Y PRECEDED BY APOSTROPHE
<ed>    /d032/d032/d036/d239    LATIN SMALL LETTER EDZ
<ED>    /d032/d032/d036/d240    LATIN CAPITAL LETTER EDZ
<Vs>    /d032/d032/d037/d032    SPACE SYMBOL
<1M>    /d032/d032/d037/d033    EM-SPACE
<1N>    /d032/d032/d037/d034    EN-SPACE
<3M>    /d032/d032/d037/d035    THREE-PER-EM SPACE
<4M>    /d032/d032/d037/d036    FOUR-PER-EM SPACE
<6M>    /d032/d032/d037/d037    SIX-PER-EM SPACE
<1H>    /d032/d032/d037/d038    HAIR SPACE
<1T>    /d032/d032/d037/d039    THIN SPACE
<-1>    /d032/d032/d037/d040    HYPHEN
<-N>    /d032/d032/d037/d041    EN-DASH
<-2>    /d032/d032/d037/d042    MINUS SIGN
<-M>    /d032/d032/d037/d043    EM-DASH
<-3>    /d032/d032/d037/d044    QUOTATION DASH
<'1>    /d032/d032/d037/d045    SINGLE PRIME
<'2>    /d032/d032/d037/d046    DOUBLE PRIME
<'3>    /d032/d032/d037/d047    TRIPLE PRIME
<9'>    /d032/d032/d037/d048    SINGLE HIGH-REVERSED-9 QUOTATION MARK
<9">    /d032/d032/d037/d049    DOUBLE HIGH-REVERSED-9 QUOTATION MARK
<.9>    /d032/d032/d037/d050    SINGLE LOW-9 QUOTATION MARK
<:9>    /d032/d032/d037/d051    DOUBLE LOW-9 QUOTATION MARK
<<1>    /d032/d032/d037/d052    SINGLE LEFT-POINTING ANGLE QUOTATION MARK
</>1>   /d032/d032/d037/d053    SINGLE RIGHT-POINTING ANGLE QUOTATION MARK
<<//>   /d032/d032/d037/d054    LEFT-POINTING ANGLE BRACKET
<///>>  /d032/d032/d037/d055    RIGHT-POINTING ANGLE BRACKET
<15>    /d032/d032/d037/d056    VULGAR FRACTION ONE FIFTH
<25>    /d032/d032/d037/d057    VULGAR FRACTION TWO FIFTHS
<35>    /d032/d032/d037/d058    VULGAR FRACTION THREE FIFTHS
<45>    /d032/d032/d037/d059    VULGAR FRACTION FOUR FIFTHS
<16>    /d032/d032/d037/d060    VULGAR FRACTION ONE SIXTH
<13>    /d032/d032/d037/d061    VULGAR FRACTION ONE THIRD
<23>    /d032/d032/d037/d062    VULGAR FRACTION TWO THIRDS
<56>    /d032/d032/d037/d063    VULGAR FRACTION FIVE SIXTHS
<*->    /d032/d032/d037/d064    MIDDLE ASTERISK
<//->   /d032/d032/d037/d065    DAGGER
<//=>   /d032/d032/d037/d066    DOUBLE-DAGGER
<-X>    /d032/d032/d037/d067    MALTESE CROSS
<%0>    /d032/d032/d037/d068    PER-MILLE SIGN
<co>    /d032/d032/d037/d069    CARE-OF SIGN
<PO>    /d032/d032/d037/d070    SOUND RECORDING COPYRIGHT SIGN
<Rx>    /d032/d032/d037/d071    PRESCRIPTION SIGN
<AO>    /d032/d032/d037/d072    ANGSTROEM SIGN
<oC>    /d032/d032/d037/d073    CENTIGRADE DEGREE SIGN
<Ml>    /d032/d032/d037/d074    MALE SIGN
<Fm>    /d032/d032/d037/d075    FEMALE SIGN
<Tl>    /d032/d032/d037/d076    TELEPHONE SIGN
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<TR>    /d032/d032/d037/d077    TELEPHONE RECORDER SIGN
<MX>    /d032/d032/d037/d078    MUSICAL SHARP SIGN
<Mb>    /d032/d032/d037/d079    MUSICAL FLAT SIGN
<Mx>    /d032/d032/d037/d080    MUSICAL NATURAL SIGN
<XX>    /d032/d032/d037/d081    BALLOT CROSS SIGN
<OK>    /d032/d032/d037/d082    CHECK MARK
<M2>    /d032/d032/d037/d083    DOUBLE MUSICAL NOTES
<!2>    /d032/d032/d037/d084    DOUBLE EXCLAMATION MARKS
<=2>    /d032/d032/d037/d085    DOUBLE LOW LINE
<Ca>    /d032/d032/d037/d086    CARET
<..>    /d032/d032/d037/d087    TWO-DOT LEADER
<.3>    /d032/d032/d037/d088    HORIZONTAL ELLIPSIS
<:3>    /d032/d032/d037/d089    VERTICAL ELLIPSIS
<.:>    /d032/d032/d037/d090    THEREFORE SIGN
<:.>    /d032/d032/d037/d091    BECAUSE SIGN
<-+>    /d032/d032/d037/d092    MINUS-PLUS SIGN
<!=>    /d032/d032/d037/d093    NOT EQUAL-TO SIGN
<=3>    /d032/d032/d037/d094    IDENTICAL-TO SIGN
<?1>    /d032/d032/d037/d095    DIFFERENCE-BETWEEN SIGN
<?2>    /d032/d032/d037/d096    ALMOST-EQUALS SIGN
<?->    /d032/d032/d037/d097    ASYMTOTICALLY-EQUALS SIGN
<?=>    /d032/d032/d037/d098    SIMILAR-TO SIGN
<=<>    /d032/d032/d037/d099    LESS-THAN OR EQUAL-TO SIGN
</>=>   /d032/d032/d037/d100    GREATER-THAN OR EQUAL-TO SIGN
<0(>    /d032/d032/d037/d101    PROPORTIONAL-TO SIGN
<00>    /d032/d032/d037/d102    INFINITY SIGN
<PP>    /d032/d032/d037/d103    PARALLEL-TO SIGN
<-T>    /d032/d032/d037/d104    ORTHOGONAL-TO SIGN
<-L>    /d032/d032/d037/d105    RIGHT ANGLE SIGN
<-V>    /d032/d032/d037/d106    ANGLE SIGN
<AN>    /d032/d032/d037/d107    LOGICAL-AND SIGN
<OR>    /d032/d032/d037/d108    LOGICAL-OR SIGN
<.P>    /d032/d032/d037/d109    PRODUCT DOT SIGN
<nS>    /d032/d032/d037/d110    SUPERSCRIPT LATIN SMALL LETTER N
<dP>    /d032/d032/d037/d111    PARTIAL DIFFERENTIAL SIGN
<f(>    /d032/d032/d037/d112    FUNCTION SIGN
<In>    /d032/d032/d037/d113    INTEGRAL SIGN
<Io>    /d032/d032/d037/d114    CONTOUR INTEGRAL SIGN
<RT>    /d032/d032/d037/d117    RADICAL SIGN
<*P>    /d032/d032/d037/d118    REPEATED PRODUCT SIGN
<+Z>    /d032/d032/d037/d119    SUMMATION SIGN
<FA>    /d032/d032/d037/d120    FOR-ALL SIGN
<TE>    /d032/d032/d037/d121    THERE-EXISTS SIGN
<GF>    /d032/d032/d037/d122    GAMMA FUNCTION SIGN
<DE>    /d032/d032/d037/d123    INCREMENT SIGN
<NB>    /d032/d032/d037/d124    NABLA
<(U>    /d032/d032/d037/d125    INTERSECTION SIGN
<)U>    /d032/d032/d037/d126    UNION SIGN
<(C>    /d032/d032/d037/d160    PROPER SUBSET SIGN
<)C>    /d032/d032/d037/d161    PROPER SUPERSET SIGN
<(_>    /d032/d032/d037/d162    SUBSET SIGN
<)_>    /d032/d032/d037/d163    SUPERSET SIGN
<(->    /d032/d032/d037/d164    ELEMENT-OF SIGN
<-)>    /d032/d032/d037/d165    HAS AN ELEMENT SIGN
<</>>   /d032/d032/d037/d166    LEFT AND RIGHT-POINTING ARROW
<UD>    /d032/d032/d037/d167    UP AND DOWN-POINTING ARROW
<Ub>    /d032/d032/d037/d168    UP AND DOWN-POINTING ARROW WITH LINE BELOW
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<<=>    /d032/d032/d037/d169    IMPLIED-BY SIGN
<=/>>   /d032/d032/d037/d170    IMPLIES SIGN
<==>    /d032/d032/d037/d171    IF-AND-ONLY-IF SIGN
<//0>   /d032/d032/d037/d172    EMPTY SIGN
<OL>    /d032/d032/d037/d173    SOLID LOZENGE
<0u>    /d032/d032/d037/d176    SMILING FACE WHITE
<0U>    /d032/d032/d037/d177    SMILING FACE BLACK
<SU>    /d032/d032/d037/d178    RADIANT SUN
<0:>    /d032/d032/d037/d179    DOTTED CIRCLE
<OS>    /d032/d032/d037/d180    SQUARE EMPTY
<fS>    /d032/d032/d037/d181    SQUARE SOLID
<Or>    /d032/d032/d037/d182    RECTANGLE EMPTY
<SR>    /d032/d032/d037/d183    RECTANGLE SOLID
<uT>    /d032/d032/d037/d184    UPWARDS-POINTING TRIANGLE EMPTY
<UT>    /d032/d032/d037/d185    UPWARDS-POINTING TRIANGLE SOLID
<dT>    /d032/d032/d037/d186    DOWNWARDS-POINTING TRIANGLE EMPTY
<Dt>    /d032/d032/d037/d187    DOWNWARDS-POINTING TRIANGLE SOLID
<PL>    /d032/d032/d037/d188    LEFTWARDS POINTER SOLID
<PR>    /d032/d032/d037/d189    RIGHTWARDS POINTER SOLID
<*1>    /d032/d032/d037/d190    STAR EMPTY
<*2>    /d032/d032/d037/d191    STAR SOLID
<VV>    /d032/d032/d037/d192    BOX DRAWINGS HEAVY VERTICAL
<HH>    /d032/d032/d037/d193    BOX DRAWINGS HEAVY HORIZONTAL
<DR>    /d032/d032/d037/d194    BOX DRAWINGS HEAVY DOWN AND RIGHT
<LD>    /d032/d032/d037/d195    BOX DRAWINGS HEAVY DOWN AND LEFT
<UR>    /d032/d032/d037/d196    BOX DRAWINGS HEAVY UP AND RIGHT
<UL>    /d032/d032/d037/d197    BOX DRAWINGS HEAVY UP AND LEFT
<VR>    /d032/d032/d037/d198    BOX DRAWINGS HEAVY VERTICAL AND RIGHT
<VL>    /d032/d032/d037/d199    BOX DRAWINGS HEAVY VERTICAL AND LEFT
<DH>    /d032/d032/d037/d200    BOX DRAWINGS HEAVY HORIZONTAL AND DOWN
<UH>    /d032/d032/d037/d201    BOX DRAWINGS HEAVY HORIZONTAL AND UP
<VH>    /d032/d032/d037/d202    BOX DRAWINGS HEAVY VERTICAL AND HORIZONTAL
<TB>    /d032/d032/d037/d203    BOX DRAWING SOLID UPPER HALF BLOCK
<LB>    /d032/d032/d037/d204    BOX DRAWING SOLID LOWER HALF BLOCK
<FB>    /d032/d032/d037/d205    BOX DRAWING SOLID FULL BLOCK
<sB>    /d032/d032/d037/d206    BOX DRAWING SOLID SMALL SQUARE
<EH>    /d032/d032/d037/d207    EMPTY HOUSE SIGN
<vv>    /d032/d032/d037/d208    BOX DRAWINGS LIGHT VERTICAL
<hh>    /d032/d032/d037/d209    BOX DRAWINGS LIGHT HORIZONTAL
<dr>    /d032/d032/d037/d210    BOX DRAWINGS LIGHT DOWN AND RIGHT
<dl>    /d032/d032/d037/d211    BOX DRAWINGS LIGHT DOWN AND LEFT
<ur>    /d032/d032/d037/d212    BOX DRAWINGS LIGHT UP AND RIGHT
<ul>    /d032/d032/d037/d213    BOX DRAWINGS LIGHT UP AND LEFT
<vr>    /d032/d032/d037/d214    BOX DRAWINGS LIGHT VERTICAL AND RIGHT
<vl>    /d032/d032/d037/d215    BOX DRAWINGS LIGHT VERTICAL AND LEFT
<dh>    /d032/d032/d037/d216    BOX DRAWINGS LIGHT HORIZONTAL AND DOWN
<uh>    /d032/d032/d037/d217    BOX DRAWINGS LIGHT HORIZONTAL AND UP
<vh>    /d032/d032/d037/d218    BOX DRAWINGS LIGHT VERTICAL AND HORIZONTAL
<.S>    /d032/d032/d037/d219    BOX DRAWING LIGHT SHADE (25%)
<:S>    /d032/d032/d037/d220    BOX DRAWING MEDIUM SHADE (50%)
<?S>    /d032/d032/d037/d221    BOX DRAWING DARK SHADE (75%)
<lB>    /d032/d032/d037/d222    BOX DRAWING SOLID LEFT HALF BLOCK
<RB>    /d032/d032/d037/d223    BOX DRAWING SOLID RIGHT HALF BLOCK
<cC>    /d032/d032/d037/d224    CLUB SYMBOL
<cD>    /d032/d032/d037/d225    DIAMOND SYMBOL
<Dr>    /d032/d032/d037/d226    BOX DRAWINGS DOWN HEAVY AND RIGHT LIGHT
<Dl>    /d032/d032/d037/d227    BOX DRAWINGS DOWN HEAVY AND LEFT LIGHT
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<Ur>    /d032/d032/d037/d228    BOX DRAWINGS UP HEAVY AND RIGHT LIGHT
<Ul>    /d032/d032/d037/d229    BOX DRAWINGS UP HEAVY AND LEFT LIGHT
<Vr>    /d032/d032/d037/d230    BOX DRAWINGS VERTICAL HEAVY AND RIGHT LIGHT
<Vl>    /d032/d032/d037/d231    BOX DRAWINGS VERTICAL HEAVY AND LEFT LIGHT
<dH>    /d032/d032/d037/d232    BOX DRAWINGS HORIZONTAL HEAVY AND DOWN LIGHT
<uH>    /d032/d032/d037/d233    BOX DRAWINGS HORIZONTAL HEAVY AND UP LIGHT
<vH>    /d032/d032/d037/d234    BOX DRAWINGS VERTICAL LIGHT AND HORIZONTAL HEAVY
<Ob>    /d032/d032/d037/d235    CIRCLE BULLET EMPTY
<Sb>    /d032/d032/d037/d236    CIRCLE BULLET SOLID
<Sn>    /d032/d032/d037/d237    CIRCLE BULLET NEGATIVE
<Pt>    /d032/d032/d037/d238    PESETA SYMBOL
<NI>    /d032/d032/d037/d239    REVERSED NOT SIGN
<cH>    /d032/d032/d037/d240    HEART SYMBOL
<cS>    /d032/d032/d037/d241    SPADE SYMBOL
<dR>    /d032/d032/d037/d242    BOX DRAWINGS DOWN LIGHT AND RIGHT HEAVY
<dL>    /d032/d032/d037/d243    BOX DRAWINGS DOWN LIGHT AND LEFT HEAVY
<uR>    /d032/d032/d037/d244    BOX DRAWINGS UP LIGHT AND RIGHT HEAVY
<uL>    /d032/d032/d037/d245    BOX DRAWINGS UP LIGHT AND LEFT HEAVY
<vR>    /d032/d032/d037/d246    BOX DRAWINGS VERTICAL LIGHT AND RIGHT HEAVY
<vL>    /d032/d032/d037/d247    BOX DRAWINGS VERTICAL LIGHT AND LEFT HEAVY
<Dh>    /d032/d032/d037/d248    BOX DRAWINGS HORIZONTAL LIGHT AND DOWN HEAVY
<Uh>    /d032/d032/d037/d249    BOX DRAWINGS HORIZONTAL LIGHT AND UP HEAVY
<Vh>    /d032/d032/d037/d250    BOX DRAWINGS VERTICAL HEAVY AND HORIZONTAL LIGHT
<0m>    /d032/d032/d037/d251    MEDIUM CIRCLE EMPTY
<0M>    /d032/d032/d037/d252    MEDIUM CIRCLE SOLID
<Ic>    /d032/d032/d037/d253    MEDIUM CIRCLE NEGATIVE
<SM>    /d032/d032/d037/d254    SERVICE MARK SIGN
<CG>    /d032/d032/d037/d255    CONGRUENCE SIGN
<Ci>    /d032/d032/d038/d037    CIRCLE
<(A>    /d032/d032/d038/d041    ARC SIGN
</>V>   /d032/d032/d038/d046    RIGHTWARDS VECTOR ABOVE
<!<>    /d032/d032/d038/d049    NOT LESS-THAN SIGN
<<*>    /d032/d032/d038/d056    MUCH-LESS-THAN SIGN
<!/>>   /d032/d032/d038/d065    NOT GREATER-THAN SIGN
<*/>>   /d032/d032/d038/d072    MUCH-GREATER-THAN SIGN
<<7>    /d032/d032/d038/d094    CEILING SIGN LEFT
<7<>    /d032/d032/d038/d095    FLOOR SIGN LEFT
</>7>   /d032/d032/d038/d110    CEILING SIGN RIGHT
<7/>>   /d032/d032/d038/d111    FLOOR SIGN RIGHT
<I2>    /d032/d032/d038/d121    DOUBLE INTEGRAL SIGN
<0.>    /d032/d032/d038/d164    DOT IN RING
<HI>    /d032/d032/d038/d177    HAS-AN-IMAGE SIGN
<::>    /d032/d032/d038/d193    PROPORTION SIGN
<FD>    /d032/d032/d038/d209    FORWARD DIAGONAL
<LZ>    /d032/d032/d038/d223    LOZENGE
<BD>    /d032/d032/d038/d225    BACKWARD DIAGONAL
<1R>    /d032/d032/d039/d032    ROMAN NUMERAL ONE
<2R>    /d032/d032/d039/d033    ROMAN NUMERAL TWO
<3R>    /d032/d032/d039/d034    ROMAN NUMERAL THREE
<4R>    /d032/d032/d039/d035    ROMAN NUMERAL FOUR
<5R>    /d032/d032/d039/d036    ROMAN NUMERAL FIVE
<6R>    /d032/d032/d039/d037    ROMAN NUMERAL SIX
<7R>    /d032/d032/d039/d038    ROMAN NUMERAL SEVEN
<8R>    /d032/d032/d039/d039    ROMAN NUMERAL EIGHT
<9R>    /d032/d032/d039/d040    ROMAN NUMERAL NINE
<aR>    /d032/d032/d039/d041    ROMAN NUMERAL TEN
<bR>    /d032/d032/d039/d042    ROMAN NUMERAL ELEVEN
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<cR>    /d032/d032/d039/d043    ROMAN NUMERAL TWELVE
<IO>    /d032/d032/d040/d161    CYRILLIC CAPITAL LETTER IO
<D%>    /d032/d032/d040/d162    CYRILLIC CAPITAL LETTER DJE (Serbocroatian)
<G%>    /d032/d032/d040/d163    CYRILLIC CAPITAL LETTER GJE (Macedonian)
<IE>    /d032/d032/d040/d164    CYRILLIC CAPITAL LETTER UKRAINIAN IE
<DS>    /d032/d032/d040/d165    CYRILLIC CAPITAL LETTER DZE (Macedonian)
<II>    /d032/d032/d040/d166    CYRILLIC CAPITAL LETTER BYELORUSSIAN-UKRAINIAN I
<YI>    /d032/d032/d040/d167    CYRILLIC CAPITAL LETTER YI (Ukrainian)
<J%>    /d032/d032/d040/d168    CYRILLIC CAPITAL LETTER JE
<LJ>    /d032/d032/d040/d169    CYRILLIC CAPITAL LETTER LJE
<NJ>    /d032/d032/d040/d170    CYRILLIC CAPITAL LETTER NJE
<Ts>    /d032/d032/d040/d171    CYRILLIC CAPITAL LETTER TSHE (Serbocroatian)
<KJ>    /d032/d032/d040/d172    CYRILLIC CAPITAL LETTER KJE (Macedonian)
<V%>    /d032/d032/d040/d174    CYRILLIC CAPITAL LETTER SHORT U (Byelorussian)
<DZ>    /d032/d032/d040/d175    CYRILLIC CAPITAL LETTER DZHE
<A=>    /d032/d032/d040/d176    CYRILLIC CAPITAL LETTER A
<B=>    /d032/d032/d040/d177    CYRILLIC CAPITAL LETTER BE
<V=>    /d032/d032/d040/d178    CYRILLIC CAPITAL LETTER VE
<G=>    /d032/d032/d040/d179    CYRILLIC CAPITAL LETTER GHE
<D=>    /d032/d032/d040/d180    CYRILLIC CAPITAL LETTER DE
<E=>    /d032/d032/d040/d181    CYRILLIC CAPITAL LETTER IE
<Z%>    /d032/d032/d040/d182    CYRILLIC CAPITAL LETTER ZHE
<Z=>    /d032/d032/d040/d183    CYRILLIC CAPITAL LETTER ZE
<I=>    /d032/d032/d040/d184    CYRILLIC CAPITAL LETTER I
<J=>    /d032/d032/d040/d185    CYRILLIC CAPITAL LETTER SHORT I
<K=>    /d032/d032/d040/d186    CYRILLIC CAPITAL LETTER KA
<L=>    /d032/d032/d040/d187    CYRILLIC CAPITAL LETTER EL
<M=>    /d032/d032/d040/d188    CYRILLIC CAPITAL LETTER EM
<N=>    /d032/d032/d040/d189    CYRILLIC CAPITAL LETTER EN
<O=>    /d032/d032/d040/d190    CYRILLIC CAPITAL LETTER O
<P=>    /d032/d032/d040/d191    CYRILLIC CAPITAL LETTER PE
<R=>    /d032/d032/d040/d192    CYRILLIC CAPITAL LETTER ER
<S=>    /d032/d032/d040/d193    CYRILLIC CAPITAL LETTER ES
<T=>    /d032/d032/d040/d194    CYRILLIC CAPITAL LETTER TE
<U=>    /d032/d032/d040/d195    CYRILLIC CAPITAL LETTER U
<F=>    /d032/d032/d040/d196    CYRILLIC CAPITAL LETTER EF
<H=>    /d032/d032/d040/d197    CYRILLIC CAPITAL LETTER HA
<C=>    /d032/d032/d040/d198    CYRILLIC CAPITAL LETTER TSE
<C%>    /d032/d032/d040/d199    CYRILLIC CAPITAL LETTER CHE
<S%>    /d032/d032/d040/d200    CYRILLIC CAPITAL LETTER SHA
<Sc>    /d032/d032/d040/d201    CYRILLIC CAPITAL LETTER SHCHA
<=">    /d032/d032/d040/d202    CYRILLIC CAPITAL HARD SIGN
<Y=>    /d032/d032/d040/d203    CYRILLIC CAPITAL LETTER YERU
<%">    /d032/d032/d040/d204    CYRILLIC CAPITAL SOFT SIGN
<JE>    /d032/d032/d040/d205    CYRILLIC CAPITAL LETTER E
<JU>    /d032/d032/d040/d206    CYRILLIC CAPITAL LETTER YU
<JA>    /d032/d032/d040/d207    CYRILLIC CAPITAL LETTER YA
<a=>    /d032/d032/d040/d208    CYRILLIC SMALL LETTER A
<b=>    /d032/d032/d040/d209    CYRILLIC SMALL LETTER BE
<v=>    /d032/d032/d040/d210    CYRILLIC SMALL LETTER VE
<g=>    /d032/d032/d040/d211    CYRILLIC SMALL LETTER GHE
<d=>    /d032/d032/d040/d212    CYRILLIC SMALL LETTER DE
<e=>    /d032/d032/d040/d213    CYRILLIC SMALL LETTER IE
<z%>    /d032/d032/d040/d214    CYRILLIC SMALL LETTER ZHE
<z=>    /d032/d032/d040/d215    CYRILLIC SMALL LETTER ZE
<i=>    /d032/d032/d040/d216    CYRILLIC SMALL LETTER I
<j=>    /d032/d032/d040/d217    CYRILLIC SMALL LETTER SHORT I
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<k=>    /d032/d032/d040/d218    CYRILLIC SMALL LETTER KA
<l=>    /d032/d032/d040/d219    CYRILLIC SMALL LETTER EL
<m=>    /d032/d032/d040/d220    CYRILLIC SMALL LETTER EM
<n=>    /d032/d032/d040/d221    CYRILLIC SMALL LETTER EN
<o=>    /d032/d032/d040/d222    CYRILLIC SMALL LETTER O
<p=>    /d032/d032/d040/d223    CYRILLIC SMALL LETTER PE
<r=>    /d032/d032/d040/d224    CYRILLIC SMALL LETTER ER
<s=>    /d032/d032/d040/d225    CYRILLIC SMALL LETTER ES
<t=>    /d032/d032/d040/d226    CYRILLIC SMALL LETTER TE
<u=>    /d032/d032/d040/d227    CYRILLIC SMALL LETTER U
<f=>    /d032/d032/d040/d228    CYRILLIC SMALL LETTER EF
<h=>    /d032/d032/d040/d229    CYRILLIC SMALL LETTER HA
<c=>    /d032/d032/d040/d230    CYRILLIC SMALL LETTER TSE
<c%>    /d032/d032/d040/d231    CYRILLIC SMALL LETTER CHE
<s%>    /d032/d032/d040/d232    CYRILLIC SMALL LETTER SHA
<sc>    /d032/d032/d040/d233    CYRILLIC SMALL LETTER SHCHA
<='>    /d032/d032/d040/d234    CYRILLIC SMALL HARD SIGN
<y=>    /d032/d032/d040/d235    CYRILLIC SMALL LETTER YERU
<%'>    /d032/d032/d040/d236    CYRILLIC SMALL SOFT SIGN
<je>    /d032/d032/d040/d237    CYRILLIC SMALL LETTER E
<ju>    /d032/d032/d040/d238    CYRILLIC SMALL LETTER YU
<ja>    /d032/d032/d040/d239    CYRILLIC SMALL LETTER YA
<N0>    /d032/d032/d040/d240    NUMERO SIGN
<io>    /d032/d032/d040/d241    CYRILLIC SMALL LETTER IO
<d%>    /d032/d032/d040/d242    CYRILLIC SMALL LETTER DJE (Serbocroatian)
<g%>    /d032/d032/d040/d243    CYRILLIC SMALL LETTER GJE (Macedonian)
<ie>    /d032/d032/d040/d244    CYRILLIC SMALL LETTER UKRAINIAN IE
<ds>    /d032/d032/d040/d245    CYRILLIC SMALL LETTER DZE (Macedonian)
<ii>    /d032/d032/d040/d246    CYRILLIC SMALL LETTER BYELORUSSIAN-UKRAINIAN I
<yi>    /d032/d032/d040/d247    CYRILLIC SMALL LETTER YI (Ukrainian)
<j%>    /d032/d032/d040/d248    CYRILLIC SMALL LETTER JE
<lj>    /d032/d032/d040/d249    CYRILLIC SMALL LETTER LJE
<nj>    /d032/d032/d040/d250    CYRILLIC SMALL LETTER NJE
<ts>    /d032/d032/d040/d251    CYRILLIC SMALL LETTER TSHE (Serbocroatian)
<kj>    /d032/d032/d040/d252    CYRILLIC SMALL LETTER KJE (Macedonian)
<v%>    /d032/d032/d040/d254    CYRILLIC SMALL LETTER SHORT U (Byelorussian)
<dz>    /d032/d032/d040/d255    CYRILLIC SMALL LETTER DZHE
<i3>    /d032/d032/d042/d160    GREEK IOTA BELOW
<;;>    /d032/d032/d042/d161    GREEK DAISA PNEUMATA (rough)
<,,>    /d032/d032/d042/d162    GREEK PSILI PNEUMATA (smooth)
<!*>    /d032/d032/d042/d164    GREEK VARIA
<?*>    /d032/d032/d042/d165    GREEK PERISPOMENI
<;'>    /d032/d032/d042/d166    GREEK DAISA AND ACUTE ACCENT
<,'>    /d032/d032/d042/d167    GREEK PSILI AND ACUTE ACCENT
<;!>    /d032/d032/d042/d168    GREEK DAISA AND VARIA
<,!>    /d032/d032/d042/d169    GREEK PSILI AND VARIA
<?;>    /d032/d032/d042/d170    GREEK PERISPOMENI AND DAISA
<?,>    /d032/d032/d042/d171    GREEK PERISPOMENI AND PSILI
<!:>    /d032/d032/d042/d174    GREEK VARIA AND DIAERESIS
<?:>    /d032/d032/d042/d175    GREEK PERISPOMENI AND DIAERESIS
<I3>    /d032/d032/d042/d176    GREEK CAPITAL LETTER IOTA WITH PERISPOMENI
#                               AND PSILI
<'%>    /d032/d032/d042/d181    ACUTE ACCENT AND DIAERESIS (Tonos and Dialytica)
<A%>    /d032/d032/d042/d182    GREEK CAPITAL LETTER ALPHA WITH ACUTE
<E%>    /d032/d032/d042/d184    GREEK CAPITAL LETTER EPSILON WITH ACUTE
<Y%>    /d032/d032/d042/d185    GREEK CAPITAL LETTER ETA WITH ACUTE
<I%>    /d032/d032/d042/d186    GREEK CAPITAL LETTER IOTA WITH ACUTE
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<O%>     /d032/d032/d042/d188    GREEK CAPITAL LETTER OMICRON WITH ACUTE
<U%>     /d032/d032/d042/d190    GREEK CAPITAL LETTER UPSILON WITH ACUTE
<W%>     /d032/d032/d042/d191    GREEK CAPITAL LETTER OMEGA WITH ACUTE
<A*>     /d032/d032/d042/d193    GREEK CAPITAL LETTER ALPHA
<B*>     /d032/d032/d042/d194    GREEK CAPITAL LETTER BETA
<G*>     /d032/d032/d042/d195    GREEK CAPITAL LETTER GAMMA
<D*>     /d032/d032/d042/d196    GREEK CAPITAL LETTER DELTA
<E*>     /d032/d032/d042/d197    GREEK CAPITAL LETTER EPSILON
<Z*>     /d032/d032/d042/d198    GREEK CAPITAL LETTER ZETA
<Y*>     /d032/d032/d042/d199    GREEK CAPITAL LETTER ETA
<H*>     /d032/d032/d042/d200    GREEK CAPITAL LETTER THETA
<I*>     /d032/d032/d042/d201    GREEK CAPITAL LETTER IOTA
<K*>     /d032/d032/d042/d202    GREEK CAPITAL LETTER KAPPA
<L*>     /d032/d032/d042/d203    GREEK CAPITAL LETTER LAMDA
<M*>     /d032/d032/d042/d204    GREEK CAPITAL LETTER MU
<N*>     /d032/d032/d042/d205    GREEK CAPITAL LETTER NU
<C*>     /d032/d032/d042/d206    GREEK CAPITAL LETTER XI
<O*>     /d032/d032/d042/d207    GREEK CAPITAL LETTER OMICRON
<P*>     /d032/d032/d042/d208    GREEK CAPITAL LETTER PI
<R*>     /d032/d032/d042/d209    GREEK CAPITAL LETTER RHO
<S*>     /d032/d032/d042/d211    GREEK CAPITAL LETTER SIGMA
<T*>     /d032/d032/d042/d212    GREEK CAPITAL LETTER TAU
<U*>     /d032/d032/d042/d213    GREEK CAPITAL LETTER UPSILON
<F*>     /d032/d032/d042/d214    GREEK CAPITAL LETTER PHI
<X*>     /d032/d032/d042/d215    GREEK CAPITAL LETTER CHI
<Q*>     /d032/d032/d042/d216    GREEK CAPITAL LETTER PSI
<W*>     /d032/d032/d042/d217    GREEK CAPITAL LETTER OMEGA
<J*>     /d032/d032/d042/d218    GREEK CAPITAL LETTER IOTA WITH DIAERESIS
<V*>     /d032/d032/d042/d219    GREEK CAPITAL LETTER UPSILON WITH DIAERESIS
<a%>     /d032/d032/d042/d220    GREEK SMALL LETTER ALPHA WITH ACUTE
<e%>     /d032/d032/d042/d221    GREEK SMALL LETTER EPSILON WITH ACUTE
<y%>     /d032/d032/d042/d222    GREEK SMALL LETTER ETA WITH ACUTE
<i%>     /d032/d032/d042/d223    GREEK SMALL LETTER IOTA WITH ACUTE
<a*>     /d032/d032/d042/d225    GREEK SMALL LETTER ALPHA
<b*>     /d032/d032/d042/d226    GREEK SMALL LETTER BETA
<g*>     /d032/d032/d042/d227    GREEK SMALL LETTER GAMMA
<d*>     /d032/d032/d042/d228    GREEK SMALL LETTER DELTA
<e*>     /d032/d032/d042/d229    GREEK SMALL LETTER EPSILON
<z*>     /d032/d032/d042/d230    GREEK SMALL LETTER ZETA
<y*>     /d032/d032/d042/d231    GREEK SMALL LETTER ETA
<h*>     /d032/d032/d042/d232    GREEK SMALL LETTER THETA
<i*>     /d032/d032/d042/d233    GREEK SMALL LETTER IOTA
<k*>     /d032/d032/d042/d234    GREEK SMALL LETTER KAPPA
<l*>     /d032/d032/d042/d235    GREEK SMALL LETTER LAMDA
<m*>     /d032/d032/d042/d236    GREEK SMALL LETTER MU
<n*>     /d032/d032/d042/d237    GREEK SMALL LETTER NU
<c*>     /d032/d032/d042/d238    GREEK SMALL LETTER XI
<o*>     /d032/d032/d042/d239    GREEK SMALL LETTER OMICRON
<p*>     /d032/d032/d042/d240    GREEK SMALL LETTER PI
<r*>     /d032/d032/d042/d241    GREEK SMALL LETTER RHO
<*s>     /d032/d032/d042/d242    GREEK SMALL LETTER FINAL SIGMA
<s*>     /d032/d032/d042/d243    GREEK SMALL LETTER SIGMA
<t*>     /d032/d032/d042/d244    GREEK SMALL LETTER TAU
<u*>     /d032/d032/d042/d245    GREEK SMALL LETTER UPSILON
<f*>     /d032/d032/d042/d246    GREEK SMALL LETTER PHI
<x*>     /d032/d032/d042/d247    GREEK SMALL LETTER CHI
<q*>     /d032/d032/d042/d248    GREEK SMALL LETTER PSI
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<w*>    /d032/d032/d042/d249    GREEK SMALL LETTER OMEGA
<j*>    /d032/d032/d042/d250    GREEK SMALL LETTER IOTA WITH DIAERESIS
<v*>    /d032/d032/d042/d251    GREEK SMALL LETTER UPSILON WITH DIAERESIS
<o%>    /d032/d032/d042/d252    GREEK SMALL LETTER OMICRON WITH ACUTE
<u%>    /d032/d032/d042/d253    GREEK SMALL LETTER UPSILON WITH ACUTE
<w%>    /d032/d032/d042/d254    GREEK SMALL LETTER OMEGA WITH ACUTE
<p+>    /d032/d032/d044/d035    ARABIC LETTER PEH
<v+>    /d032/d032/d044/d040    ARABIC LETTER VEH
<gf>    /d032/d032/d044/d052    ARABIC LETTER GAF
<,+>    /d032/d032/d044/d172    ARABIC COMMA
<;+>    /d032/d032/d044/d187    ARABIC SEMICOLON
<?+>    /d032/d032/d044/d191    ARABIC QUESTION MARK
<H'>    /d032/d032/d044/d193    ARABIC LETTER HAMZA
<aM>    /d032/d032/d044/d194    ARABIC LETTER ALEF WITH MADDA ABOVE
<aH>    /d032/d032/d044/d195    ARABIC LETTER ALEF WITH HAMZA ABOVE
<wH>    /d032/d032/d044/d196    ARABIC LETTER WAW WITH HAMZA ABOVE
<ah>    /d032/d032/d044/d197    ARABIC LETTER ALEF WITH HAMZA BELOW
<yH>    /d032/d032/d044/d198    ARABIC LETTER YEH WITH HAMZA ABOVE
<a+>    /d032/d032/d044/d199    ARABIC LETTER ALEF
<b+>    /d032/d032/d044/d200    ARABIC LETTER BEH
<tm>    /d032/d032/d044/d201    ARABIC LETTER TEH MARBUTA
<t+>    /d032/d032/d044/d202    ARABIC LETTER TEH
<tk>    /d032/d032/d044/d203    ARABIC LETTER THEH
<g+>    /d032/d032/d044/d204    ARABIC LETTER JEEM
<hk>    /d032/d032/d044/d205    ARABIC LETTER HAH
<x+>    /d032/d032/d044/d206    ARABIC LETTER KHAH
<d+>    /d032/d032/d044/d207    ARABIC LETTER DAL
<dk>    /d032/d032/d044/d208    ARABIC LETTER THAL
<r+>    /d032/d032/d044/d209    ARABIC LETTER RA
<z+>    /d032/d032/d044/d210    ARABIC LETTER ZAIN
<s+>    /d032/d032/d044/d211    ARABIC LETTER SEEN
<sn>    /d032/d032/d044/d212    ARABIC LETTER SHEEN
<c+>    /d032/d032/d044/d213    ARABIC LETTER SAD
<dd>    /d032/d032/d044/d214    ARABIC LETTER DAD
<tj>    /d032/d032/d044/d215    ARABIC LETTER TAH
<zH>    /d032/d032/d044/d216    ARABIC LETTER ZAH
<e+>    /d032/d032/d044/d217    ARABIC LETTER AIN
<i+>    /d032/d032/d044/d218    ARABIC LETTER GHAIN
<++>    /d032/d032/d044/d224    ARABIC TATWEEL
<f+>    /d032/d032/d044/d225    ARABIC LETTER FEH
<q+>    /d032/d032/d044/d226    ARABIC LETTER QAF
<k+>    /d032/d032/d044/d227    ARABIC LETTER KAF
<l+>    /d032/d032/d044/d228    ARABIC LETTER LAM
<m+>    /d032/d032/d044/d229    ARABIC LETTER MEEM
<n+>    /d032/d032/d044/d230    ARABIC LETTER NOON
<h+>    /d032/d032/d044/d231    ARABIC LETTER HEH
<w+>    /d032/d032/d044/d232    ARABIC LETTER WAW
<j+>    /d032/d032/d044/d233    ARABIC LETTER ALEF MAKSURA
<y+>    /d032/d032/d044/d234    ARABIC LETTER YEH
<:+>    /d032/d032/d044/d235    ARABIC FATHATAN
<"+>    /d032/d032/d044/d236    ARABIC DAMMATAN
<=+>    /d032/d032/d044/d237    ARABIC KASRATAN
<//+>   /d032/d032/d044/d238    ARABIC FATHA
<'+>    /d032/d032/d044/d239    ARABIC DAMMA
<1+>    /d032/d032/d044/d240    ARABIC KASRA
<3+>    /d032/d032/d044/d241    ARABIC SHADDA
<0+>    /d032/d032/d044/d242    ARABIC SUKUN
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<A+>    /d032/d032/d045/d224    HEBREW LETTER ALEF
<B+>    /d032/d032/d045/d225    HEBREW LETTER BET
<G+>    /d032/d032/d045/d226    HEBREW LETTER GIMEL
<D+>    /d032/d032/d045/d227    HEBREW LETTER DALET
<H+>    /d032/d032/d045/d228    HEBREW LETTER HE
<W+>    /d032/d032/d045/d229    HEBREW LETTER VAV
<Z+>    /d032/d032/d045/d230    HEBREW LETTER ZAYIN
<X+>    /d032/d032/d045/d231    HEBREW LETTER HET
<Tj>    /d032/d032/d045/d232    HEBREW LETTER TET
<J+>    /d032/d032/d045/d233    HEBREW LETTER YOD
<K%>    /d032/d032/d045/d234    HEBREW LETTER FINAL KAF
<K+>    /d032/d032/d045/d235    HEBREW LETTER KAF
<L+>    /d032/d032/d045/d236    HEBREW LETTER LAMED
<M%>    /d032/d032/d045/d237    HEBREW LETTER FINAL MEM
<M+>    /d032/d032/d045/d238    HEBREW LETTER MEM
<N%>    /d032/d032/d045/d239    HEBREW LETTER FINAL NUN
<N+>    /d032/d032/d045/d240    HEBREW LETTER NUN
<S+>    /d032/d032/d045/d241    HEBREW LETTER SAMEKH
<E+>    /d032/d032/d045/d242    HEBREW LETTER AYIN
<P%>    /d032/d032/d045/d243    HEBREW LETTER FINAL PE
<P+>    /d032/d032/d045/d244    HEBREW LETTER PE
<Zj>    /d032/d032/d045/d245    HEBREW LETTER FINAL TSADI
<ZJ>    /d032/d032/d045/d246    HEBREW LETTER TSADI
<Q+>    /d032/d032/d045/d247    HEBREW LETTER QOF
<R+>    /d032/d032/d045/d248    HEBREW LETTER RESH
<Sh>    /d032/d032/d045/d249    HEBREW LETTER SIN
<T+>    /d032/d032/d045/d250    HEBREW LETTER TAV
<IS>    /d032/d032/d046/d032    IDEOGRAPHIC SPACE
<,_>    /d032/d032/d046/d033    IDEOGRAPHIC COMMA
<._>    /d032/d032/d046/d034    IDEOGRAPHIC FULL STOP
<+">    /d032/d032/d046/d035    DITTO MARK
<+_>    /d032/d032/d046/d036    IDEOGRAPHIC DITTO MARK
<*_>    /d032/d032/d046/d037    IDEOGRAPHIC REPETITION MARK
<;_>    /d032/d032/d046/d038    IDEOGRAPHIC CLOSING MARK
<0_>    /d032/d032/d046/d039    IDEOGRAPHIC NUMBER ZERO
<<+>    /d032/d032/d046/d042    LEFT-POINTING DOUBLE ANGLE BRACKET
</>+>   /d032/d032/d046/d043    RIGHT-POINTING DOUBLE ANGLE BRACKET
<<'>    /d032/d032/d046/d044    IDEOGRAPHIC LEFT BRACKET
</>'>   /d032/d032/d046/d045    IDEOGRAPHIC RIGHT BRACKET
<<">    /d032/d032/d046/d046    IDEOGRAPHIC LEFT DOUBLE BRACKET
</>">   /d032/d032/d046/d047    IDEOGRAPHIC RIGHT DOUBLE BRACKET
<(">    /d032/d032/d046/d048    LEFT BOLDFACE SQUARE BRACKET
<)">    /d032/d032/d046/d049    RIGHT BOLDFACE SQUARE BRACKET
<=//>   /d032/d032/d046/d050    POSTAL MARK
<=_>    /d032/d032/d046/d051    GETA MARK
<('>    /d032/d032/d046/d052    LEFT TORTOISE-SHELL BRACKET
<)'>    /d032/d032/d046/d053    RIGHT TORTOISE-SHELL BRACKET
<KM>    /d032/d032/d046/d054    KOME MARK
<b4>    /d032/d032/d046/d069    BOPOMOFO LETTER B
<p4>    /d032/d032/d046/d070    BOPOMOFO LETTER P
<m4>    /d032/d032/d046/d071    BOPOMOFO LETTER M
<f4>    /d032/d032/d046/d072    BOPOMOFO LETTER F
<d4>    /d032/d032/d046/d073    BOPOMOFO LETTER D
<t4>    /d032/d032/d046/d074    BOPOMOFO LETTER T
<n4>    /d032/d032/d046/d075    BOPOMOFO LETTER N
<l4>    /d032/d032/d046/d076    BOPOMOFO LETTER L
<g4>    /d032/d032/d046/d077    BOPOMOFO LETTER G
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<k4>    /d032/d032/d046/d078    BOPOMOFO LETTER K
<h4>    /d032/d032/d046/d079    BOPOMOFO LETTER H
<j4>    /d032/d032/d046/d080    BOPOMOFO LETTER J
<q4>    /d032/d032/d046/d081    BOPOMOFO LETTER Q
<x4>    /d032/d032/d046/d082    BOPOMOFO LETTER X
<zh>    /d032/d032/d046/d083    BOPOMOFO LETTER ZH
<ch>    /d032/d032/d046/d084    BOPOMOFO LETTER CH
<sh>    /d032/d032/d046/d085    BOPOMOFO LETTER SH
<r4>    /d032/d032/d046/d086    BOPOMOFO LETTER R
<z4>    /d032/d032/d046/d087    BOPOMOFO LETTER Z
<c4>    /d032/d032/d046/d088    BOPOMOFO LETTER C
<s4>    /d032/d032/d046/d089    BOPOMOFO LETTER S
<a4>    /d032/d032/d046/d090    BOPOMOFO LETTER A
<o4>    /d032/d032/d046/d091    BOPOMOFO LETTER O
<e4>    /d032/d032/d046/d092    BOPOMOFO LETTER E
<eh>    /d032/d032/d046/d093    BOPOMOFO LETTER EH
<ai>    /d032/d032/d046/d094    BOPOMOFO LETTER AI
<ei>    /d032/d032/d046/d095    BOPOMOFO LETTER EI
<au>    /d032/d032/d046/d096    BOPOMOFO LETTER AU
<ou>    /d032/d032/d046/d097    BOPOMOFO LETTER OU
<an>    /d032/d032/d046/d098    BOPOMOFO LETTER AN
<en>    /d032/d032/d046/d099    BOPOMOFO LETTER EN
<aN>    /d032/d032/d046/d100    BOPOMOFO LETTER ANG
<eN>    /d032/d032/d046/d101    BOPOMOFO LETTER ENG
<er>    /d032/d032/d046/d102    BOPOMOFO LETTER ER
<i4>    /d032/d032/d046/d103    BOPOMOFO LETTER I
<u4>    /d032/d032/d046/d104    BOPOMOFO LETTER U
<iu>    /d032/d032/d046/d105    BOPOMOFO LETTER IU
<A5>    /d032/d032/d047/d033    HIRAGANA LETTER SMALL A
<a5>    /d032/d032/d047/d034    HIRAGANA LETTER A
<I5>    /d032/d032/d047/d035    HIRAGANA LETTER SMALL I
<i5>    /d032/d032/d047/d036    HIRAGANA LETTER I
<U5>    /d032/d032/d047/d037    HIRAGANA LETTER SMALL U
<u5>    /d032/d032/d047/d038    HIRAGANA LETTER U
<E5>    /d032/d032/d047/d039    HIRAGANA LETTER SMALL E
<e5>    /d032/d032/d047/d040    HIRAGANA LETTER E
<O5>    /d032/d032/d047/d041    HIRAGANA LETTER SMALL O
<o5>    /d032/d032/d047/d042    HIRAGANA LETTER O
<ka>    /d032/d032/d047/d043    HIRAGANA LETTER KA
<ga>    /d032/d032/d047/d044    HIRAGANA LETTER GA
<ki>    /d032/d032/d047/d045    HIRAGANA LETTER KI
<gi>    /d032/d032/d047/d046    HIRAGANA LETTER GI
<ku>    /d032/d032/d047/d047    HIRAGANA LETTER KU
<gu>    /d032/d032/d047/d048    HIRAGANA LETTER GU
<ke>    /d032/d032/d047/d049    HIRAGANA LETTER KE
<ge>    /d032/d032/d047/d050    HIRAGANA LETTER GE
<ko>    /d032/d032/d047/d051    HIRAGANA LETTER KO
<go>    /d032/d032/d047/d052    HIRAGANA LETTER GO
<sa>    /d032/d032/d047/d053    HIRAGANA LETTER SA
<za>    /d032/d032/d047/d054    HIRAGANA LETTER ZA
<si>    /d032/d032/d047/d055    HIRAGANA LETTER SI
<zi>    /d032/d032/d047/d056    HIRAGANA LETTER ZI
<su>    /d032/d032/d047/d057    HIRAGANA LETTER SU
<zu>    /d032/d032/d047/d058    HIRAGANA LETTER ZU
<se>    /d032/d032/d047/d059    HIRAGANA LETTER SE
<ze>    /d032/d032/d047/d060    HIRAGANA LETTER ZE
<so>    /d032/d032/d047/d061    HIRAGANA LETTER SO
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<zo>    /d032/d032/d047/d062    HIRAGANA LETTER ZO
<ta>    /d032/d032/d047/d063    HIRAGANA LETTER TA
<da>    /d032/d032/d047/d064    HIRAGANA LETTER DA
<ti>    /d032/d032/d047/d065    HIRAGANA LETTER TI
<di>    /d032/d032/d047/d066    HIRAGANA LETTER DI
<tU>    /d032/d032/d047/d067    HIRAGANA LETTER SMALL TU
<tu>    /d032/d032/d047/d068    HIRAGANA LETTER TU
<du>    /d032/d032/d047/d069    HIRAGANA LETTER DU
<te>    /d032/d032/d047/d070    HIRAGANA LETTER TE
<de>    /d032/d032/d047/d071    HIRAGANA LETTER DE
<to>    /d032/d032/d047/d072    HIRAGANA LETTER TO
<do>    /d032/d032/d047/d073    HIRAGANA LETTER DO
<na>    /d032/d032/d047/d074    HIRAGANA LETTER NA
<ni>    /d032/d032/d047/d075    HIRAGANA LETTER NI
<nu>    /d032/d032/d047/d076    HIRAGANA LETTER NU
<ne>    /d032/d032/d047/d077    HIRAGANA LETTER NE
<no>    /d032/d032/d047/d078    HIRAGANA LETTER NO
<ha>    /d032/d032/d047/d079    HIRAGANA LETTER HA
<ba>    /d032/d032/d047/d080    HIRAGANA LETTER BA
<pa>    /d032/d032/d047/d081    HIRAGANA LETTER PA
<hi>    /d032/d032/d047/d082    HIRAGANA LETTER HI
<bi>    /d032/d032/d047/d083    HIRAGANA LETTER BI
<pi>    /d032/d032/d047/d084    HIRAGANA LETTER PI
<hu>    /d032/d032/d047/d085    HIRAGANA LETTER HU
<bu>    /d032/d032/d047/d086    HIRAGANA LETTER BU
<pu>    /d032/d032/d047/d087    HIRAGANA LETTER PU
<he>    /d032/d032/d047/d088    HIRAGANA LETTER HE
<be>    /d032/d032/d047/d089    HIRAGANA LETTER BE
<pe>    /d032/d032/d047/d090    HIRAGANA LETTER PE
<ho>    /d032/d032/d047/d091    HIRAGANA LETTER HO
<bo>    /d032/d032/d047/d092    HIRAGANA LETTER BO
<po>    /d032/d032/d047/d093    HIRAGANA LETTER PO
<ma>    /d032/d032/d047/d094    HIRAGANA LETTER MA
<mi>    /d032/d032/d047/d095    HIRAGANA LETTER MI
<mu>    /d032/d032/d047/d096    HIRAGANA LETTER MU
<me>    /d032/d032/d047/d097    HIRAGANA LETTER ME
<mo>    /d032/d032/d047/d098    HIRAGANA LETTER MO
<yA>    /d032/d032/d047/d099    HIRAGANA LETTER SMALL YA
<ya>    /d032/d032/d047/d100    HIRAGANA LETTER YA
<yU>    /d032/d032/d047/d101    HIRAGANA LETTER SMALL YU
<yu>    /d032/d032/d047/d102    HIRAGANA LETTER YU
<yO>    /d032/d032/d047/d103    HIRAGANA LETTER SMALL YO
<yo>    /d032/d032/d047/d104    HIRAGANA LETTER YO                    1
<ra>    /d032/d032/d047/d105    HIRAGANA LETTER RA
<ri>    /d032/d032/d047/d106    HIRAGANA LETTER RI
<ru>    /d032/d032/d047/d107    HIRAGANA LETTER RU
<re>    /d032/d032/d047/d108    HIRAGANA LETTER RE
<ro>    /d032/d032/d047/d109    HIRAGANA LETTER RO
<wA>    /d032/d032/d047/d110    HIRAGANA LETTER SMALL WA
<wa>    /d032/d032/d047/d111    HIRAGANA LETTER WA
<wi>    /d032/d032/d047/d112    HIRAGANA LETTER WI
<we>    /d032/d032/d047/d113    HIRAGANA LETTER WE
<wo>    /d032/d032/d047/d114    HIRAGANA LETTER WO
<n5>    /d032/d032/d047/d115    HIRAGANA LETTER N
<"5>    /d032/d032/d047/d122    HIRAGANA-KATAKANA VOICED SOUND MARK
<05>    /d032/d032/d047/d123    HIRAGANA-KATAKANA SEMI-VOICED SOUND MARK
<*5>    /d032/d032/d047/d124    HIRAGANA ITERATION MARK
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<+5>    /d032/d032/d047/d125    HIRAGANA VOICED ITERATION MARK
<a6>    /d032/d032/d047/d161    KATAKANA LETTER SMALL A
<A6>    /d032/d032/d047/d162    KATAKANA LETTER A
<i6>    /d032/d032/d047/d163    KATAKANA LETTER SMALL I
<I6>    /d032/d032/d047/d164    KATAKANA LETTER I
<u6>    /d032/d032/d047/d165    KATAKANA LETTER SMALL U
<U6>    /d032/d032/d047/d166    KATAKANA LETTER U
<e6>    /d032/d032/d047/d167    KATAKANA LETTER SMALL E
<E6>    /d032/d032/d047/d168    KATAKANA LETTER E
<o6>    /d032/d032/d047/d169    KATAKANA LETTER SMALL O
<O6>    /d032/d032/d047/d170    KATAKANA LETTER O
<Ka>    /d032/d032/d047/d171    KATAKANA LETTER KA
<Ga>    /d032/d032/d047/d172    KATAKANA LETTER GA
<Ki>    /d032/d032/d047/d173    KATAKANA LETTER KI
<Gi>    /d032/d032/d047/d174    KATAKANA LETTER GI
<Ku>    /d032/d032/d047/d175    KATAKANA LETTER KU
<Gu>    /d032/d032/d047/d176    KATAKANA LETTER GU
<Ke>    /d032/d032/d047/d177    KATAKANA LETTER KE
<Ge>    /d032/d032/d047/d178    KATAKANA LETTER GE
<Ko>    /d032/d032/d047/d179    KATAKANA LETTER KO
<Go>    /d032/d032/d047/d180    KATAKANA LETTER GO
<Sa>    /d032/d032/d047/d181    KATAKANA LETTER SA
<Za>    /d032/d032/d047/d182    KATAKANA LETTER ZA
<Si>    /d032/d032/d047/d183    KATAKANA LETTER SI
<Zi>    /d032/d032/d047/d184    KATAKANA LETTER ZI
<Su>    /d032/d032/d047/d185    KATAKANA LETTER SU
<Zu>    /d032/d032/d047/d186    KATAKANA LETTER ZU
<Se>    /d032/d032/d047/d187    KATAKANA LETTER SE
<Ze>    /d032/d032/d047/d188    KATAKANA LETTER ZE
<So>    /d032/d032/d047/d189    KATAKANA LETTER SO
<Zo>    /d032/d032/d047/d190    KATAKANA LETTER ZO
<Ta>    /d032/d032/d047/d191    KATAKANA LETTER TA
<Da>    /d032/d032/d047/d192    KATAKANA LETTER DA
<Ti>    /d032/d032/d047/d193    KATAKANA LETTER TI
<Di>    /d032/d032/d047/d194    KATAKANA LETTER DI
<TU>    /d032/d032/d047/d195    KATAKANA LETTER SMALL TU
<Tu>    /d032/d032/d047/d196    KATAKANA LETTER TU
<Du>    /d032/d032/d047/d197    KATAKANA LETTER DU
<Te>    /d032/d032/d047/d198    KATAKANA LETTER TE
<De>    /d032/d032/d047/d199    KATAKANA LETTER DE
<To>    /d032/d032/d047/d200    KATAKANA LETTER TO
<Do>    /d032/d032/d047/d201    KATAKANA LETTER DO
<Na>    /d032/d032/d047/d202    KATAKANA LETTER NA
<Ni>    /d032/d032/d047/d203    KATAKANA LETTER NI
<Nu>    /d032/d032/d047/d204    KATAKANA LETTER NU
<Ne>    /d032/d032/d047/d205    KATAKANA LETTER NE
<No>    /d032/d032/d047/d206    KATAKANA LETTER NO
<Ha>    /d032/d032/d047/d207    KATAKANA LETTER HA
<Ba>    /d032/d032/d047/d208    KATAKANA LETTER BA
<Pa>    /d032/d032/d047/d209    KATAKANA LETTER PA
<Hi>    /d032/d032/d047/d210    KATAKANA LETTER HI
<Bi>    /d032/d032/d047/d211    KATAKANA LETTER BI                1
<Pi>    /d032/d032/d047/d212    KATAKANA LETTER PI                1
<Hu>    /d032/d032/d047/d213    KATAKANA LETTER HU
<Bu>    /d032/d032/d047/d214    KATAKANA LETTER BU
<Pu>    /d032/d032/d047/d215    KATAKANA LETTER PU
<He>    /d032/d032/d047/d216    KATAKANA LETTER HE
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<Be>    /d032/d032/d047/d217    KATAKANA LETTER BE
<Pe>    /d032/d032/d047/d218    KATAKANA LETTER PE
<Ho>    /d032/d032/d047/d219    KATAKANA LETTER HO
<Bo>    /d032/d032/d047/d220    KATAKANA LETTER BO
<Po>    /d032/d032/d047/d221    KATAKANA LETTER PO
<Ma>    /d032/d032/d047/d222    KATAKANA LETTER MA
<Mi>    /d032/d032/d047/d223    KATAKANA LETTER MI
<Mu>    /d032/d032/d047/d224    KATAKANA LETTER MU
<Me>    /d032/d032/d047/d225    KATAKANA LETTER ME
<Mo>    /d032/d032/d047/d226    KATAKANA LETTER MO
<YA>    /d032/d032/d047/d227    KATAKANA LETTER SMALL YA
<Ya>    /d032/d032/d047/d228    KATAKANA LETTER YA
<YU>    /d032/d032/d047/d229    KATAKANA LETTER SMALL YU
<Yu>    /d032/d032/d047/d230    KATAKANA LETTER YU
<YO>    /d032/d032/d047/d231    KATAKANA LETTER SMALL YO
<Yo>    /d032/d032/d047/d232    KATAKANA LETTER YO
<Ra>    /d032/d032/d047/d233    KATAKANA LETTER RA
<Ri>    /d032/d032/d047/d234    KATAKANA LETTER RI
<Ru>    /d032/d032/d047/d235    KATAKANA LETTER RU
<Re>    /d032/d032/d047/d236    KATAKANA LETTER RE
<Ro>    /d032/d032/d047/d237    KATAKANA LETTER RO
<WA>    /d032/d032/d047/d238    KATAKANA LETTER SMALL WA
<Wa>    /d032/d032/d047/d239    KATAKANA LETTER WA
<Wi>    /d032/d032/d047/d240    KATAKANA LETTER WI
<We>    /d032/d032/d047/d241    KATAKANA LETTER WE
<Wo>    /d032/d032/d047/d242    KATAKANA LETTER WO
<N6>    /d032/d032/d047/d243    KATAKANA LETTER N
<Vu>    /d032/d032/d047/d244    KATAKANA LETTER VU
<KA>    /d032/d032/d047/d245    KATAKANA LETTER SMALL KA
<KE>    /d032/d032/d047/d246    KATAKANA LETTER SMALL KE
<-6>    /d032/d032/d047/d252    HIRAGANA-KATAKANA PROLONGED SOUND MARK
<*6>    /d032/d032/d047/d253    KATAKANA ITERATION MARK
<+6>    /d032/d032/d047/d254    KATAKANA VOICED ITERATION MARK
<ff>    /d032/d032/d060/d040    LATIN SMALL LIGATURE FF
<fi>    /d032/d032/d060/d041    LATIN SMALL LIGATURE FI
<fl>    /d032/d032/d060/d042    LATIN SMALL LIGATURE FL
<ft>    /d032/d032/d060/d045    LATIN SMALL LIGATURE FT
<st>    /d032/d032/d060/d046    LATIN SMALL LIGATURE ST
<Iu>    /d032/d032/d060/d048    INTEGRAL SIGN UPPER PART
<Il>    /d032/d032/d060/d049    INTEGRAL SIGN LOWER PART
<NU>    /d000/d128/d128/d128    NULL (NUL)                                  1
<SH>    /d001/d128/d128/d128    START OF HEADING (SOH)                      1
<SX>    /d002/d128/d128/d128    START OF TEXT (STX)                         1
<EX>    /d003/d128/d128/d128    END OF TEXT (ETX)                           1
<ET>    /d004/d128/d128/d128    END OF TRANSMISSION (EOT)                   1
<EQ>    /d005/d128/d128/d128    ENQUIRY (ENQ)                               1
<AK>    /d006/d128/d128/d128    ACKNOWLEDGE (ACK)                           1
<BL>    /d007/d128/d128/d128    BELL (BEL)                                  1
<BS>    /d008/d128/d128/d128    BACKSPACE (BS)                              1
<HT>    /d009/d128/d128/d128    CHARACTER TABULATION (HT)                   1
<LF>    /d010/d128/d128/d128    LINE FEED (LF)                              1
<VT>    /d011/d128/d128/d128    LINE TABULATION (VT)                        1
<FF>    /d012/d128/d128/d128    FORM FEED (FF)                              1
<CR>    /d013/d128/d128/d128    CARRIAGE RETURN (CR)                        1
<SO>    /d014/d128/d128/d128    SHIFT OUT (SO)                              1
<SI>    /d015/d128/d128/d128    SHIFT IN (SI)                               1
<DL>    /d016/d128/d128/d128    DATALINK ESCAPE (DLE)                       1
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<D1>    /d017/d128/d128/d128    DEVICE CONTROL ONE (DC1)                              1
<D2>    /d018/d128/d128/d128    DEVICE CONTROL TWO (DC2)                              1
<D3>    /d019/d128/d128/d128    DEVICE CONTROL THREE (DC3)                            1
<D4>    /d020/d128/d128/d128    DEVICE CONTROL FOUR (DC4)                             1
<NK>    /d021/d128/d128/d128    NEGATIVE ACKNOWLEDGE (NAK)                            1
<SY>    /d022/d128/d128/d128    SYNCHRONOUS IDLE (SYN)                                1
<EB>    /d023/d128/d128/d128    END OF TRANSMISSION BLOCK (ETB)                       1
<CN>    /d024/d128/d128/d128    CANCEL (CAN)                                          1
<EM>    /d025/d128/d128/d128    END OF MEDIUM (EM)                                    1
<SB>    /d026/d128/d128/d128    SUBSTITUTE (SUB)                                      1
<EC>    /d027/d128/d128/d128    ESCAPE (ESC)                                          1
<FS>    /d028/d128/d128/d128    FILE SEPARATOR (IS4)                                  1
<GS>    /d029/d128/d128/d128    GROUP SEPARATOR (IS3)                                 1
<RS>    /d030/d128/d128/d128    RECORD SEPARATOR (IS2)                                1
<US>    /d031/d128/d128/d128    UNIT SEPARATOR (IS1)                                  1
<DT>    /d127/d128/d128/d128    DELETE (DEL)                                          1
<PA>    /d128/d128/d128/d128    PADDING CHARACTER (PAD)                               1
<HO>    /d129/d128/d128/d128    HIGH OCTET PRESET (HOP)                               1
<BH>    /d130/d128/d128/d128    BREAK PERMITTED HERE (BPH)                            1
<NH>    /d131/d128/d128/d128    NO BREAK HERE (NBH)                                   1
<IN>    /d132/d128/d128/d128    INDEX (IND)                                           1
<NL>    /d133/d128/d128/d128    NEXT LINE (NEL)                                       1
<SA>    /d134/d128/d128/d128    START OF SELECTED AREA (SSA)                          1
<ES>    /d135/d128/d128/d128    END OF SELECTED AREA (ESA)                            1
<HS>    /d136/d128/d128/d128    CHARACTER TABULATION SET (HTS)                        1
<HJ>    /d137/d128/d128/d128    CHARACTER TABULATION WITH JUSTIFICATION (HTJ)         1
<VS>    /d138/d128/d128/d128    LINE TABULATION SET (VTS)                             1
<PD>    /d139/d128/d128/d128    PARTIAL LINE FORWARD (PLD)                            1
<PU>    /d140/d128/d128/d128    PARTIAL LINE BACKWARD (PLU)                           1
<RI>    /d141/d128/d128/d128    REVERSE LINE FEED (RI)                                1
<S2>    /d142/d128/d128/d128    SINGLE-SHIFT TWO (SS2)                                1
<S3>    /d143/d128/d128/d128    SINGLE-SHIFT THREE (SS3)                              1
<DC>    /d144/d128/d128/d128    DEVICE CONTROL STRING (DCS)                           1
<P1>    /d145/d128/d128/d128    PRIVATE USE ONE (PU1)                                 1
<P2>    /d146/d128/d128/d128    PRIVATE USE TWO (PU2)                                 1
<TS>    /d147/d128/d128/d128    SET TRANSMIT STATE (STS)                              1
<CC>    /d148/d128/d128/d128    CANCEL CHARACTER (CCH)                                1
<MW>    /d149/d128/d128/d128    MESSAGE WAITING (MW)                                  1
<SG>    /d150/d128/d128/d128    START OF GUARDED AREA (SPA)                           1
<EG>    /d151/d128/d128/d128    END OF GUARDED AREA (EPA)                             1
<SS>    /d152/d128/d128/d128    START OF STRING (SOS)                                 1
<GC>    /d153/d128/d128/d128    SINGLE GRAPHIC CHARACTER INTRODUCER (SGCI)            1
<SC>    /d154/d128/d128/d128    SINGLE CHARACTER INTRODUCER (SCI)                     1
<CI>    /d155/d128/d128/d128    CONTROL SEQUENCE INTRODUCER (CSI)                     1
<ST>    /d156/d128/d128/d128    STRING TERMINATOR (ST)                                1
<OC>    /d157/d128/d128/d128    OPERATING SYSTEM COMMAND (OSC)                        1
<PM>    /d158/d128/d128/d128    PRIVACY MESSAGE (PM)                                  1
<AC>    /d159/d128/d128/d128    APPLICATION PROGRAM COMMAND (APC)                     1
<__>    /d032/d032/d052/d032    indicates unfinished
<"!>    /d032/d032/d052/d033    NON-SPACING GRAVE ACCENT (ISO IR 70 193)
<"'>    /d032/d032/d052/d034    NON-SPACING ACUTE ACCENT (ISO IR 70 194)
<"/>>   /d032/d032/d052/d035    NON-SPACING CIRCUMFLEX ACCENT (ISO IR 70 195)
<"?>    /d032/d032/d052/d036    NON-SPACING TILDE (ISO IR 70 196)
<"->    /d032/d032/d052/d037    NON-SPACING MACRON (ISO IR 70 197)
<"(>    /d032/d032/d052/d038    NON-SPACING BREVE (ISO IR 70 198)
<".>    /d032/d032/d052/d039    NON-SPACING DOT ABOVE (ISO IR 70 199)
<":>    /d032/d032/d052/d040    NON-SPACING DIAERESIS (ISO IR 70 200)
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<"//>   /d032/d032/d052/d041    NON-SPACING SOLIDUS (ISO IR 99 201)
<"0>    /d032/d032/d052/d042    NON-SPACING RING ABOVE (ISO IR 70 202)
<",>    /d032/d032/d052/d043    NON-SPACING CEDILLA (ISO IR 70 203)
<"_>    /d032/d032/d052/d044    NON-SPACING UNDERLINE (ISO IR 99 216)
<"">    /d032/d032/d052/d045    NON-SPACING DOUBLE ACCUTE ACCENT (ISO IR 70 205)
<"<>    /d032/d032/d052/d046    NON-SPACING CARON (ISO IR 70 207)
<";>    /d032/d032/d052/d047    NON-SPACING OGONEK (ISO IR 53 208)
<"=>    /d032/d032/d052/d048    NON-SPACING DOUBLE UNDERLINE (ISO IR 53 217)
<"1>    /d032/d032/d052/d049    NON-SPACING DIAERESIS WITH ACCENT
#                               (ISO IR 70 192)
<"2>    /d032/d032/d052/d050    NON-SPACING UMLAUT (ISO 5426 201)
<Fd>    /d032/d032/d052/d051    FILLED FORWARD DIAGONAL
#                               (ANSI X3.110-1983 218)
<Bd>    /d032/d032/d052/d052    FILLED BACKWARD DIAGONAL
#                               (ANSI X3.110-1983 219)
<Fl>    /d032/d032/d052/d053    Dutch guilder sign (IBM CP 437 159)
<Li>    /d032/d032/d052/d054    Italian Lira sign (HP ROMAN 8 175)
<//f>   /d032/d032/d052/d055    VULGAR FRACTION BAR (MacIntosh 218)
<0s>    /d032/d032/d052/d056    SUBSCRIPT ZERO (ISO IR 50 096)
<1s>    /d032/d032/d052/d057    SUBSCRIPT ONE (ISO IR 50 097)
<2s>    /d032/d032/d052/d058    SUBSCRIPT TWO (ISO IR 50 098)
<3s>    /d032/d032/d052/d059    SUBSCRIPT THREE (ISO IR 50 099)
<4s>    /d032/d032/d052/d060    SUBSCRIPT FOUR (ISO IR 50 100)
<5s>    /d032/d032/d052/d061    SUBSCRIPT FIVE (ISO IR 50 101)
<6s>    /d032/d032/d052/d062    SUBSCRIPT SIX (ISO IR 50 102)
<7s>    /d032/d032/d052/d063    SUBSCRIPT SEVEN (ISO IR 50 103)
<8s>    /d032/d032/d052/d064    SUBSCRIPT EIGHT (ISO IR 50 104)
<9s>    /d032/d032/d052/d065    SUBSCRIPT NINE (ISO IR 50 105)
<0S>    /d032/d032/d052/d066    SUPERSCRIPT ZERO (ISO IR 50 112)
<4S>    /d032/d032/d052/d067    SUPERSCRIPT FOUR (ISO IR 50 116)
<5S>    /d032/d032/d052/d068    SUPERSCRIPT FIVE (ISO IR 50 117)
<6S>    /d032/d032/d052/d069    SUPERSCRIPT SIX (ISO IR 50 118)
<7S>    /d032/d032/d052/d070    SUPERSCRIPT SEVEN (ISO IR 50 119)
<8S>    /d032/d032/d052/d071    SUPERSCRIPT EIGHT (ISO IR 50 120)
<9S>    /d032/d032/d052/d072    SUPERSCRIPT NINE (ISO IR 50 121)
<+S>    /d032/d032/d052/d073    SUPERSCRIPT PLUS (ISO IR 50 106)
<-S>    /d032/d032/d052/d074    SUPERSCRIPT MINUS (ISO IR 50 107)
<1h>    /d032/d032/d052/d075    ABSTRACT SYMBOL H ONE (HOOK)
#                               (JIS C 6229-1984 060)
<2h>    /d032/d032/d052/d076    ABSTRACT SYMBOL H TWO (FORK)
#                               (JIS C 6229-1984 093)
<3h>    /d032/d032/d052/d077    ABSTRACT SYMBOL H THREE (CHAIR)
#                               (JIS C 6229-1984 062)
<4h>    /d032/d032/d052/d078    ABSTRACT SYMBOL H FOUR (LONG VERTICAL MARK)
#                               (JIS C 6229-1984 125)
<1j>    /d032/d032/d052/d079    SYMBOL ONE (ISO 2033-1983 058)
<2j>    /d032/d032/d052/d080    SYMBOL TWO (ISO 2033-1983 059)
<3j>    /d032/d032/d052/d081    SYMBOL THREE (ISO 2033-1983 060)
<4j>    /d032/d032/d052/d082    SYMBOL FOUR (ISO 2033-1983 061)
<UA>    /d032/d032/d052/d083    Unit space A (ISO IR 8-1 064)
<UB>    /d032/d032/d052/d084    Unit space B (ISO IR 8-1 096)
<yf>    /d032/d032/d052/d085    ARABIC LETTER YEH FINAL (CODAR U 090)
<yr>    /d032/d032/d052/d086    OLD NORSE YR (DIN 31624 251)
<.6>    /d032/d032/d052/d087    KATAKANA FULL STOP (JIS C 6220 033)
<<6>    /d032/d032/d052/d088    KATAKANA OPENING BRACKET (JIS C 6220 034)
</>6>   /d032/d032/d052/d089    KATAKANA CLOSING BRACKET (JIS C 6220 035)
<,6>    /d032/d032/d052/d090    KATAKANA COMMA (JIS C 6220 036)
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<&6>    /d032/d032/d052/d091    KATAKANA CONJUNCTION SYMBOL (JIS C 6220 037)
<(S>    /d032/d032/d052/d092    LEFT PARENTHESIS SUPERSCRIPT
#                               (CSA Z243.4-1985-gr 168)
<)S>    /d032/d032/d052/d093    RIGHT PARENTHESIS SUPERSCRIPT
#                               (CSA Z243.4-1985-gr 169)
END CHARMAP
```

F.5.2 `ISO_8859-1` Charmap

```
<escape_char> /
<mb_cur_max> 1
CHARMAP
<NUL>                   /d000 NULL (NUL)                                    1
<SOH>                   /d001 START OF HEADING (SOH)
<STX>                   /d002 START OF TEXT (STX)
<ETX>                   /d003 END OF TEXT (ETX)
<EOT>                   /d004 END OF TRANSMISSION (EOT)
<ENQ>                   /d005 ENQUIRY (ENQ)
<ACK>                   /d006 ACKNOWLEDGE (ACK)
<alert>                 /d007 BELL (BEL)
<BEL>                   /d007 BELL (BEL)
<backspace>             /d008 BACKSPACE (BS)
<tab>                   /d009 CHARACTER TABULATION (HT)
<newline>               /d010 LINE FEED (LF)
<vertical-tab>          /d011 LINE TABULATION (VT)
<form-feed>             /d012 FORM FEED (FF)
<carriage-return>       /d013 CARRIAGE RETURN (CR)
<DLE>                   /d016 DATALINK ESCAPE (DLE)
<DC1>                   /d017 DEVICE CONTROL ONE (DC1)
<DC2>                   /d018 DEVICE CONTROL TWO (DC2)
<DC3>                   /d019 DEVICE CONTROL THREE (DC3)
<DC4>                   /d020 DEVICE CONTROL FOUR (DC4)
<NAK>                   /d021 NEGATIVE ACKNOWLEDGE (NAK)
<SYN>                   /d022 SYNCHRONOUS IDLE (SYN)
<ETB>                   /d023 END OF TRANSMISSION BLOCK (ETB)
<CAN>                   /d024 CANCEL (CAN)
<SUB>                   /d026 SUBSTITUTE (SUB)
<ESC>                   /d027 ESCAPE (ESC)
<IS4>                   /d028 FILE SEPARATOR (IS4)
<IS3>                   /d029 GROUP SEPARATOR (IS3)
<intro>                 /d029 GROUP SEPARATOR (IS3)
<IS2>                   /d030 RECORD SEPARATOR (IS2)
<IS1>                   /d031 UNIT SEPARATOR (IS1)
<DEL>                   /d127 DELETE (DEL)                                  1
<space>                 /d032   SPACE
<exclamation-mark>      /d033   EXCLAMATION MARK
<quotation-mark>        /d034   QUOTATION MARK
<number-sign>           /d035   NUMBER SIGN
<dollar-sign>           /d036   DOLLAR SIGN
<percent-sign>          /d037   PERCENT SIGN
<ampersand>             /d038   AMPERSAND
<apostrophe>            /d039   APOSTROPHE
<left-parenthesis>      /d040   LEFT PARENTHESIS
<right-parenthesis>     /d041   RIGHT PARENTHESIS
<asterisk>              /d042   ASTERISK
<plus-sign>             /d043   PLUS SIGN
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<comma>                 /d044   COMMA
<hyphen>                /d045   HYPHEN-MINUS
<hyphen-minus>          /d045   HYPHEN-MINUS
<period>                /d046   FULL STOP
<full-stop>             /d046   FULL STOP
<slash>                 /d047   SOLIDUS
<solidus>               /d047   SOLIDUS
<zero>                  /d048   DIGIT ZERO
<one>                   /d049   DIGIT ONE
<two>                   /d050   DIGIT TWO
<three>                 /d051   DIGIT THREE
<four>                  /d052   DIGIT FOUR
<five>                  /d053   DIGIT FIVE
<six>                   /d054   DIGIT SIX
<seven>                 /d055   DIGIT SEVEN
<eight>                 /d056   DIGIT EIGHT
<nine>                  /d057   DIGIT NINE
<colon>                 /d058   COLON
<semicolon>             /d059   SEMICOLON
<less-than-sign>        /d060   LESS-THAN SIGN
<equals-sign>           /d061   EQUALS SIGN
<greater-than-sign>     /d062   GREATER-THAN SIGN
<question-mark>         /d063   QUESTION MARK
<commercial-at>         /d064   COMMERCIAL AT
<left-square-bracket>   /d091   LEFT SQUARE BRACKET
<reverse-solidus>       /d092   REVERSE SOLIDUS
<backslash>             /d092   REVERSE SOLIDUS
<right-square-bracket>  /d093   RIGHT SQUARE BRACKET
<circumflex-accent>     /d094   CIRCUMFLEX ACCENT
<low-line>              /d095   LOW LINE
<underscore>            /d095   LOW LINE
<grave-accent>          /d096   GRAVE ACCENT
<left-curly-bracket>    /d123   LEFT CURLY BRACKET
<vertical-line>         /d124   VERTICAL LINE
<right-curly-bracket>   /d125   RIGHT CURLY BRACKET
<tilde>                 /d126   TILDE
<SP>    /d032   SPACE
<!>     /d033   EXCLAMATION MARK
<">     /d034   QUOTATION MARK
<Nb>    /d035   NUMBER SIGN
<DO>    /d036   DOLLAR SIGN
<%>     /d037   PERCENT SIGN
<&>     /d038   AMPERSAND
<'>     /d039   APOSTROPHE
<(>     /d040   LEFT PARENTHESIS
<)>     /d041   RIGHT PARENTHESIS
<*>     /d042   ASTERISK
<+>     /d043   PLUS SIGN
<,>     /d044   COMMA
<->     /d045   HYPHEN-MINUS
<.>     /d046   FULL STOP
<//>    /d047   SOLIDUS
<0>     /d048   DIGIT ZERO
<1>     /d049   DIGIT ONE
<2>     /d050   DIGIT TWO
<3>     /d051   DIGIT THREE
<4>     /d052   DIGIT FOUR
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<5>     /d053   DIGIT FIVE
<6>     /d054   DIGIT SIX
<7>     /d055   DIGIT SEVEN
<8>     /d056   DIGIT EIGHT
<9>     /d057   DIGIT NINE
<:>     /d058   COLON
<;>     /d059   SEMICOLON
<<>     /d060   LESS-THAN SIGN
<=>     /d061   EQUALS SIGN
</>>    /d062   GREATER-THAN SIGN
<?>     /d063   QUESTION MARK
<At>    /d064   COMMERCIAL AT
<A>     /d065   LATIN CAPITAL LETTER A
<B>     /d066   LATIN CAPITAL LETTER B
<C>     /d067   LATIN CAPITAL LETTER C
<D>     /d068   LATIN CAPITAL LETTER D
<E>     /d069   LATIN CAPITAL LETTER E
<F>     /d070   LATIN CAPITAL LETTER F
<G>     /d071   LATIN CAPITAL LETTER G
<H>     /d072   LATIN CAPITAL LETTER H
<I>     /d073   LATIN CAPITAL LETTER I
<J>     /d074   LATIN CAPITAL LETTER J
<K>     /d075   LATIN CAPITAL LETTER K
<L>     /d076   LATIN CAPITAL LETTER L
<M>     /d077   LATIN CAPITAL LETTER M
<N>     /d078   LATIN CAPITAL LETTER N
<O>     /d079   LATIN CAPITAL LETTER O
<P>     /d080   LATIN CAPITAL LETTER P
<Q>     /d081   LATIN CAPITAL LETTER Q
<R>     /d082   LATIN CAPITAL LETTER R
<S>     /d083   LATIN CAPITAL LETTER S
<T>     /d084   LATIN CAPITAL LETTER T
<U>     /d085   LATIN CAPITAL LETTER U
<V>     /d086   LATIN CAPITAL LETTER V
<W>     /d087   LATIN CAPITAL LETTER W
<X>     /d088   LATIN CAPITAL LETTER X
<Y>     /d089   LATIN CAPITAL LETTER Y
<Z>     /d090   LATIN CAPITAL LETTER Z
<<(>    /d091   LEFT SQUARE BRACKET
<////>  /d092   REVERSE SOLIDUS
<)/>>   /d093   RIGHT SQUARE BRACKET
<'/>>   /d094   CIRCUMFLEX ACCENT
<_>     /d095   LOW LINE
<'!>    /d096   GRAVE ACCENT
<a>     /d097   LATIN SMALL LETTER A
<b>     /d098   LATIN SMALL LETTER B
<c>     /d099   LATIN SMALL LETTER C
<d>     /d100   LATIN SMALL LETTER D
<e>     /d101   LATIN SMALL LETTER E
<f>     /d102   LATIN SMALL LETTER F
<g>     /d103   LATIN SMALL LETTER G
<h>     /d104   LATIN SMALL LETTER H
<i>     /d105   LATIN SMALL LETTER I
<j>     /d106   LATIN SMALL LETTER J
<k>     /d107   LATIN SMALL LETTER K
<l>     /d108   LATIN SMALL LETTER L
<m>     /d109   LATIN SMALL LETTER M
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<n>     /d110   LATIN SMALL LETTER N
<o>     /d111   LATIN SMALL LETTER O
<p>     /d112   LATIN SMALL LETTER P
<q>     /d113   LATIN SMALL LETTER Q
<r>     /d114   LATIN SMALL LETTER R
<s>     /d115   LATIN SMALL LETTER S
<t>     /d116   LATIN SMALL LETTER T
<u>     /d117   LATIN SMALL LETTER U
<v>     /d118   LATIN SMALL LETTER V
<w>     /d119   LATIN SMALL LETTER W
<x>     /d120   LATIN SMALL LETTER X
<y>     /d121   LATIN SMALL LETTER Y
<z>     /d122   LATIN SMALL LETTER Z
<(!>    /d123   LEFT CURLY BRACKET
<!!>    /d124   VERTICAL LINE
<!)>    /d125   RIGHT CURLY BRACKET
<'?>    /d126   TILDE
<NS>    /d160   NO-BREAK SPACE
<!I>    /d161   INVERTED EXCLAMATION MARK
<Ct>    /d162   CENT SIGN
<Pd>    /d163   POUND SIGN
<Cu>    /d164   CURRENCY SIGN
<Ye>    /d165   YEN SIGN
<BB>    /d166   BROKEN BAR
<SE>    /d167   SECTION SIGN
<':>    /d168   DIAERESIS
<Co>    /d169   COPYRIGHT SIGN
<-a>    /d170   FEMININE ORDINAL INDICATOR
<<<>    /d171   LEFT POINTING DOUBLE ANGLE QUOTATION MARK
<NO>    /d172   NOT SIGN
<-->    /d173   SOFT HYPHEN
<Rg>    /d174   REGISTERED SIGN
<'->    /d175   MACRON
<DG>    /d176   DEGREE SIGN
<+->    /d177   PLUS-MINUS SIGN
<2S>    /d178   SUPERSCRIPT TWO
<3S>    /d179   SUPERSCRIPT THREE
<''>    /d180   ACUTE ACCENT
<My>    /d181   MICRO SIGN
<PI>    /d182   PILCROW SIGN
<.M>    /d183   MIDDLE DOT
<',>    /d184   CEDILLA
<1S>    /d185   SUPERSCRIPT ONE
<-o>    /d186   MASCULINE ORDINAL INDICATOR
</>>>>  /d187   RIGHT POINTING DOUBLE ANGLE QUOTATION MARK                1
<14>    /d188   VULGAR FRACTION ONE QUARTER
<12>    /d189   VULGAR FRACTION ONE HALF
<34>    /d190   VULGAR FRACTION THREE QUARTERS
<?I>    /d191   INVERTED QUESTION MARK
<A!>    /d192   LATIN CAPITAL LETTER A WITH GRAVE
<A'>    /d193   LATIN CAPITAL LETTER A WITH ACUTE
<A/>>   /d194   LATIN CAPITAL LETTER A WITH CIRCUMFLEX
<A?>    /d195   LATIN CAPITAL LETTER A WITH TILDE
<A:>    /d196   LATIN CAPITAL LETTER A WITH DIAERESIS
<AA>    /d197   LATIN CAPITAL LETTER A WITH RING ABOVE
<AE>    /d198   LATIN CAPITAL LETTER AE
<C,>    /d199   LATIN CAPITAL LETTER C WITH CEDILLA
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
3712  <E!>    /d200   LATIN CAPITAL LETTER E WITH GRAVE
3713  <E'>    /d201   LATIN CAPITAL LETTER E WITH ACUTE
3714  <E/>>   /d202   LATIN CAPITAL LETTER E WITH CIRCUMFLEX
3715  <E:>    /d203   LATIN CAPITAL LETTER E WITH DIAERESIS
3716  <I!>    /d204   LATIN CAPITAL LETTER I WITH GRAVE
3717  <I'>    /d205   LATIN CAPITAL LETTER I WITH ACUTE
3718  <I/>>   /d206   LATIN CAPITAL LETTER I WITH CIRCUMFLEX
3719  <I:>    /d207   LATIN CAPITAL LETTER I WITH DIAERESIS
3720  <D->    /d208   LATIN CAPITAL LETTER ETH (Icelandic)
3721  <N?>    /d209   LATIN CAPITAL LETTER N WITH TILDE
3722  <O!>    /d210   LATIN CAPITAL LETTER O WITH GRAVE
3723  <O'>    /d211   LATIN CAPITAL LETTER O WITH ACUTE
3724  <O/>>   /d212   LATIN CAPITAL LETTER O WITH CIRCUMFLEX
3725  <O?>    /d213   LATIN CAPITAL LETTER O WITH TILDE
3726  <O:>    /d214   LATIN CAPITAL LETTER O WITH DIAERESIS
3727  <*X>    /d215   MULTIPLICATION SIGN
3728  <O//>   /d216   LATIN CAPITAL LETTER O WITH STROKE
3729  <U!>    /d217   LATIN CAPITAL LETTER U WITH GRAVE
3730  <U'>    /d218   LATIN CAPITAL LETTER U WITH ACUTE
3731  <U/>>   /d219   LATIN CAPITAL LETTER U WITH CIRCUMFLEX
3732  <U:>    /d220   LATIN CAPITAL LETTER U WITH DIAERESIS
3733  <Y'>    /d221   LATIN CAPITAL LETTER Y WITH ACUTE
3734  <TH>    /d222   LATIN CAPITAL LETTER THORN (Icelandic)
3735  <ss>    /d223   LATIN SMALL LETTER SHARP S (German)
3736  <a!>    /d224   LATIN SMALL LETTER A WITH GRAVE
3737  <a'>    /d225   LATIN SMALL LETTER A WITH ACUTE
3738  <a/>>   /d226   LATIN SMALL LETTER A WITH CIRCUMFLEX
3739  <a?>    /d227   LATIN SMALL LETTER A WITH TILDE
3740  <a:>    /d228   LATIN SMALL LETTER A WITH DIAERESIS
3741  <aa>    /d229   LATIN SMALL LETTER A WITH RING ABOVE
3742  <ae>    /d230   LATIN SMALL LETTER AE
3743  <c,>    /d231   LATIN SMALL LETTER C WITH CEDILLA
3744  <e!>    /d232   LATIN SMALL LETTER E WITH GRAVE
3745  <e'>    /d233   LATIN SMALL LETTER E WITH ACUTE
3746  <e/>>   /d234   LATIN SMALL LETTER E WITH CIRCUMFLEX
3747  <e:>    /d235   LATIN SMALL LETTER E WITH DIAERESIS
3748  <i!>    /d236   LATIN SMALL LETTER I WITH GRAVE
3749  <i'>    /d237   LATIN SMALL LETTER I WITH ACUTE
3750  <i/>>   /d238   LATIN SMALL LETTER I WITH CIRCUMFLEX
3751  <i:>    /d239   LATIN SMALL LETTER I WITH DIAERESIS
3752  <d->    /d240   LATIN SMALL LETTER ETH (Icelandic)
3753  <n?>    /d241   LATIN SMALL LETTER N WITH TILDE
3754  <o!>    /d242   LATIN SMALL LETTER O WITH GRAVE
3755  <o'>    /d243   LATIN SMALL LETTER O WITH ACUTE
3756  <o/>>   /d244   LATIN SMALL LETTER O WITH CIRCUMFLEX
3757  <o?>    /d245   LATIN SMALL LETTER O WITH TILDE
3758  <o:>    /d246   LATIN SMALL LETTER O WITH DIAERESIS
3759  <-:>    /d247   DIVISION SIGN
3760  <o//>   /d248   LATIN SMALL LETTER O WITH STROKE
3761  <u!>    /d249   LATIN SMALL LETTER U WITH GRAVE
3762  <u'>    /d250   LATIN SMALL LETTER U WITH ACUTE
3763  <u/>>   /d251   LATIN SMALL LETTER U WITH CIRCUMFLEX
3764  <u:>    /d252   LATIN SMALL LETTER U WITH DIAERESIS
3765  <y'>    /d253   LATIN SMALL LETTER Y WITH ACUTE
3766  <th>    /d254   LATIN SMALL LETTER THORN (Icelandic)
3767  <y:>    /d255   LATIN SMALL LETTER Y WITH DIAERESIS
3768  <NU>    /d000   NULL (NUL)
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<SH>    /d001   START OF HEADING (SOH)
<SX>    /d002   START OF TEXT (STX)
<EX>    /d003   END OF TEXT (ETX)
<ET>    /d004   END OF TRANSMISSION (EOT)
<EQ>    /d005   ENQUIRY (ENQ)
<AK>    /d006   ACKNOWLEDGE (ACK)
<BL>    /d007   BELL (BEL)
<BS>    /d008   BACKSPACE (BS)
<HT>    /d009   CHARACTER TABULATION (HT)
<LF>    /d010   LINE FEED (LF)
<VT>    /d011   LINE TABULATION (VT)
<FF>    /d012   FORM FEED (FF)
<CR>    /d013   CARRIAGE RETURN (CR)
<SO>    /d014   SHIFT OUT (SO)
<SI>    /d015   SHIFT IN (SI)
<DL>    /d016   DATALINK ESCAPE (DLE)
<D1>    /d017   DEVICE CONTROL ONE (DC1)
<D2>    /d018   DEVICE CONTROL TWO (DC2)
<D3>    /d019   DEVICE CONTROL THREE (DC3)
<D4>    /d020   DEVICE CONTROL FOUR (DC4)
<NK>    /d021   NEGATIVE ACKNOWLEDGE (NAK)
<SY>    /d022   SYNCHRONOUS IDLE (SYN)
<EB>    /d023   END OF TRANSMISSION BLOCK (ETB)
<CN>    /d024   CANCEL (CAN)
<EM>    /d025   END OF MEDIUM (EM)
<SB>    /d026   SUBSTITUTE (SUB)
<EC>    /d027   ESCAPE (ESC)
<FS>    /d028   FILE SEPARATOR (IS4)
<GS>    /d029   GROUP SEPARATOR (IS3)
<RS>    /d030   RECORD SEPARATOR (IS2)
<US>    /d031   UNIT SEPARATOR (IS1)
<DT>    /d127   DELETE (DEL)
<PA>    /d128   PADDING CHARACTER (PAD)
<HO>    /d129   HIGH OCTET PRESET (HOP)
<BH>    /d130   BREAK PERMITTED HERE (BPH)
<NH>    /d131   NO BREAK HERE (NBH)
<IN>    /d132   INDEX (IND)
<NL>    /d133   NEXT LINE (NEL)
<SA>    /d134   START OF SELECTED AREA (SSA)
<ES>    /d135   END OF SELECTED AREA (ESA)
<HS>    /d136   CHARACTER TABULATION SET (HTS)
<HJ>    /d137   CHARACTER TABULATION WITH JUSTIFICATION (HTJ)
<VS>    /d138   LINE TABULATION SET (VTS)
<PD>    /d139   PARTIAL LINE FORWARD (PLD)
<PU>    /d140   PARTIAL LINE BACKWARD (PLU)
<RI>    /d141   REVERSE LINE FEED (RI)
<S2>    /d142   SINGLE-SHIFT TWO (SS2)
<S3>    /d143   SINGLE-SHIFT THREE (SS3)
<DC>    /d144   DEVICE CONTROL STRING (DCS)
<P1>    /d145   PRIVATE USE ONE (PU1)
<P2>    /d146   PRIVATE USE TWO (PU2)
<TS>    /d147   SET TRANSMIT STATE (STS)
<CC>    /d148   CANCEL CHARACTER (CCH)
<MW>    /d149   MESSAGE WAITING (MW)
<SG>    /d150   START OF GUARDED AREA (SPA)
<EG>    /d151   END OF GUARDED AREA (EPA)
<SS>    /d152   START OF STRING (SOS)
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

```
<GC>    /d153   SINGLE GRAPHIC CHARACTER INTRODUCER (SGCI)
<SC>    /d154   SINGLE CHARACTER INTRODUCER (SCI)
<CI>    /d155   CONTROL SEQUENCE INTRODUCER (CSI)
<ST>    /d156   STRING TERMINATOR (ST)
<OC>    /d157   OPERATING SYSTEM COMMAND (OSC)
<PM>    /d158   PRIVACY MESSAGE (PM)
<AC>    /d159   APPLICATION PROGRAM COMMAND (APC)
END CHARMAP
```

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.

Annex G
(inform ative)

Balloting Instructions

This annex will not appear in the final standard. It is included in the draft to provide instructions for balloting that cannot be separated easily from the main document, as a cover letter might.

If you have received a copy of this draft before October 1991 it is important that you read this annex, whether you are an official member of the P1003.2 Balloting Group or not; comments on this draft are welcomed from all interested technical experts. **Your ballot is due to the IEEE office by 21 October 1991. This is not the date to postmark it—it is the date of receipt.**

Summary of Draft 11.2 Instructions

This is the fifth ‘‘recirculation draft’’ of P1003.2. The recirculation procedure is described in this annex. For this recirculation, we are accepting objections against any normative changes that occurred from Draft 11.1 to Draft 11.2 and the contents of the Unresolved Objections List, provided as a separate document from the draft.

This is the first ballot in which the draft is available for online review; see the Editor’s Notes for details on accessing this information.

Send your ballot and/or comments to:

IEEE Standards Office
Computer Society Secretariat
ATTN: P1003.2 Ballot (Anna Kaczmarek)
P.O. Box 1331
445 Hoes Lane
Piscataway, NJ 08855-1331

It would also be very helpful if you sent us your ballot in machine-readable form. Your official ballot must be returned via mail to the IEEE office; if we receive only the e-mail or diskette version, that version will not count as an official document. However, the online version would be a great help to ballot resolution. We can accept e-mail to the following address:

`hlj@Posix.COM` or **`uunet!posix!hlj`**

Copyright © 1991 IEEE. All rights reserved.
This is an unapproved IEEE Standards Draft, subject to change.